

#####

<chess@chessgriffin.com>
#####: 43126

#####.

#####

2013#11#07 #####.

#####

(###) ## #####.

#####

1. ##### (###)	1
2. #####	2
3. #####	2
4. #####	3
5. #####	4
6. #####	5
7. #####	7
#####	7

1. ##### (###)

(#####
#####), #####® # #####®#####

```
#####
```

```
#####. ### ##### ##### ##### #####, #####  
##### ##### # ##### # ##### # #####—  
##### @.
```

```
##### ##### ##### ##### ##### #####  
(##### #####, ###) ### ##### #—  
#####. ##### #####: ###, ### #  
##### (#####). #####  
##### # #####, #####  
(##### #####, ###), ##### @  
#####. # ##### #—  
##### # #####, ##### @, ### @ #
```

```
##### # http://www.cups.org/.
```

2.

```
#### ##### # #####. #####—  
#### # #####, ##### root #—  
#####:
```

```
# cd /usr/ports/print/cups && make install clean
```

```
### #####, #####:
```


```
# pkg_add -r cups
```

```
##### # #####/  
##### # ##### #—  
## # #####. #####  
##### /usr/local/etc/cups.
```

3.

```
#####—  
#####. ### ##### # /etc/devfs.rules #  
##### #—  
##### #—  
##### cups:
```

```
[system=10]  
add path -'unlpt*' mode 0660 group cups  
add path -'ulpt*' mode 0660 group cups  
add path -'lpt*' mode 0660 group cups  
add path -'usb/X.Y.Z' mode 0660 group cups
```

 #####

```
##### X, Y # Z ##### ##### #####-
##### ##### #, ##### # ##### /dev/usb. #####
##### #####, ##### #####(8) # #-
##### ##### # ##### ##### #####-
##### ugenX.Y, ##### ##### #####-
##### # ##### /dev/usb.
```

```

cupsd_enable="YES"
devfs_system_ruleset="system"

```

[illegible]

application/octet-stream

```
# /etc/rc.d/devfs restart
# /usr/local/etc/rc.d/cupsd restart
```


#####

3

#####

#.#. ##### ###, # ##### ##### ##### ##### #####
(#####), ##### ##### ##### # ##### ##### #####-
###, ##### ## ##### ##### ##### # ##### ##### # #####-
###, ##### ##### ##### ##### ##### #, ##### ##### #-
#####.

#####, ## ##### ##

#####

5. #####

```
##### ##, ## ##### ## ## #####, ##### ##### # ##### #####-
## # ##, ##### ## # ## ##### ##### ## ##, ##### #####
##### # ##### ##, ### # ## ##### ##### #####, #####
##### ##### # ##### # #####, ## # ##### ## #####
## # #####.
```

5.1. #####® #####

```
## #####  #####  #####  #####  #####. #####  #####
#####  ##  #####, #####, #####  #  ##, ##  #####
#####  #####  #####  #####  #####  #####, #####  ##
#####  ##  ##. #  #####  #####, ##  #####  #####
#####  ##  ##  #####  #####  ##  #####  http://localhost:631 #  ##  #####
#####  #####  #####  #####. #####  #####  #####  #####
##  #####, #####  #####  #####  #####, #####  ##  #####
#####, ##  #####  ipp ##  http #  #####  ##  ##  #####  (##) #####
#####:
```

ipp://server-name-or-ip/printers/printername

`http://server-name-or-ip:631/printers/printername`

```
#####  
##### /usr/local/etc/cups/client.conf #####  
#####:
```

ServerName *server-ip*

```
# ##### server-ip ##### ## ## ##### ##### # #####.
```

```
#####  
#####
```

5.2. #####®#####

```
#####®, #####  
###. #####® ## # #####  
#####  
#####  
# #####  
## ##### (Add Printer) ##### (Network Printer), # #####  
#####
```

```
http://server-name-or-ip:631/printers/printername
```

```
### #####® ###  
#####  
#####3. #####
```

6. ##### #

```
##### # #####  
##### (8) (#####). #####  
#####  
##### cups. #####  
#####  
#####  
#####  
##### /usr/local/etc/cups/cupsd.conf # #####  
#####  
##### /usr/local/etc/cups/cupsd.conf. #####  
##### cupsd.conf #####  
#####  
#####
```

```
# Log general information in error_log -- change -"info" to -"debug" for  
# troubleshooting...  
LogLevel info  
  
# Administrator user group...  
SystemGroup wheel  
  
# Listen for connections on Port 631.  
Port 631  
#Listen localhost:631  
Listen -/var/run/cups.sock  
  
# Show shared printers on the local network.  
Browsing On  
BrowseOrder allow,deny  
#BrowseAllow @LOCAL
```

```
BrowseAllow 192.168.1.* # change to local LAN settings
BrowseAddress 192.168.1.* # change to local LAN settings

# Default authentication type, when authentication is required...
DefaultAuthType Basic
DefaultEncryption Never # comment this line to allow encryption

# Allow access to the server from any machine on the LAN
<Location -/>
  Order allow,deny
  #Allow localhost
  Allow 192.168.1.* # change to local LAN settings
</Location>

# Allow access to the admin pages from any machine on the LAN
<Location -/admin>
  #Encryption Required
  Order allow,deny
  #Allow localhost
  Allow 192.168.1.* # change to local LAN settings
</Location>

# Allow access to configuration files from any machine on the LAN
<Location -/admin/conf>
  AuthType Basic
  Require user @SYSTEM
  Order allow,deny
  #Allow localhost
  Allow 192.168.1.* # change to local LAN settings
</Location>

# Set the default printer/job policies...
<Policy default>
  # Job-related operations must be done by the owner or an administrator...
  <Limit Send-Document Send-URI Hold-Job Release-Job Restart-Job Purge-Jobs \
Set-Job-Attributes Create-Job-Subscription Renew-Subscription Cancel-Subscription \
Get-Notifications Reprocess-Job Cancel-Current-Job Suspend-Current-Job Resume-Job \
CUPS-Move-Job>
    Require user @OWNER @SYSTEM
    Order deny,allow
  </Limit>

  # All administration operations require an administrator to authenticate...
  <Limit Pause-Printer Resume-Printer Set-Printer-Attributes Enable-Printer \
Disable-Printer Pause-Printer-After-Current-Job Hold-New-Jobs Release-Held-New-Jobs \
Deactivate-Printer Activate-Printer Restart-Printer Shutdown-Printer Startup-Printer \
Promote-Job Schedule-Job-After CUPS-Add-Printer CUPS-Delete-Printer CUPS-Add-Class \
CUPS-Delete-Class CUPS-Accept-Jobs CUPS-Reject-Jobs CUPS-Set-Default>
    AuthType Basic
    Require user @SYSTEM
    Order deny,allow
  </Limit>
```


#####

```
# Only the owner or an administrator can cancel or authenticate a job...
<Limit Cancel-Job CUPS-Authenticate-Job>
  Require user @OWNER @SYSTEM
  Order deny,allow
</Limit>

<Limit All>
  Order deny,allow
</Limit>
</Policy>
```

7.

/etc/make.conf, #####
####.

```
WITH_CUPS=YES
CUPS_OVERWRITE_BASE=YES
WITHOUT_LPR=YES
```


buildworld. #####
WITHOUT_LPR, #####
#####.

#####

####, 1

#####, 1

