

Package ‘spant’

March 28, 2025

Type Package

Title MR Spectroscopy Analysis Tools

Version 3.3.0

Date 2025-03-27

Description Tools for reading, visualising and processing Magnetic Resonance Spectroscopy data. The package includes methods for spectral fitting: Wilson (2021) <[DOI:10.1002/mrm.28385](https://doi.org/10.1002/mrm.28385)> and spectral alignment: Wilson (2018) <[DOI:10.1002/mrm.27605](https://doi.org/10.1002/mrm.27605)>.

BugReports <https://github.com/martin3141/spant/issues/>

License GPL-3

RoxygenNote 7.3.2

NeedsCompilation yes

Depends R (>= 4.1.0)

Imports abind, plyr, pracma, stringr, expm (>= 1.0-0), signal, minpack.lm, utils, graphics, grDevices, ptw, mmand, RNifti, RNiftyReg, fields, numDeriv, nloptr, irlba, jsonlite

Suggests viridisLite, shiny, ggplot2, miniUI, knitr, kableExtra, rmarkdown, testthat, ragg, doParallel, parallel, digest, readxl, fslr, car

VignetteBuilder knitr

Encoding UTF-8

Language en-GB

URL <https://spantdoc.wilsonlab.co.uk/>,
<https://martin3141.github.io/spant/>,
<https://github.com/martin3141/spant/>

Author Martin Wilson [cre, aut] (<<https://orcid.org/0000-0002-2089-3956>>),
Yong Wang [ctb],
John Muschelli [ctb]

Maintainer Martin Wilson <martin@pipegrep.co.uk>

Repository CRAN

Date/Publication 2025-03-28 10:40:04 UTC

Contents

spant-package	9
abfit_opts	10
abfit_opts_v1_9_0	14
abfit_reg_opts	15
acquire	18
add_noise	19
add_noise_spec_snr	20
align	20
apodise_xy	21
append_basis	22
append_coils	22
append_dyns	23
append_regs	23
apply_axes	24
apply_mrs	24
apply_pulse	25
Arg.mrs_data	26
array2mrs_data	26
auto_phase	27
back_extrap_ar	28
basis2dyn_mrs_data	28
basis2mrs_data	29
bbase	30
bc_als	30
bc_constant	31
bc_gauss	31
bc_poly	32
bc_spline	32
beta2lw	33
bin_spec	33
calc_basis_corr_mat	34
calc_basis_crlbs	34
calc_coil_noise_cor	35
calc_coil_noise_sd	35
calc_design_efficiency	36
calc_ed_from_lambda	36
calc_peak_info_vec	37
calc_sd_poly	37
calc_spec_diff	38
calc_spec_snr	38
check_lcm	39
check_tqn	39
circ_mask	40
coherence_filter	40
collapse_to_dyns	41
comb_coils	41

comb_coils_mrsi_gls	42
comb_coils_svs_gls	43
comb_fit_list_fit_tables	43
comb_fit_list_result_tables	44
comb_fit_tables	45
comb_metab_ref	45
Conj.mrs_data	46
conv_mrs	46
crop_basis	47
crop_spec	47
crop_td_pts	48
crop_td_pts_end	48
crop_td_pts_pot	49
crop_xy	49
crossprod_3d	50
decimate_mrs_fd	50
decimate_mrs_td	51
deconv_mrs	51
def_acq_paras	52
def_fs	53
def_ft	53
def_N	53
def_nuc	54
def_ref	54
dicom_reader	54
diff_mrs	55
downsample_mrs_fd	56
downsample_mrs_td	56
dyn_acq_times	57
ecc	57
elliptical_mask	58
est_noise_sd	59
fd2td	59
fd_conv_filt	60
fd_gauss_smo	60
find_bids_mrs	61
find_mrs_files	61
fit_amps	62
fit_diags	62
fit_mrs	63
fit_res2csv	64
fit_svs	65
fit_svs_edited	68
fit_svs_group_results	71
fit_svs_gui	72
fit_t1_ti_array	72
fit_t1_tr_array	73
fit_t2_te_array	73

fp_phase	74
fp_phase_correct	75
fp_scale	75
fs	76
ft_dyns	76
ft_shift	77
ft_shift_mat	77
gausswin_2d	78
gen_baseline_reg	78
gen_bold_reg	79
gen_conv_reg	80
gen_F	81
gen_F_xy	81
gen_group_reg	82
gen_I	82
gen_impulse_reg	83
gen_poly_reg	83
gen_trap_reg	84
get_1h_braino_basis_names	85
get_1h_brain_basis_names	86
get_1h_brain_basis_paras	86
get_1h_brain_basis_paras_v1	87
get_1h_brain_basis_paras_v2	87
get_1h_brain_basis_paras_v3	88
get_1h_spectre_basis_names	88
get_2d_psf	89
get_acq_paras	89
get_basis_subset	90
get_dyns	90
get_even_dyns	91
get_fh_dyns	91
get_fit_map	92
get_fp	92
get_guassain_pulse	93
get_head_dyns	93
get_hrf	94
get_lcm_cmd	94
get_metab	94
get_mol_names	95
get_mol_paras	95
get_mrsi2d_seg	96
get_mrsi_voi	96
get_mrsi_voxel	97
get_mrsi_voxel_xy_psf	97
get_mrs_affine	98
get_odd_dyns	98
get_ref	99
get_seg_ind	99

get_sh_dyns	100
get_slice	100
get_spin_num	101
get_subset	101
get_svs_voi	102
get_tail_dyns	103
get_td_amp	103
get_tqn_cmd	104
get_uncoupled_mol	104
get_voi_cog	105
get_voi_seg	105
get_voi_seg_psf	106
get_voxel	106
glm_spec	107
glm_spec_fmrs_fl	107
glm_spec_fmrs_group	108
glm_spec_group_linhyp	109
gridplot	109
gridplot.mrs_data	110
grid_shift_xy	110
hsvd	111
hsvd_filt	112
hsvd_vec	113
hz	113
ift_shift	114
ift_shift_mat	114
Im.mrs_data	115
image.mrs_data	115
img2kspace_xy	117
Imzap	117
install_cli	118
interleave_dyns	118
int_spec	119
inv_even_dyns	119
inv_odd_dyns	120
is.def	120
is_fd	121
kspace2img_xy	121
l2_reg	122
lb	123
lofdc	123
lw2alpha	124
lw2beta	125
make_basis_from_raw	125
mask_dyns	126
mask_fit_res	126
mask_xy	127
mask_xy_corners	127

mask_xy_ellipse	128
mask_xy_mat	128
mat2mrs_data	129
matexp	129
max_mrs	130
max_mrs_interp	130
mean.list	131
mean.mrs_data	131
mean_dyns	132
mean_dyn_blocks	132
mean_dyn_pairs	133
mean_mrs_list	133
mean_vec_blocks	134
median_dyns	134
Mod.mrs_data	135
mod_td	135
mrs_data2basis	136
mrs_data2bids	136
mrs_data2mat	137
mrs_data2spec_mat	138
mrs_data2vec	138
mvfftshift	139
mviftshift	139
n2coord	140
Ncoils	140
Ndyns	140
nifti_flip_lr	141
Npts	141
Nspec	142
Ntrans	142
Nx	142
Ny	143
Nz	143
one_page_pdf	143
ortho3	144
ortho3_inter	145
peak_info	146
pg_extrap_xy	146
phase	147
phase_ref_1h_brain	148
plot.fit_result	148
plot.mrs_data	150
plot_bc	152
plot_reg	152
plot_slice_fit	153
plot_slice_fit_inter	153
plot_slice_map	154
plot_slice_map_inter	155

plot_spec_sd	156
plot_voi_overlay	156
plot_voi_overlay_seg	157
ppm	157
precomp	158
preproc_svs	158
preproc_svs_dataset	159
print.fit_result	159
print.mrs_data	160
qn_states	160
rats	161
Re.mrs_data	162
read_basis	163
read_ima_coil_dir	163
read_ima_dyn_dir	164
read_lcm_coord	164
read_mrs	165
read_mrs_tqn	166
read_pulse_ascii	167
read_pulse_bruker	167
read_pulse_pta	168
read_siemens_txt_hdr	168
read_tqn_fit	169
read_tqn_result	169
recon_imag	170
recon_imag_vec	170
recon_twix_2d_mrsi	171
rectangular_mask	171
rep_array_dim	172
rep_dyn	172
rep_mrs	173
resample_basis	173
resample_img	174
resample_voi	174
reslice_to_mrs	175
reson_table2mrs_data	175
re_weighting	176
rm_dyns	176
scale_amp_legacy	177
scale_amp_molal	178
scale_amp_molal_pvc	179
scale_amp_molar	179
scale_amp_molar2molal_pvc	180
scale_amp_ratio	181
scale_amp_ratio_value	181
scale_amp_water_ratio	182
scale_basis_amp	182
scale_basis_from_singlet	183

scale_mrs_amp	183
scale_spec	184
sd	184
sd.mrs_data	185
seconds	185
segment_t1_fsl	186
seq_cpmg_ideal	186
seq_mega_press_ideal	187
seq_press_2d_shaped	188
seq_press_ideal	189
seq_pulse_acquire	189
seq_slaser_ideal	190
seq_spin_echo_ideal	190
seq_steam_ideal	191
seq_steam_ideal_cof	191
seq_steam_ideal_young	192
set_def_acq_paras	193
set_lcm_cmd	193
set_lw	194
set_mask_xy_mat	194
set_Ntrans	195
set_precomp_mode	195
set_precomp_verbose	195
set_ref	196
set_td_pts	196
set_tqn_cmd	197
set_tr	197
shift	198
shift_basis	198
sim_basis	199
sim_basis_1h_brain	200
sim_basis_1h_brain_press	200
sim_basis_mm_lip_lcm	201
sim_basis_tqn	202
sim_brain_1h	202
sim_mol	203
sim_noise	204
sim_resonances	205
sim_th_excit_profile	206
sim_zero	207
smooth_dyns	207
sort_basis	208
spant_abfit_benchmark	208
spant_simulation_benchmark	209
spant_sim_fmrs_dataset	209
spec_decomp	210
spec_op	210
spin_sys	211

spm_pve2categorical	212
ssp	212
stackplot	213
stackplot.fit_result	213
stackplot.mrs_data	215
sub_first_dyn	217
sub_mean_dyns	217
sub_median_dyns	218
sum_coils	218
sum_dyns	219
sum_mrs	219
sum_mrs_list	220
svs_1h_brain_analysis	220
svs_1h_brain_analysis_dev	221
svs_1h_brain_batch_analysis	223
sv_res_table	224
td2fd	224
tdsr	225
td_conv_filt	225
te	226
tr	226
t_test_spec	227
varpro_3_para_opts	227
varpro_basic_opts	228
varpro_opts	229
vec2mrs_data	230
write_basis	231
write_basis_tqn	231
write_mrs	232
write_mrs_nifti	232
write_pulse_ascii	233
zero_fade_spec	233
zero_higher_orders	234
zero_td_pts_end	234
zf	235
zf_xy	235

Index**237**

spant-package

*spant: spectroscopy analysis tools.***Description**

spant provides a set of tools for reading, visualising and processing Magnetic Resonance Spectroscopy (MRS) data.

Details

To get started with spant, take a look at the introduction vignette:

```
vignette("spant-intro", package="spant")
```

Full list of vignettes:

```
browseVignettes(package = "spant")
```

Full list of functions:

```
help(package = spant, help_type = "html")
```

An online version of the documentation is available from:

<https://martin3141.github.io/spant/>

Author(s)

Maintainer: Martin Wilson <martin@pipegrep.co.uk> ([ORCID](#))

Other contributors:

- Yong Wang [contributor]
- John Muschelli [contributor]

See Also

Useful links:

- <https://spantdoc.wilsonlab.co.uk/>
- <https://martin3141.github.io/spant/>
- <https://github.com/martin3141/spant/>
- Report bugs at <https://github.com/martin3141/spant/issues/>

abfit_opts

Return a list of options for an ABfit analysis.

Description

Return a list of options for an ABfit analysis.

Usage

```
abfit_opts(  
  init_damping = 5,  
  maxiters = 1024,  
  max_shift_pre = 0.078,  
  max_shift_fine = NULL,  
  max_damping = 15,  
  max_phase = 360,  
  lambda = NULL,
```

```
ppm_left = 4,  
ppm_right = 0.2,  
zp = TRUE,  
bl_ed_pppm = 2,  
auto_bl_flex = TRUE,  
bl_comps_pppm = 15,  
adaptive_bl_comps_pppm = FALSE,  
export_sp_fit = FALSE,  
max_asym = 0.25,  
max_basis_shift = 0.0078,  
max_basis_damping = 2,  
maxiters_pre = 1000,  
algo_pre = "NLOPT_LN_NELDERMEAD",  
min_bl_ed_pppm = NULL,  
max_bl_ed_pppm = 7,  
auto_bl_flex_n = 20,  
pre_fit_bl_ed_pppm = 1,  
remove_lip_mm_prefit = FALSE,  
pre_align = TRUE,  
max_pre_align_shift = 0.1,  
pre_align_ref_freqs = c(2.01, 3.03, 3.22),  
noise_region = c(-0.5, -2.5),  
optimal_smooth_criterion = "maic",  
aic_smoothing_factor = 5,  
anal_jac = TRUE,  
pre_fit_ppm_left = 4,  
pre_fit_ppm_right = 1.8,  
phi1_optim = FALSE,  
phi1_init = 0,  
max_dphi1 = 0.2,  
max_basis_shift_broad = NULL,  
max_basis_damping_broad = NULL,  
ahat_calc_method = "lh_pnnls",  
prefit_phase_search = TRUE,  
freq_reg = NULL,  
freq_reg_naa = NULL,  
lb_reg = NULL,  
asym_reg = NULL,  
output_all_paras = FALSE,  
output_all_paras_raw = FALSE,  
input_paras_raw = NULL,  
optim_lw_only = FALSE,  
optim_lw_only_limit = 20,  
lb_init = 0.001,  
lb_init_approx_fit = FALSE,  
zf_offset = NULL  
)
```

Arguments

init_damping	initial value of the Gaussian global damping parameter (Hz). Very poorly shimmed or high field data may benefit from a larger value.
maxiters	The maximum number of iterations to run for the detailed fit.
max_shift_pre	The maximum allowable global shift to be applied in the approximate (pre-fit) phases of analysis (ppm).
max_shift_fine	The maximum allowable global shift to be applied in the detailed fit phase of analysis (ppm).
max_damping	maximum permitted value of the global damping parameter (Hz).
max_phase	the maximum absolute permitted value of the global zero-order phase term (degrees). Note, the prefit_phase_search option is not constrained by this term.
lambda	manually set the the baseline smoothness parameter.
ppm_left	downfield frequency limit for the fitting range (ppm).
ppm_right	upfield frequency limit for the fitting range (ppm).
zp	zero pad the data to twice the original length before fitting.
bl_ed_pppm	manually set the the baseline smoothness parameter (ED per ppm).
auto_bl_flex	automatically determine the level of baseline smoothness.
bl_comps_pppm	spline basis density (signals per ppm).
adaptive_bl_comps_pppm	adjust the spline basis density in the detailed fit phase, based on the required level of smoothness, to reduce computation time.
export_sp_fit	add the fitted spline functions to the fit result.
max_asym	maximum allowable value of the asymmetry parameter.
max_basis_shift	maximum allowable frequency shift for individual basis signals (ppm).
max_basis_damping	maximum allowable Lorentzian damping factor for individual basis signals (Hz).
maxiters_pre	maximum iterations for the coarse (pre-)fit.
algo_pre	optimisation method for the coarse (pre-)fit.
min_bl_ed_pppm	minimum value for the candidate baseline flexibility analyses (ED per ppm).
max_bl_ed_pppm	minimum value for the candidate baseline flexibility analyses (ED per ppm).
auto_bl_flex_n	number of candidate baseline analyses to perform.
pre_fit_bl_ed_pppm	level of baseline flexibility to use in the coarse fitting stage of the algorithm (ED per ppm).
remove_lip_mm_prefit	remove broad signals in the coarse fitting stage of the algorithm.
pre_align	perform a pre-alignment step before coarse fitting.
max_pre_align_shift	maximum allowable shift in the pre-alignment step (ppm).

pre_align_ref_freqs	a vector of prominent spectral frequencies used in the pre-alignment step (ppm).
noise_region	spectral region to estimate the noise level (ppm).
optimal_smooth_criterion	method to determine the optimal smoothness.
aic_smoothing_factor	modification factor for the AIC calculation. Larger values result in less flexible baselines.
anal_jac	use a analytical approximation to the jacobian in the detailed fitting stage.
pre_fit_ppm_left	downfield frequency limit for the fitting range in the coarse fitting stage of the algorithm (ppm).
pre_fit_ppm_right	upfield frequency limit for the fitting range in the coarse fitting stage of the algorithm (ppm).
phi1_optim	apply and optimise a frequency dependant phase term.
phi1_init	initial value for the frequency dependant phase term (ms).
max_dphi1	maximum allowable change from the initial frequency dependant phase term (ms).
max_basis_shift_broad	maximum allowable shift for broad signals in the basis (ppm). Determined based on their name beginning with Lip or MM. The default value is set to max_basis_shift.
max_basis_damping_broad	maximum allowable Lorentzian damping for broad signals in the basis (Hz). Determined based on their name beginning with Lip or MM. The default value is set to max_basis_damping.
ahat_calc_method	method to calculate the metabolite amplitudes. May be one of: "lh_pnnls" or "ls".
prefit_phase_search	perform a 1D search for the optimal phase in the prefit stage of the algorithm.
freq_reg	frequency shift parameter.
freq_reg_naa	frequency shift parameter for NAA and NAAG.
lb_reg	individual line broadening parameter.
asym_reg	lineshape asymmetry parameter.
output_all_paras	include more fitting parameters in the fit table, e.g. individual shift and damping factors for each basis set element.
output_all_paras_raw	include raw fitting parameters in the fit table. For advanced diagnostic use only.
input_paras_raw	input raw fitting parameters. For advanced diagnostic use only.
optim_lw_only	optimize the global line-broadening term only.

optim_lw_only_limit	limits for the line-broadening term as a percentage of the starting value when optim_lw_only is TRUE.
lb_init	initial Lorentzian line broadening value (in Hz) for the individual basis signals. Setting to 0 will clash with the minimum allowable value (eg hard constraint) during the detailed fit.
lb_init_approx_fit	apply lb_init to the basis during the approximate iterative fit.
zf_offset	offset in number of data points from the end of the FID to zero-fill. Default is NULL and will automatically set this to 50 points when the FID distortion flag is set for the mrs_data.

Value

full list of options.

Examples

```
opts <- abfit_opts(ppm_left = 4.2, noise_region = c(-1, -3))
```

abfit_opts_v1_9_0	<i>Return a list of options for an ABfit analysis to maintain comparability with analyses performed with version 1.9.0 (and earlier) of spant.</i>
-------------------	--

Description

Return a list of options for an ABfit analysis to maintain comparability with analyses performed with version 1.9.0 (and earlier) of spant.

Usage

```
abfit_opts_v1_9_0(...)
```

Arguments

... arguments passed to [abfit_opts](#).

Value

full list of options.

abfit_reg_opts	<i>Return a list of options for an ABfit analysis with regularisation.</i>
----------------	--

Description

Return a list of options for an ABfit analysis with regularisation.

Usage

```
abfit_reg_opts(  
  init_damping = 5,  
  maxiters = 128,  
  max_shift_pre = 0.078,  
  max_shift_fine = 0.05,  
  max_damping = 15,  
  max_phase = 360,  
  lambda = NULL,  
  ppm_left = 4,  
  ppm_right = 0.2,  
  zp = TRUE,  
  bl_ed_pppm = 2,  
  auto_bl_flex = TRUE,  
  bl_comps_pppm = 15,  
  adaptive_bl_comps_pppm = TRUE,  
  export_sp_fit = FALSE,  
  max_asym = Inf,  
  max_basis_shift = Inf,  
  max_basis_damping = Inf,  
  maxiters_pre = 1000,  
  algo_pre = "NLOPT_LN_NELDERMEAD",  
  min_bl_ed_pppm = NULL,  
  max_bl_ed_pppm = 7,  
  auto_bl_flex_n = 20,  
  pre_fit_bl_ed_pppm = 1,  
  remove_lip_mm_prefit = FALSE,  
  pre_align = TRUE,  
  max_pre_align_shift = 0.1,  
  pre_align_ref_freqs = c(2.01, 3.03, 3.22),  
  noise_region = c(-0.5, -2.5),  
  optimal_smooth_criterion = "maic",  
  aic_smoothing_factor = 5,  
  anal_jac = TRUE,  
  pre_fit_ppm_left = 4,  
  pre_fit_ppm_right = 1.8,  
  phi1_optim = FALSE,  
  phi1_init = 0,  
  max_dphi1 = 0.2,  
)
```

```

max_basis_shift_broad = NULL,
max_basis_damping_broad = NULL,
ahat_calc_method = "lh_pnnls",
prefit_phase_search = TRUE,
freq_reg = 0.004,
freq_reg_naa = NULL,
lb_reg = "lcm_compat",
asym_reg = 0.1,
output_all_paras = FALSE,
output_all_paras_raw = FALSE,
input_paras_raw = NULL,
optim_lw_only = FALSE,
optim_lw_only_limit = 20,
lb_init = "lcm_compat",
lb_init_approx_fit = FALSE,
zf_offset = NULL
)

```

Arguments

<code>init_damping</code>	initial value of the Gaussian global damping parameter (Hz). Very poorly shimmed or high field data may benefit from a larger value.
<code>maxiters</code>	The maximum number of iterations to run for the detailed fit.
<code>max_shift_pre</code>	The maximum allowable global shift to be applied in the approximate (pre-fit) phases of analysis (ppm).
<code>max_shift_fine</code>	The maximum allowable global shift to be applied in the detailed fit phase of analysis (ppm).
<code>max_damping</code>	maximum permitted value of the global damping parameter (Hz).
<code>max_phase</code>	the maximum absolute permitted value of the global zero-order phase term (degrees). Note, the <code>prefit_phase_search</code> option is not constrained by this term.
<code>lambda</code>	manually set the the baseline smoothness parameter.
<code>ppm_left</code>	downfield frequency limit for the fitting range (ppm).
<code>ppm_right</code>	upfield frequency limit for the fitting range (ppm).
<code>zp</code>	zero pad the data to twice the original length before fitting.
<code>bl_ed_pppm</code>	manually set the the baseline smoothness parameter (ED per ppm).
<code>auto_bl_flex</code>	automatically determine the level of baseline smoothness.
<code>bl_comps_pppm</code>	spline basis density (signals per ppm).
<code>adaptive_bl_comps_pppm</code>	adjust the spline basis density in the detailed fit phase, based on the required level of smoothness, to reduce computation time.
<code>export_sp_fit</code>	add the fitted spline functions to the fit result.
<code>max_asym</code>	maximum allowable value of the asymmetry parameter.
<code>max_basis_shift</code>	maximum allowable frequency shift for individual basis signals (ppm).

max_basis_damping	maximum allowable Lorentzian damping factor for individual basis signals (Hz).
maxiters_pre	maximum iterations for the coarse (pre-)fit.
algo_pre	optimisation method for the coarse (pre-)fit.
min_bl_ed_ppm	minimum value for the candidate baseline flexibility analyses (ED per ppm).
max_bl_ed_ppm	maximum value for the candidate baseline flexibility analyses (ED per ppm).
auto_bl_flex_n	number of candidate baseline analyses to perform.
pre_fit_bl_ed_ppm	level of baseline flexibility to use in the coarse fitting stage of the algorithm (ED per ppm).
remove_lip_mm_prefit	remove broad signals in the coarse fitting stage of the algorithm.
pre_align	perform a pre-alignment step before coarse fitting.
max_pre_align_shift	maximum allowable shift in the pre-alignment step (ppm).
pre_align_ref_freqs	a vector of prominent spectral frequencies used in the pre-alignment step (ppm).
noise_region	spectral region to estimate the noise level (ppm).
optimal_smooth_criterion	method to determine the optimal smoothness.
aic_smoothing_factor	modification factor for the AIC calculation. Larger values result in less flexible baselines.
anal_jac	use an analytical approximation to the jacobian in the detailed fitting stage.
pre_fit_ppm_left	downfield frequency limit for the fitting range in the coarse fitting stage of the algorithm (ppm).
pre_fit_ppm_right	upfield frequency limit for the fitting range in the coarse fitting stage of the algorithm (ppm).
phi1_optim	apply and optimise a frequency dependant phase term.
phi1_init	initial value for the frequency dependant phase term (ms).
max_dphi1	maximum allowable change from the initial frequency dependant phase term (ms).
max_basis_shift_broad	maximum allowable shift for broad signals in the basis (ppm). Determined based on their name beginning with Lip or MM. The default value is set to max_basis_shift.
max_basis_damping_broad	maximum allowable Lorentzian damping for broad signals in the basis (Hz). Determined based on their name beginning with Lip or MM. The default value is set to max_basis_damping.

ahat_calc_method	method to calculate the metabolite amplitudes. May be one of: "lh_pnnls" or "ls".
prefit_phase_search	perform a 1D search for the optimal phase in the prefit stage of the algorithm.
freq_reg	frequency shift parameter.
freq_reg_naa	frequency shift parameter for NAA and NAAG.
lb_reg	individual line broadening parameter.
asym_reg	lineshape asymmetry parameter.
output_all_paras	include more fitting parameters in the fit table, e.g. individual shift and damping factors for each basis set element.
output_all_paras_raw	include raw fitting parameters in the fit table. For advanced diagnostic use only.
input_paras_raw	input raw fitting parameters. For advanced diagnostic use only.
optim_lw_only	optimize the global line-broadening term only.
optim_lw_only_limit	limits for the line-broadening term as a percentage of the starting value when optim_lw_only is TRUE.
lb_init	initial Lorentzian line broadening value (in Hz) for the individual basis signals. Setting to 0 will clash with the minimum allowable value (eg hard constraint) during the detailed fit.
lb_init_approx_fit	apply lb_init to the basis during the approximate iterative fit.
zf_offset	offset in number of data points from the end of the FID to zero-fill. Default is NULL and will automatically set this to 50 points when the FID distortion flag is set for the mrs_data.

Value

full list of options.

Examples

```
opts <- abfit_reg_opts(ppm_left = 4.2, noise_region = c(-1, -3))
```

acquire

Simulate pulse sequence acquisition.

Description

Simulate pulse sequence acquisition.

Usage

```
acquire(sys, rec_phase = 0, tol = 1e-04, detect = NULL, amp_scale = 1)
```

Arguments

sys	spin system object.
rec_phase	receiver phase in degrees.
tol	ignore resonance amplitudes below this threshold.
detect	detection nuclei.
amp_scale	scaling factor for the output amplitudes.

Value

a list of resonance amplitudes and frequencies.

add_noise	<i>Add noise to an mrs_data object.</i>
-----------	---

Description

Add noise to an mrs_data object.

Usage

```
add_noise(mrs_data, sd = 0.1, fd = TRUE)
```

Arguments

mrs_data	data to add noise to.
sd	standard deviation of the noise.
fd	generate the noise samples in the frequency-domain (TRUE) or time-domain (FALSE). This is required since the absolute value of the standard deviation of noise samples changes when data is Fourier transformed.

Value

mrs_data object with additive normally distributed noise.

`add_noise_spec_snr` *Add noise to an mrs_data object to match a given SNR.*

Description

Add noise to an `mrs_data` object to match a given SNR.

Usage

```
add_noise_spec_snr(
  mrs_data,
  target_snr,
  sig_region = c(4, 0.5),
  ref_data = NULL
)
```

Arguments

<code>mrs_data</code>	data to add noise to.
<code>target_snr</code>	desired spectral SNR, note this assumes the input data is noise-free, eg simulated data. Note the SNR is estimated from the first scan in the dataset and the same noise level is added to all spectra.
<code>sig_region</code>	spectral limits to search for the strongest spectral data point.
<code>ref_data</code>	measure the signal from the first scan in this reference data and apply the same target noise level to <code>mrs_data</code> .

Value

`mrs_data` object with additive normally distributed noise.

`align` *Align spectra to a reference frequency using a convolution based method.*

Description

Align spectra to a reference frequency using a convolution based method.

Usage

```
align(
  mrs_data,
  ref_freq = 4.65,
  ref_amp = 1,
  zf_factor = 2,
  lb = 2,
  max_shift = 20,
  ret_df = FALSE,
  mean_dyns = FALSE
)
```

Arguments

mrs_data	data to be aligned.
ref_freq	reference frequency in ppm units. More than one frequency may be specified.
ref_amp	amplitude value for the reference signal. More than one value may be specified to match the number of ref_freq signals.
zf_factor	zero filling factor to increase alignment resolution.
lb	line broadening to apply to the reference signal.
max_shift	maximum allowable shift in Hz.
ret_df	return frequency shifts in addition to aligned data (logical).
mean_dyns	align the mean spectrum and apply the same shift to each dynamic.

Value

aligned data object.

apodise_xy	<i>Apodise MRSI data in the x-y direction with a k-space filter.</i>
------------	--

Description

Apodise MRSI data in the x-y direction with a k-space filter.

Usage

```
apodise_xy(mrs_data, func = "hamming", w = 2.5)
```

Arguments

mrs_data	MRSI data.
func	must be "hamming", "hanning" or "gaussian".
w	the reciprocal of the standard deviation for the Gaussian function.

Value

apodised data.

append_basis	<i>Combine a pair of basis set objects.</i>
--------------	---

Description

Combine a pair of basis set objects.

Usage

```
append_basis(basis_a, basis_b)
```

Arguments

basis_a	first basis.
basis_b	second basis.

Value

combined basis set object.

append_coils	<i>Append MRS data across the coil dimension, assumes they matched across the other dimensions.</i>
--------------	---

Description

Append MRS data across the coil dimension, assumes they matched across the other dimensions.

Usage

```
append_coils(...)
```

Arguments

...	MRS data objects as arguments, or a list of MRS data objects.
-----	---

Value

a single MRS data object with the input objects concatenated together.

append_dyns	<i>Append MRS data across the dynamic dimension, assumes they matched across the other dimensions.</i>
-------------	--

Description

Append MRS data across the dynamic dimension, assumes they matched across the other dimensions.

Usage

```
append_dyns(...)
```

Arguments

... MRS data objects as arguments, or a list of MRS data objects.

Value

a single MRS data object with the input objects concatenated together.

append_regs	<i>Append multiple regressor data frames into a single data frame.</i>
-------------	--

Description

Append multiple regressor data frames into a single data frame.

Usage

```
append_regs(...)
```

Arguments

... input regressor data frames.

Value

output regressor data frame.

apply_axes *Apply a function over specified array axes.*

Description

Apply a function over specified array axes.

Usage

```
apply_axes(x, axes, fun, ...)
```

Arguments

x an array.
axes a vector of axes to apply fun over.
fun function to be applied.
... optional arguments to fun.

Value

array.

Examples

```
z <- array(1:1000, dim = c(10, 10, 10))  
a <- apply_axes(z, 3, fft)  
a[1,1,] == fft(z[1,1,])  
a <- apply_axes(z, 3, sum)  
a[1,1,] == sum(z[1,1,])
```

apply_mrs *Apply a function across given dimensions of a MRS data object.*

Description

Apply a function across given dimensions of a MRS data object.

Usage

```
apply_mrs(mrs_data, dims, fun, ..., data_only = FALSE)
```


Arguments

mrs_data	MRS data.
dims	dimensions to apply the function.
fun	name of the function.
...	arguments to the function.
data_only	return an array rather than an MRS data object.

apply_pulse	<i>Simulate an RF pulse on a single spin.</i>
-------------	---

Description

Simulate an RF pulse on a single spin.

Usage

```
apply_pulse(sys, rho, spin_n, angle, nuc, xy)
```

Arguments

sys	spin system object.
rho	density matrix.
spin_n	spin index.
angle	RF flip angle in degrees.
nuc	nucleus influenced by the pulse.
xy	x or y pulse.

Value

density matrix.

Arg.mrs_data	<i>Apply Arg operator to an MRS dataset.</i>
--------------	--

Description

Apply Arg operator to an MRS dataset.

Usage

```
## S3 method for class 'mrs_data'
Arg(z)
```

Arguments

z MRS data.

Value

MRS data following Arg operator.

array2mrs_data	<i>Convert a 7 dimensional array in into a mrs_data object. The array dimensions should be ordered as : dummy, X, Y, Z, dynamic, coil, FID.</i>
----------------	---

Description

Convert a 7 dimensional array in into a mrs_data object. The array dimensions should be ordered as : dummy, X, Y, Z, dynamic, coil, FID.

Usage

```
array2mrs_data(
  data_array,
  mrs_data = NULL,
  fs = NULL,
  ft = NULL,
  ref = NULL,
  nuc = NULL,
  fd = FALSE
)
```

Arguments

data_array	7d data array.
mrs_data	example data to copy acquisition parameters from.
fs	sampling frequency in Hz.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
nuc	nucleus that is resonant at the transmitter frequency.
fd	flag to indicate if the matrix is in the frequency domain (logical).

Value

mrs_data object.

auto_phase	<i>Perform zeroth-order phase correction based on the minimisation of the squared difference between the real and magnitude components of the spectrum.</i>
------------	---

Description

Perform zeroth-order phase correction based on the minimisation of the squared difference between the real and magnitude components of the spectrum.

Usage

```
auto_phase(mrs_data, xlim = c(4, 1.8), smo_ppm_sd = 0.05, ret_phase = FALSE)
```

Arguments

mrs_data	an object of class mrs_data.
xlim	frequency range (default units of PPM) to including in the phase.
smo_ppm_sd	Gaussian smoother sd in ppm units.
ret_phase	return phase values (logical).

Value

MRS data object and phase values (optional).

back_extrap_ar	<i>Back extrapolate time-domain data points using an autoregressive model.</i>
----------------	--

Description

Back extrapolate time-domain data points using an autoregressive model.

Usage

```
back_extrap_ar(
  mrs_data,
  extrap_pts,
  pred_pts = NULL,
  method = "burg",
  rem_add = TRUE,
  ...
)
```

Arguments

mrs_data	mrs_data object.
extrap_pts	number of points to extrapolate.
pred_pts	number of points to base the extrapolation on.
method	character string specifying the method to fit the model. Must be one of the strings in the default argument (the first few characters are sufficient). Defaults to "burg".
rem_add	remove additional points from the end of the FID to maintain the original length of the dataset. Default to TRUE.
...	additional arguments to specific methods, see ?ar.

Value

back extrapolated data.

basis2dyn_mrs_data	<i>Convert a basis object to a dynamic mrs_data object.</i>
--------------------	---

Description

Convert a basis object to a dynamic mrs_data object.

Usage

```
basis2dyn_mrs_data(basis, amps, tr)
```

Arguments

basis	basis set object.
amps	a data frame with each column corresponding to a basis element and each row corresponding to each dynamic scan.
tr	the dataset repetition time in seconds.

Value

a dynamic mrs_data object.

basis2mrs_data	<i>Convert a basis object to an mrs_data object - where basis signals are spread across the dynamic dimension.</i>
----------------	--

Description

Convert a basis object to an mrs_data object - where basis signals are spread across the dynamic dimension.

Usage

```
basis2mrs_data(
  basis,
  sum_elements = FALSE,
  amps = NULL,
  shifts = NULL,
  lbs = NULL
)
```

Arguments

basis	basis set object.
sum_elements	return the sum of basis elements (logical)
amps	a vector of scaling factors to apply to each basis element.
shifts	a vector of frequency shifts (in ppm) to apply to each basis element.
lbs	a vector of Lorentzian line broadening terms (in Hz) to apply to each basis element.

Value

an mrs_data object with basis signals spread across the dynamic dimension or summed.

bbase	<i>Generate a spline basis, slightly adapted from : "Splines, knots, and penalties", Eilers 2010.</i>
-------	---

Description

Generate a spline basis, slightly adapted from : "Splines, knots, and penalties", Eilers 2010.

Usage

```
bbase(N, number, deg = 3)
```

Arguments

N	number of data points.
number	number of spline functions.
deg	spline degree : deg = 1 linear, deg = 2 quadratic, deg = 3 cubic.

Value

spline basis as a matrix.

bc_als	<i>Baseline correction using the ALS method.</i>
--------	--

Description

Eilers P. H. C. and Boelens H. F. M. (2005) Baseline correction with asymmetric least squares smoothing. Leiden Univ. Medical Centre Report.

Usage

```
bc_als(mrs_data, lambda = 10000, p = 0.001, ret_bc_only = TRUE)
```

Arguments

mrs_data	mrs_data object.
lambda	controls the baseline flexibility.
p	controls the penalty for negative data points.
ret_bc_only	return the baseline corrected data only. When FALSE the baseline estimate and input data will be returned.

Value

baseline corrected data.

bc_constant	<i>Remove a constant baseline offset based on a reference spectral region.</i>
-------------	--

Description

Remove a constant baseline offset based on a reference spectral region.

Usage

```
bc_constant(mrs_data, xlim)
```

Arguments

mrs_data	MRS data.
xlim	spectral range containing a flat baseline region to measure the offset.

Value

baseline corrected data.

bc_gauss	<i>Apply and subtract a Gaussian smoother in the spectral domain.</i>
----------	---

Description

Apply and subtract a Gaussian smoother in the spectral domain.

Usage

```
bc_gauss(mrs_data, smo_ppm_sd)
```

Arguments

mrs_data	mrs_data object.
smo_ppm_sd	Gaussian smoother sd in ppm units.

Value

smoother subtracted data.

bc_poly	<i>Fit and subtract a polynomial to each spectrum in a dataset.</i>
---------	---

Description

Fit and subtract a polynomial to each spectrum in a dataset.

Usage

```
bc_poly(mrs_data, p_deg = 1)
```

Arguments

mrs_data	mrs_data object.
p_deg	polynomial degree.

Value

polynomial subtracted data.

bc_spline	<i>Fit and subtract a smoothing spline to each spectrum in a dataset.</i>
-----------	---

Description

Fit and subtract a smoothing spline to each spectrum in a dataset.

Usage

```
bc_spline(mrs_data, spar = 0.5, nknots = 100)
```

Arguments

mrs_data	mrs_data object.
spar	smoothing parameter typically between 0 and 1.
nknots	number of spline knots.

Value

smoothing spline subtracted data.

beta2lw	<i>Covert a beta value in the time-domain to an equivalent linewidth in Hz: $x * \exp(-i * t * t * \text{beta})$.</i>
---------	--

Description

Covert a beta value in the time-domain to an equivalent linewidth in Hz: $x * \exp(-i * t * t * \text{beta})$.

Usage

```
beta2lw(beta)
```

Arguments

beta	beta damping value.
------	---------------------

Value

linewidth value in Hz.

bin_spec	<i>Bin equally spaced spectral regions.</i>
----------	---

Description

Bin equally spaced spectral regions.

Usage

```
bin_spec(mrs_data, width = 0.05, unit = "ppm")
```

Arguments

mrs_data	data to be "binned".
width	bin width.
unit	bin width unit, can be "ppm" (default) or "pts".

Value

binned mrs_data object.

calc_basis_corr_mat *Estimate the correlation matrix for a basis set.*

Description

Estimate the correlation matrix for a basis set.

Usage

```
calc_basis_corr_mat(basis, xlim = c(4, 0.2), zf = TRUE)
```

Arguments

basis	basis_set object.
xlim	spectral range to use in ppm.
zf	zero-fill the basis set.

Value

correlation matrix.

calc_basis_crlbs *Estimate the CRLB for each element in a basis set.*

Description

Estimate the CRLB for each element in a basis set.

Usage

```
calc_basis_crlbs(
  basis,
  xlim = c(4, 0.2),
  zf = TRUE,
  sd = 1,
  bl_comp_pppm = NULL
)
```

Arguments

basis	basis_set object.
xlim	spectral range to use in ppm.
zf	zero-fill the basis set.
sd	standard deviation of the noise.
bl_comp_pppm	number spline baseline components to append per-ppm.

Value

a vector of predicted errors.

calc_coil_noise_cor *Calculate the noise correlation between coil elements.*

Description

Calculate the noise correlation between coil elements.

Usage

```
calc_coil_noise_cor(noise_data)
```

Arguments

noise_data mrs_data object with one FID for each coil element.

Value

correlation matrix.

calc_coil_noise_sd *Calculate the noise standard deviation for each coil element.*

Description

Calculate the noise standard deviation for each coil element.

Usage

```
calc_coil_noise_sd(noise_data)
```

Arguments

noise_data mrs_data object with one FID for each coil element.

Value

array of standard deviations.

calc_design_efficiency

Calculate the efficiency of a regressor data frame.

Description

Calculate the efficiency of a regressor data frame.

Usage

```
calc_design_efficiency(regressor_df, contrasts)
```

Arguments

regressor_df input regressor data frame.

contrasts a vector of contrast values.

calc_ed_from_lambda *Calculate the effective dimensions of a spline smoother from lambda.*

Description

Calculate the effective dimensions of a spline smoother from lambda.

Usage

```
calc_ed_from_lambda(spline_basis, deriv_mat, lambda)
```

Arguments

spline_basis spline basis.

deriv_mat derivative matrix.

lambda smoothing parameter.

Value

the effective dimension value.

calc_peak_info_vec	<i>Calculate the FWHM of a peak from a vector of intensity values.</i>
--------------------	--

Description

Calculate the FWHM of a peak from a vector of intensity values.

Usage

```
calc_peak_info_vec(data_pts, interp_f)
```

Arguments

data_pts	input vector.
interp_f	interpolation factor to improve the FWHM estimate.

Value

a vector of: x position of the highest data point, maximum peak value in the y axis, FWHM in the units of data points.

calc_sd_poly	<i>Perform a polynomial fit, subtract and return the standard deviation of the residuals.</i>
--------------	---

Description

Perform a polynomial fit, subtract and return the standard deviation of the residuals.

Usage

```
calc_sd_poly(y, degree = 1)
```

Arguments

y	array.
degree	polynomial degree.

Value

standard deviation of the fit residuals.

calc_spec_diff	<i>Calculate the sum of squares differences between two mrs_data objects.</i>
----------------	---

Description

Calculate the sum of squares differences between two mrs_data objects.

Usage

```
calc_spec_diff(mrs_data, ref = NULL, xlim = c(4, 0.5))
```

Arguments

mrs_data	mrs_data object.
ref	reference mrs_data object to calculate differences.
xlim	spectral limits to perform calculation.

Value

an array of the sum of squared difference values.

calc_spec_snr	<i>Calculate the spectral SNR.</i>
---------------	------------------------------------

Description

SNR is defined as the maximum signal value divided by the standard deviation of the noise.

Usage

```
calc_spec_snr(  
  mrs_data,  
  sig_region = c(4, 0.5),  
  noise_region = c(-0.5, -2.5),  
  p_order = 2,  
  interp_f = 4,  
  full_output = FALSE  
)
```

Arguments

mrs_data	an object of class mrs_data.
sig_region	a ppm region to define where the maximum signal value should be estimated.
noise_region	a ppm region to defined where the noise level should be estimated.
p_order	polynomial order to fit to the noise region before estimating the standard deviation.
interp_f	interpolation factor to improve detection of the highest signal value.
full_output	output signal, noise and SNR values separately.

Details

The mean noise value is subtracted from the maximum signal value to reduce DC offset bias. A polynomial detrending fit (second order by default) is applied to the noise region before the noise standard deviation is estimated.

Value

an array of SNR values.

check_lcm	<i>Check LCMModel can be run</i>
-----------	----------------------------------

Description

Check LCMModel can be run

Usage

```
check_lcm()
```

check_tqn	<i>Check the TARQUIN binary can be run</i>
-----------	--

Description

Check the TARQUIN binary can be run

Usage

```
check_tqn()
```

circ_mask	<i>Create a logical circular mask spanning the full extent of an $n \times n$ matrix.</i>
-----------	--

Description

Create a logical circular mask spanning the full extent of an $n \times n$ matrix.

Usage

```
circ_mask(d, n, offset = 1)
```

Arguments

d	diameter of the mask.
n	number of matrix rows and columns.
offset	offset the mask centre in matrix dimension units.

Value

logical $n \times n$ mask matrix.

coherence_filter	<i>Zero all coherence orders other than the one supplied as an argument.</i>
------------------	--

Description

Zero all coherence orders other than the one supplied as an argument.

Usage

```
coherence_filter(sys, rho, order = 0)
```

Arguments

sys	spin system object.
rho	density matrix.
order	coherence order to keep (default is 0).

Value

density matrix.

collapse_to_dyns	<i>Collapse MRS data by concatenating spectra along the dynamic dimension.</i>
------------------	--

Description

Collapse MRS data by concatenating spectra along the dynamic dimension.

Usage

```
collapse_to_dyns(x, rm_masked = FALSE)

## S3 method for class 'mrs_data'
collapse_to_dyns(x, rm_masked = FALSE)

## S3 method for class 'fit_result'
collapse_to_dyns(x, rm_masked = FALSE)
```

Arguments

x	data object to be collapsed (mrs_data or fit_result object).
rm_masked	remove masked dynamics from the output.

Value

collapsed data with spectra or fits concatenated along the dynamic dimension.

comb_coils	<i>Combine coil data based on the first data point of a reference signal.</i>
------------	---

Description

By default, elements are phased and scaled prior to summation. Where a reference signal is not given, the mean dynamic signal will be used instead.

Usage

```
comb_coils(
  metab,
  ref = NULL,
  noise = NULL,
  scale = TRUE,
  scale_method = "sig_noise_sq",
  sum_coils = TRUE,
  noise_region = c(-0.5, -2.5),
```

```

average_ref_dyns = TRUE,
ref_pt_index = 1,
ret_metab_only = FALSE
)

```

Arguments

metab	MRS data containing metabolite data.
ref	MRS data containing reference data (optional).
noise	MRS data from a noise scan (optional).
scale	option to rescale coil elements based on the first data point (logical).
scale_method	one of "sig_noise_sq", "sig_noise" or "sig".
sum_coils	sum the coil elements as a final step (logical).
noise_region	the spectral region (in ppm) to estimate the noise.
average_ref_dyns	take the mean of the reference scans in the dynamic dimension before use.
ref_pt_index	time-domain point to use for estimating phase and scaling values.
ret_metab_only	return the metabolite data only, even if reference data has been specified.

Value

MRS data.

comb_coils_mrsi_gls *Combine MRSI coil data using the GLS method presented by An et al JMRI 37:1445-1450 (2013).*

Description

Combine MRSI coil data using the GLS method presented by An et al JMRI 37:1445-1450 (2013).

Usage

```
comb_coils_mrsi_gls(metab, noise_pts = 30, noise_mrs = NULL)
```

Arguments

metab	MRSI data containing metabolite data.
noise_pts	number of points from the end of the FIDs to use for noise covariance estimation.
noise_mrs	MRS data containing noise information for each coil.

Value

coil combined MRSI data.

comb_coils_svs_gls	<i>Combine SVS coil data using the GLS method presented by An et al JMRI 37:1445-1450 (2013).</i>
--------------------	---

Description

Combine SVS coil data using the GLS method presented by An et al JMRI 37:1445-1450 (2013).

Usage

```
comb_coils_svs_gls(  
  metab,  
  ref = NULL,  
  noise_pts = 256,  
  noise_mrs = NULL,  
  use_mean_sens = TRUE  
)
```

Arguments

metab	MRS data containing metabolite data.
ref	MRS data containing reference data (optional).
noise_pts	number of points from the end of the FIDs to use for noise covariance estimation.
noise_mrs	MRS data containing noise information for each coil.
use_mean_sens	use the dynamic mean to estimate coil sensitivities.

Value

coil combined MRS data.

comb_fit_list_fit_tables	<i>Combine all fitting data points from a list of fits into a single data frame.</i>
--------------------------	--

Description

Combine all fitting data points from a list of fits into a single data frame.

Usage

```
comb_fit_list_fit_tables(
  fit_list,
  add_extra = TRUE,
  harmonise_ppm = TRUE,
  inc_basis_sigs = FALSE,
  inc_indices = TRUE,
  add_res_id = TRUE
)
```

Arguments

`fit_list` list of `fit_result` objects.

`add_extra` add variables in the extra data frame to the output (TRUE).

`harmonise_ppm` ensure the ppm scale for each fit is identical to the first.

`inc_basis_sigs` include the individual fitting basis signals in the output table, defaults to FALSE.

`inc_indices` include indices such as X, Y and coil in the output, defaults to TRUE. These are generally not useful for SVS analysis.

`add_res_id` add a `res_id` column to the output to distinguish between datasets.

Value

a data frame containing the fit data points.

`comb_fit_list_result_tables`

Combine the fit result tables from a list of fit results.

Description

Combine the fit result tables from a list of fit results.

Usage

```
comb_fit_list_result_tables(fit_list, add_extra = TRUE, add_res_id = TRUE)
```

Arguments

`fit_list` a list of `fit_result` objects.

`add_extra` add variables in the extra data frame to the output (TRUE).

`add_res_id` add a `res_id` column to the output to distinguish between datasets.

Value

a data frame combine all fit result tables with an additional id column to differentiate between data sets. Any variables in the extra data frame may be optionally added to the result.

comb_fit_tables	<i>Combine all fitting data points into a single data frame.</i>
-----------------	--

Description

Combine all fitting data points into a single data frame.

Usage

```
comb_fit_tables(fit_res, inc_basis_sigs = FALSE, inc_indices = TRUE)
```

Arguments

fit_res	a single fit_result object.
inc_basis_sigs	include the individual fitting basis signals in the output table, defaults to FALSE.
inc_indices	include indices such as X, Y and coil in the output, defaults to TRUE. These are generally not useful for SVS analysis.

Value

a data frame containing the fit data points.

comb_metab_ref	<i>Combine a reference and metabolite mrs_data object.</i>
----------------	--

Description

Combine a reference and metabolite mrs_data object.

Usage

```
comb_metab_ref(metab, ref)
```

Arguments

metab	metabolite mrs_data object.
ref	reference mrs_data object.

Value

combined metabolite and reference mrs_data object.

Conj.mrs_data	<i>Apply Conj operator to an MRS dataset.</i>
---------------	---

Description

Apply Conj operator to an MRS dataset.

Usage

```
## S3 method for class 'mrs_data'  
Conj(z)
```

Arguments

z MRS data.

Value

MRS data following Conj operator.

conv_mrs	<i>Convolve two MRS data objects.</i>
----------	---------------------------------------

Description

Convolve two MRS data objects.

Usage

```
conv_mrs(mrs_data, conv)
```

Arguments

mrs_data MRS data to be convolved.
conv convolution data stored as an mrs_data object.

Value

convolved data.

crop_basis	<i>Crop basis_set object based on a frequency range.</i>
------------	--

Description

Crop basis_set object based on a frequency range.

Usage

```
crop_basis(basis, xlim = c(4, 0.2), scale = "ppm")
```

Arguments

basis	basis_set object to be cropped in the spectral dimension.
xlim	range of values to crop in the spectral dimension eg xlim = c(4, 0.2).
scale	the units to use for the frequency scale, can be one of: "ppm", "hz" or "points".

Value

cropped mrs_data object.

crop_spec	<i>Crop mrs_data object based on a frequency range.</i>
-----------	---

Description

Crop mrs_data object based on a frequency range.

Usage

```
crop_spec(mrs_data, xlim = c(4, 0.2), scale = "ppm")
```

Arguments

mrs_data	MRS data.
xlim	range of values to crop in the spectral dimension eg xlim = c(4, 0.2).
scale	the units to use for the frequency scale, can be one of: "ppm", "hz" or "points".

Value

cropped mrs_data object.

crop_td_pts	<i>Crop mrs_data object data points in the time-domain.</i>
-------------	---

Description

Crop mrs_data object data points in the time-domain.

Usage

```
crop_td_pts(mrs_data, start = NULL, end = NULL)
```

Arguments

mrs_data	MRS data.
start	starting data point (defaults to 1).
end	ending data point (defaults to the last saved point).

Value

cropped mrs_data object.

crop_td_pts_end	<i>Crop mrs_data object data points at the end of the FID.</i>
-----------------	--

Description

Crop mrs_data object data points at the end of the FID.

Usage

```
crop_td_pts_end(mrs_data, pts)
```

Arguments

mrs_data	MRS data.
pts	number of points to remove from the end of the FID.

Value

cropped mrs_data object.

crop_td_pts_pot	<i>Crop mrs_data object data points in the time-domain rounding down to the next smallest power of two (pot). Data that already has a pot length will not be changed.</i>
-----------------	---

Description

Crop mrs_data object data points in the time-domain rounding down to the next smallest power of two (pot). Data that already has a pot length will not be changed.

Usage

```
crop_td_pts_pot(mrs_data)
```

Arguments

mrs_data	MRS data.
----------	-----------

Value

cropped mrs_data object.

crop_xy	<i>Crop an MRSI dataset in the x-y direction</i>
---------	--

Description

Crop an MRSI dataset in the x-y direction

Usage

```
crop_xy(mrs_data, x_dim, y_dim)
```

Arguments

mrs_data	MRS data object.
x_dim	x dimension output length.
y_dim	y dimension output length.

Value

selected subset of MRS data.

crossprod_3d	<i>Compute the vector cross product between vectors x and y. Adapted from http://stackoverflow.com/questions/15162741/what-is-rs-crossproduct-function</i>
--------------	---

Description

Compute the vector cross product between vectors x and y . Adapted from <http://stackoverflow.com/questions/15162741/what-is-rs-crossproduct-function>

Usage

```
crossprod_3d(x, y)
```

Arguments

x	vector of length 3.
y	vector of length 3.

Value

vector cross product of x and y .

decimate_mrs_fd	<i>Decimate an MRS signal to half the original sampling frequency by filtering in the frequency domain before down sampling.</i>
-----------------	--

Description

Decimate an MRS signal to half the original sampling frequency by filtering in the frequency domain before down sampling.

Usage

```
decimate_mrs_fd(mrs_data)
```

Arguments

mrs_data	MRS data object.
----------	------------------

Value

decimated data at half the original sampling frequency.

decimate_mrs_td	<i>Decimate an MRS signal by filtering in the time domain before downsampling.</i>
-----------------	--

Description

Decimate an MRS signal by filtering in the time domain before downsampling.

Usage

```
decimate_mrs_td(mrs_data, q = 2, n = 4, ftype = "iir")
```

Arguments

mrs_data	MRS data object.
q	integer factor to downsample by (default = 2).
n	filter order used in the downsampling.
ftype	filter type, "iir" or "fir".

Value

decimated data.

deconv_mrs	<i>Deconvolve two MRS data objects.</i>
------------	---

Description

Deconvolve two MRS data objects.

Usage

```
deconv_mrs(mrs_data_a, mrs_data_b)
```

Arguments

mrs_data_a	MRS data to be deconvolved.
mrs_data_b	MRS data to be deconvolved.

Value

deconvolved data.

def_acq_paras	<i>Return (and optionally modify using the input arguments) a list of the default acquisition parameters.</i>
---------------	---

Description

Return (and optionally modify using the input arguments) a list of the default acquisition parameters.

Usage

```
def_acq_paras(  
    ft = getOption("spant.def_ft"),  
    fs = getOption("spant.def_fs"),  
    N = getOption("spant.def_N"),  
    ref = getOption("spant.def_ref"),  
    nuc = getOption("spant.def_nuc")  
)
```

Arguments

ft	specify the transmitter frequency in Hz.
fs	specify the sampling frequency in Hz.
N	specify the number of data points in the spectral dimension.
ref	specify the reference value for ppm scale.
nuc	specify the resonant nucleus.

Value

A list containing the following elements:

- ft transmitter frequency in Hz.
- fs sampling frequency in Hz.
- N number of data points in the spectral dimension.
- ref reference value for ppm scale.
- nuc resonant nucleus.

def_fs	<i>Return the default sampling frequency in Hz.</i>
--------	---

Description

Return the default sampling frequency in Hz.

Usage

def_fs()

Value

sampling frequency in Hz.

def_ft	<i>Return the default transmitter frequency in Hz.</i>
--------	--

Description

Return the default transmitter frequency in Hz.

Usage

def_ft()

Value

transmitter frequency in Hz.

def_N	<i>Return the default number of data points in the spectral dimension.</i>
-------	--

Description

Return the default number of data points in the spectral dimension.

Usage

def_N()

Value

number of data points in the spectral dimension.

def_nuc *Return the default nucleus.*

Description

Return the default nucleus.

Usage

```
def_nuc()
```

Value

number of data points in the spectral dimension.

def_ref *Return the default reference value for ppm scale.*

Description

Return the default reference value for ppm scale.

Usage

```
def_ref()
```

Value

reference value for ppm scale.

dicom_reader *A very simple DICOM reader.*

Description

Note this reader is very basic and does not use a DICOM dictionary or try to convert the data to the correct datatype. For a more robust and sophisticated reader use the oro.dicom package.

Usage

```
dicom_reader(  
    input,  
    tags = list(sop_class_uid = "0008,0016"),  
    endian = "little",  
    debug = FALSE  
)
```

Arguments

input	either a file path or raw binary object.
tags	a named list of tags to be extracted from the file. eg tags <- list(spec_data = "7FE1,1010", pat_name = "0010,0010")
endian	can be "little" or "big".
debug	print out some debugging information, can be "little" or "big".

Value

a list with the same structure as the input, but with tag codes replaced with the corresponding data in a raw format.

diff_mrs	<i>Apply the diff operator to an MRS dataset in the FID/spectral dimension.</i>
----------	---

Description

Apply the diff operator to an MRS dataset in the FID/spectral dimension.

Usage

```
diff_mrs(mrs_data, ...)
```

Arguments

mrs_data	MRS data.
...	additional arguments to the diff function.

Value

MRS data following diff operator.

downsample_mrs_fd	<i>Downsample an MRS signal by a factor of 2 using an FFT "brick-wall" filter.</i>
-------------------	--

Description

Downsample an MRS signal by a factor of 2 using an FFT "brick-wall" filter.

Usage

```
downsample_mrs_fd(mrs_data)
```

Arguments

mrs_data MRS data object.

Value

downsampled data.

downsample_mrs_td	<i>Downsample an MRS signal by a factor of 2 by removing every other data point in the time-domain. Note, signals outside the new sampling frequency will be aliased.</i>
-------------------	---

Description

Downsample an MRS signal by a factor of 2 by removing every other data point in the time-domain. Note, signals outside the new sampling frequency will be aliased.

Usage

```
downsample_mrs_td(mrs_data)
```

Arguments

mrs_data MRS data object.

Value

downsampled data.

dyn_acq_times	<i>Return a time scale vector of acquisition times for a dynamic MRS scan. The first temporal scan is assigned a value of 0.</i>
---------------	--

Description

Return a time scale vector of acquisition times for a dynamic MRS scan. The first temporal scan is assigned a value of 0.

Usage

```
dyn_acq_times(mrs_data = NULL, tr = NULL, Ndyns = NULL, Ntrans = NULL)
```

Arguments

mrs_data	MRS data.
tr	repetition time.
Ndys	number of dynamic scans stored, potentially less than Ntrans if block averaging has been performed.
Ntrans	number of dynamic scans acquired.

Value

time scale vector in units of seconds.

ecc	<i>Eddy current correction.</i>
-----	---------------------------------

Description

Apply eddy current correction using the Klose method.

Usage

```
ecc(metab, ref, rev = FALSE)
```

Arguments

metab	MRS data to be corrected.
ref	reference dataset.
rev	reverse the correction.

Details

In vivo proton spectroscopy in presence of eddy currents. Klose U. Magn Reson Med. 1990 Apr;14(1):26-30.

Value

corrected data in the time domain.

elliptical_mask *Create an elliptical mask stored as a matrix of logical values.*

Description

Create an elliptical mask stored as a matrix of logical values.

Usage

```
elliptical_mask(xN, yN, x0, y0, xr, yr, angle)
```

Arguments

xN	number of pixels in the x dimension.
yN	number of pixels in the y dimension.
x0	centre of ellipse in the x direction in units of pixels.
y0	centre of ellipse in the y direction in units of pixels.
xr	radius in the x direction in units of pixels.
yr	radius in the y direction in units of pixels.
angle	angle of rotation in degrees.

Value

logical mask matrix with dimensions fov_yN x fov_xN.

est_noise_sd	<i>Estimate the standard deviation of the noise from a segment of an mrs_data object.</i>
--------------	---

Description

Estimate the standard deviation of the noise from a segment of an mrs_data object.

Usage

```
est_noise_sd(mrs_data, n = 100, offset = 100, p_order = 2)
```

Arguments

mrs_data	MRS data object.
n	number of data points (taken from the end of array) to use in the estimation.
offset	number of final points to exclude from the calculation.
p_order	polynomial order to fit to the data before estimating the standard deviation.

Value

standard deviation array.

fd2td	<i>Transform frequency-domain data to the time-domain.</i>
-------	--

Description

Transform frequency-domain data to the time-domain.

Usage

```
fd2td(mrs_data)
```

Arguments

mrs_data	MRS data in frequency-domain representation.
----------	--

Value

MRS data in time-domain representation.

fd_conv_filt	<i>Frequency-domain convolution based filter.</i>
--------------	---

Description

Frequency-domain convolution based filter.

Usage

```
fd_conv_filt(mrs_data, K = 25, ext = 1)
```

Arguments

mrs_data	MRS data to be filtered.
K	window width in data points.
ext	point separation for linear extrapolation.

fd_gauss_smo	<i>Apply a Gaussian smoother in the spectral domain.</i>
--------------	--

Description

Apply a Gaussian smoother in the spectral domain.

Usage

```
fd_gauss_smo(mrs_data, smo_ppm_sd)
```

Arguments

mrs_data	mrs_data object.
smo_ppm_sd	Gaussian smoother sd in ppm units.

Value

spectrally smoothed data.

find_bids_mrs	<i>Search for MRS data files in a BIDS filesystem structure.</i>
---------------	--

Description

Search for MRS data files in a BIDS filesystem structure.

Usage

```
find_bids_mrs(path, output_full_path = FALSE)
```

Arguments

path path to the directory containing the BIDS structure.
output_full_path output the full normalised data paths.

Value

data frame containing full paths and information on each MRS file.

find_mrs_files	<i>Find valid MRS data files recursively from a directory path.</i>
----------------	---

Description

Find valid MRS data files recursively from a directory path.

Usage

```
find_mrs_files(dir)
```

Arguments

dir a directory path.

Value

a vector of valid MRS data files.

fit_amps	<i>Extract the fit amplitudes from an object of class fit_result.</i>
----------	---

Description

Extract the fit amplitudes from an object of class fit_result.

Usage

```
fit_amps(  
  x,  
  inc_index = FALSE,  
  sort_names = FALSE,  
  append_common_1h_comb = TRUE  
)
```

Arguments

x	fit_result object.
inc_index	include columns for the voxel index.
sort_names	sort the basis set names alphabetically.
append_common_1h_comb	append commonly used 1H metabolite combinations eg tNAA = NAA + NAAG.

Value

a dataframe of amplitudes.

fit_diags	<i>Calculate diagnostic information for object of class fit_result.</i>
-----------	---

Description

Calculate diagnostic information for object of class fit_result.

Usage

```
fit_diags(x, amps = NULL)
```

Arguments

x	fit_result object.
amps	known metabolite amplitudes.

Value

a dataframe of diagnostic information.

fit_mrs

Perform a fit based analysis of MRS data.

Description

Note that TARQUIN and LCModel require these packages to be installed, and the functions `set_tqn_cmd` and `set_lcm_cmd` (respectively) need to be used to specify the location of these software packages.

Usage

```
fit_mrs(
  metab,
  basis = NULL,
  method = "ABFIT",
  w_ref = NULL,
  opts = NULL,
  parallel = FALSE,
  cl = NULL,
  time = TRUE,
  progress = "text",
  extra = NULL
)
```

Arguments

<code>metab</code>	metabolite data.
<code>basis</code>	basis class object or character vector to basis file in LCModel .basis format.
<code>method</code>	'ABFIT' (default), 'VARPRO', 'VARPRO_3P', 'TARQUIN' or 'LCMODEL'.
<code>w_ref</code>	water reference data for concentration scaling (optional).
<code>opts</code>	options to pass to the analysis method.
<code>parallel</code>	perform analyses in parallel (TRUE or FALSE).
<code>cl</code>	a parallel socket cluster required to run analyses in parallel. Eg, <code>cl <- parallel::makeCluster(4)</code> .
<code>time</code>	measure the time taken for the analysis to complete (TRUE or FALSE).
<code>progress</code>	option is passed to <code>plyr::alply</code> function to display a progress bar during fitting. Default value is "text", set to "none" to disable.
<code>extra</code>	an optional data frame to provide additional variables for use in subsequent analysis steps, eg id or grouping variables.

Details

Fitting approaches described in the following references: ABfit Wilson, M. Adaptive baseline fitting for 1H MR spectroscopy analysis. *Magn Reson Med* 2012;85:13-29.

VARPRO van der Veen JW, de Beer R, Luyten PR, van Ormondt D. Accurate quantification of in vivo 31P NMR signals using the variable projection method and prior knowledge. *Magn Reson Med* 1988;6:92-98.

TARQUIN Wilson, M., Reynolds, G., Kauppinen, R. A., Arvanitis, T. N. & Peet, A. C. A constrained least-squares approach to the automated quantitation of in vivo 1H magnetic resonance spectroscopy data. *Magn Reson Med* 2011;65:1-12.

LCModel Provencher SW. Estimation of metabolite concentrations from localized in vivo proton NMR spectra. *Magn Reson Med* 1993;30:672-679.

Value

MRS analysis object.

Examples

```
fname <- system.file("extdata", "philips_spar_sdat_WS.SDAT", package =
"spant")
svs <- read_mrs(fname)
## Not run:
basis <- sim_basis_1h_brain_press(svs)
fit_result <- fit_mrs(svs, basis)

## End(Not run)
```

fit_res2csv

Write fit results table to a csv file.

Description

Write fit results table to a csv file.

Usage

```
fit_res2csv(fit_res, fname, unscaled = FALSE)
```

Arguments

`fit_res` fit result object.
`fname` filename of csv file.
`unscaled` output the unscaled result table (default = FALSE).

fit_svs	<i>Standard SVS 1H brain analysis pipeline.</i>
---------	---

Description

Note this function is still under development and liable to changes.

Usage

```
fit_svs(  
  input,  
  w_ref = NULL,  
  output_dir = NULL,  
  mri = NULL,  
  mri_seg = NULL,  
  external_basis = NULL,  
  append_external_basis = FALSE,  
  p_vols = NULL,  
  format = NULL,  
  pul_seq = NULL,  
  TE = NULL,  
  TR = NULL,  
  TE1 = NULL,  
  TE2 = NULL,  
  TE3 = NULL,  
  TM = NULL,  
  append_basis = NULL,  
  remove_basis = NULL,  
  pre_align = TRUE,  
  dfp_corr = TRUE,  
  output_ratio = NULL,  
  ecc = FALSE,  
  hsvd_width = NULL,  
  decimate = FALSE,  
  trunc_fid_pts = NULL,  
  fit_method = NULL,  
  fit_opts = NULL,  
  fit_subset = NULL,  
  legacy_ws = FALSE,  
  w_att = 0.7,  
  w_conc = 35880,  
  use_basis_cache = "auto",  
  summary_measures = NULL,  
  dyn_av_block_size = NULL,  
  dyn_av_scheme = NULL,  
  dyn_av_scheme_file = NULL,  
  lcm_bin_path = NULL,
```

```

    plot_ppm_xlim = NULL,
    extra_output = FALSE,
    verbose = FALSE
)

```

Arguments

input	path or mrs_data object containing MRS data.
w_ref	path or mrs_data object containing MRS water reference data.
output_dir	directory path to output fitting results.
mri	filepath or nifti object containing anatomical MRI data.
mri_seg	filepath or nifti object containing segmented MRI data.
external_basis	precompiled basis set object to use for analysis.
append_external_basis	append the external basis with the internally generated one. Useful for adding experimentally acquired baseline signals to internally simulated basis sets. Defaults to FALSE - meaning only signals from the external basis will be used in analysis.
p_vols	a numeric vector of partial volumes expressed as percentages. Defaults to 100% white matter. A voxel containing 100% gray matter tissue would use : p_vols = c(WM = 0, GM = 100, CSF = 0).
format	Override automatic data format detection. See format argument in read_mrs() for permitted values.
pul_seq	Pulse sequence to use for basis simulation. Can be one of the following values : "press", "press_ideal", "press_shaped", "steam" or "slaser". If "press" then "press_ideal" will be assumed unless the magnetic field is stronger than 2.8 Tesla, "press_shaped" will be assumed for 2.9 Tesla and above.
TE	metabolite mrs data echo time in seconds. If not supplied this will be guessed from the metab data file.
TR	metabolite mrs data repetition time in seconds. If not supplied this will be guessed from the metab data file.
TE1	PRESS or sLASER sequence timing parameter in seconds.
TE2	PRESS or sLASER sequence timing parameter in seconds.
TE3	sLASER sequence timing parameter in seconds.
TM	STEAM mixing time parameter in seconds.
append_basis	names of extra signals to add to the default basis. Eg append_basis = c("peth", "cit"). Cannot be used with precompiled basis sets.
remove_basis	grep expression to match names of signals to remove from the basis. For example: use "*" to remove all signals, "^mm ^lip" to remove all macromolecular and lipid signals, "^lac" to remove lactate. This operation is performed before signals are added with append_basis. Cannot be used with precompiled basis sets.
pre_align	perform simple frequency alignment to known reference peaks.

dfp_corr	perform dynamic frequency and phase correction using the RATS method.
output_ratio	optional string to specify a metabolite ratio to output. Defaults to "tCr". Multiple metabolites may be specified for multiple outputs. Set to NA to omit.
ecc	option to perform water reference based eddy current correction, defaults to FALSE.
hsvd_width	set the width of the HSVD filter in Hz. Note the applied width is between -width and +width Hz, with 0 Hz being defined at the centre of the spectral width. Default is disabled (set to NULL), 30 Hz is a reasonable value.
decimate	option on decimate the data by a factor of 2 before analysis. Defaults to FALSE.
trunc_fid_pts	number of points to truncate the input data by in the time-domain. E.g. setting to 1024 will ensure data with more time-domain points will be truncated to a length of 1024. Defaults to NULL, where truncation is not performed.
fit_method	can be "ABFIT-REG" or "LCMODEL". Defaults to "ABFIT-REG".
fit_opts	options to pass to the fitting method.
fit_subset	specify a subset of dynamics to analyse, for example 1:16 would only fit the first 16 dynamic scans.
legacy_ws	perform and output legacy water scaling compatible with default LCModel and TARQUIN behaviour. See w_att and w_conc arguments to change the default assumptions. Default value is FALSE.
w_att	water attenuation factor (default = 0.7) for legacy water scaling. Assumes water T2 of 80ms and a TE = 30 ms. $\exp(-30\text{ms} / 80\text{ms}) \sim 0.7$.
w_conc	assumed water concentration (default = 35880) for legacy water scaling. Default value corresponds to typical white matter. Set to 43300 for gray matter, and 55556 for phantom measurements.
use_basis_cache	Pre-cache basis sets to reduce analysis speed. Can be one of the following : "auto", "all" or "none". The default value of "auto" will only use the cache for 3T PRESS - which generally requires more detailed simulation due to high CSD.
summary_measures	output an additional table with a subset of metabolite levels, eg c("tNAA", "tNAA/tCr", "tNAA/tCho", "Lac/tNAA").
dyn_av_block_size	perform temporal averaging with the specified block size. Defaults to NULL, eg average across all dynamic scans.
dyn_av_scheme	a numeric vector of sequential integers (starting at 1), with the same length as the number of dynamic scans in the metabolite data. For example: c(1, 1, 2, 1, 1, 3, 1, 1).
dyn_av_scheme_file	a file path containing a single column of sequential integers (starting at 1) with the same length as the number of dynamic scans in the metabolite data. File may be formatted as .xlsx, .xls, text or csv format.
lcm_bin_path	set the path to LCModel binary.
plot_ppm_xlim	plotting ppm axis limits in the html results. results.
extra_output	write extra output files for generating custom plots. Defaults to FALSE.
verbose	output potentially useful information.

Examples

```
metab <- system.file("extdata", "philips_spar_sdat_WS.SDAT",
                    package = "spant")
w_ref <- system.file("extdata", "philips_spar_sdat_W.SDAT",
                   package = "spant")
out_dir <- file.path("~", "fit_svs_result")
## Not run:
fit_result <- fit_svs(metab, w_ref, out_dir)

## End(Not run)
```

fit_svs_edited

Edited SVS 1H brain analysis pipeline.

Description

Note this function is still under development and liable to changes.

Usage

```
fit_svs_edited(
  input,
  w_ref = NULL,
  output_dir = NULL,
  mri = NULL,
  mri_seg = NULL,
  external_basis = NULL,
  p_vols = NULL,
  format = NULL,
  editing_scheme = NULL,
  invert_edit_on = NULL,
  invert_edit_off = NULL,
  pul_seq = NULL,
  TE = NULL,
  TR = NULL,
  TE1 = NULL,
  TE2 = NULL,
  TE3 = NULL,
  TM = NULL,
  append_basis_ed_off = NULL,
  remove_basis_ed_off = NULL,
  pre_align = TRUE,
  dfp_corr = TRUE,
  output_ratio = NULL,
  ecc = FALSE,
  hsvd_width = NULL,
  decimate = FALSE,
```

```

trunc_fid_pts = NULL,
fit_opts_edited = NULL,
fit_opts_ed_off = NULL,
fit_subset = NULL,
legacy_ws = FALSE,
w_att = 0.7,
w_conc = 35880,
use_basis_cache = "auto",
summary_measures = NULL,
dyn_av_block_size = NULL,
dyn_av_scheme = NULL,
dyn_av_scheme_file = NULL,
plot_ppm_xlim = NULL,
extra_output = FALSE,
verbose = FALSE
)

```

Arguments

input	path or mrs_data object containing MRS data.
w_ref	path or mrs_data object containing MRS water reference data.
output_dir	directory path to output fitting results.
mri	filepath or nifti object containing anatomical MRI data.
mri_seg	filepath or nifti object containing segmented MRI data.
external_basis	precompiled basis set object to use for analysis.
p_vols	a numeric vector of partial volumes expressed as percentages. Defaults to 100% white matter. A voxel containing 100% gray matter tissue would use : p_vols = c(WM = 0, GM = 100, CSF = 0).
format	Override automatic data format detection. See format argument in read_mrs() for permitted values.
editing_scheme	describes the dynamic data ordering. Can be one of: 'on-off-blocks', 'on-off-interleaved', 'off-on-blocks' or 'off-on-interleaved'.
invert_edit_on	set to TRUE to invert the edit-on sub-spectra.
invert_edit_off	set to TRUE to invert the edit-off sub-spectra.
pul_seq	Pulse sequence to use for basis simulation. Can be one of the following values : "press", "press_ideal", "press_shaped", "steam" or "slaser". If "press" then "press_ideal" will be assumed unless the magnetic field is stronger than 2.8 Tesla, "press_shaped" will be assumed for 2.9 Tesla and above.
TE	metabolite mrs data echo time in seconds. If not supplied this will be guessed from the metab data file.
TR	metabolite mrs data repetition time in seconds. If not supplied this will be guessed from the metab data file.
TE1	PRESS or sLASER sequence timing parameter in seconds.

TE2	PRESS or sLASER sequence timing parameter in seconds.
TE3	sLASER sequence timing parameter in seconds.
TM	STEAM mixing time parameter in seconds.
append_basis_ed_off	names of extra signals to add to the default basis. Eg <code>append_basis_ed_off = c("peth", "cit")</code> . Cannot be used with precompiled basis sets.
remove_basis_ed_off	grep expression to match names of signals to remove from the basis. For example: use "*" to remove all signals, "^mml^lip" to remove all macromolecular and lipid signals, "^lac" to remove lactate. This operation is performed before signals are added with <code>append_basis_ed_off</code> . Cannot be used with precompiled basis sets.
pre_align	perform simple frequency alignment to known reference peaks.
dfp_corr	perform dynamic frequency and phase correction using the RATS method.
output_ratio	optional string to specify a metabolite ratio to output. Defaults to "tCr". Multiple metabolites may be specified for multiple outputs. Set to NA to omit.
ecc	option to perform water reference based eddy current correction, defaults to FALSE.
hsvd_width	set the width of the HSVD filter in Hz. Note the applied width is between -width and +width Hz, with 0 Hz being defined at the centre of the spectral width. Default is disabled (set to NULL), 30 Hz is a reasonable value.
decimate	option on decimate the data by a factor of 2 before analysis. Defaults to FALSE.
trunc_fid_pts	number of points to truncate the input data by in the time-domain. E.g. setting to 1024 will ensure data with more time-domain points will be truncated to a length of 1024. Defaults to NULL, where truncation is not performed.
fit_opts_edited	options to pass to the fitting method for the edited spectrum.
fit_opts_ed_off	options to pass to the fitting method for the edit-off spectrum.
fit_subset	specify a subset of dynamics to analyse, for example 1:16 would only fit the first 16 dynamic scans.
legacy_ws	perform and output legacy water scaling compatible with default LCModel and TARQUIN behaviour. See <code>w_att</code> and <code>w_conc</code> arguments to change the default assumptions. Default value is FALSE.
w_att	water attenuation factor (default = 0.7) for legacy water scaling. Assumes water T2 of 80ms and a TE = 30 ms. $\exp(-30\text{ms} / 80\text{ms}) \sim 0.7$.
w_conc	assumed water concentration (default = 35880) for legacy water scaling. Default value corresponds to typical white matter. Set to 43300 for gray matter, and 55556 for phantom measurements.
use_basis_cache	Pre-cache basis sets to reduce analysis speed. Can be one of the following : "auto", "all" or "none". The default value of "auto" will only use the cache for 3T PRESS - which generally requires more detailed simulation due to high CSD.

summary_measures	output an additional table with a subset of metabolite levels, eg c("tNAA", "tNAA/tCr", "tNAA/tCho", "Lac/tNAA").
dyn_av_block_size	perform temporal averaging with the specified block size. Defaults to NULL, eg average across all dynamic scans.
dyn_av_scheme	a numeric vector of sequential integers (starting at 1), with the same length as the number of dynamic scans in the metabolite data. For example: c(1, 1, 2, 1, 3, 1, 1).
dyn_av_scheme_file	a file path containing a single column of sequential integers (starting at 1) with the same length as the number of dynamic scans in the metabolite data. File may be formatted as .xlsx, .xls, text or csv format.
plot_ppm_xlim	plotting ppm axis limits in the html results. results.
extra_output	write extra output files for generating custom plots. Defaults to FALSE.
verbose	output potentially useful information.

Examples

```
metab <- system.file("extdata", "philips_spar_sdat_WS.SDAT",
  package = "spant")
w_ref <- system.file("extdata", "philips_spar_sdat_W.SDAT",
  package = "spant")
out_dir <- file.path("~/", "fit_svs_result")
## Not run:
fit_result <- fit_svs(metab, w_ref, out_dir)

## End(Not run)
```

fit_svs_group_results *Combine fitting results for group analysis.*

Description

Combine fitting results for group analysis.

Usage

```
fit_svs_group_results(search_path, output_dir = "fit_svs_group_results")
```

Arguments

search_path	path to start recursive search for fitting results.
output_dir	directory path to store group results.

fit_svs_gui	<i>GUI interface for the standard SVS 1H brain analysis pipeline, this is a work in progress, and not ready for serious use.</i>
-------------	--

Description

GUI interface for the standard SVS 1H brain analysis pipeline, this is a work in progress, and not ready for serious use.

Usage

```
fit_svs_gui()
```

fit_t1_ti_array	<i>Fit a T1 recovery curve, from multiple TIs, to a set of amplitudes.</i>
-----------------	--

Description

Fit a T1 recovery curve, from multiple TIs, to a set of amplitudes.

Usage

```
fit_t1_ti_array(
    ti_vec,
    amp_vec,
    lower = 0,
    upper = 10,
    output_fit_res = 0.01,
    ret_full = TRUE
)
```

Arguments

ti_vec	vector of T1 values in seconds.
amp_vec	vector of amplitudes.
lower	minimum allowable T1 value.
upper	maximum allowable T1 value.
output_fit_res	temporal resolution (seconds) of the ideal output relaxation curve.
ret_full	return full fitting information including ideal relaxation curve.

Value

a list containing relaxation parameters and an ideal curve for fit evaluation.

fit_t1_tr_array *Fit a T1 recovery curve, from multiple TRs, to a set of amplitudes.*

Description

Fit a T1 recovery curve, from multiple TRs, to a set of amplitudes.

Usage

```
fit_t1_tr_array(  
    tr_vec,  
    amp_vec,  
    lower = 0,  
    upper = 10,  
    output_fit_res = 0.01,  
    ret_full = TRUE  
)
```

Arguments

tr_vec vector of TR values in seconds.
amp_vec vector of amplitudes.
lower minimum allowable T1 value.
upper maximum allowable T1 value.
output_fit_res temporal resolution (seconds) of the ideal output relaxation curve.
ret_full return full fitting information including ideal relaxation curve.

Value

a list containing relaxation parameters and an ideal curve for fit evaluation.

fit_t2_te_array *Fit a T2 relaxation curve, from multiple TEs, to a set of amplitudes.*

Description

Fit a T2 relaxation curve, from multiple TEs, to a set of amplitudes.

Usage

```
fit_t2_te_array(
  te_vec,
  amp_vec,
  lower = 0,
  upper = 10,
  output_fit_res = 0.01,
  ret_full = TRUE
)
```

Arguments

te_vec	vector of TE values in seconds.
amp_vec	vector of amplitudes.
lower	minimum allowable T2 value.
upper	maximum allowable T2 value.
output_fit_res	temporal resolution (seconds) of the ideal output relaxation curve.
ret_full	return full fitting information including ideal relaxation curve.

Value

a list containing relaxation parameters and an ideal curve for fit evaluation.

fp_phase	<i>Return the phase of the first data point in the time-domain.</i>
----------	---

Description

Return the phase of the first data point in the time-domain.

Usage

```
fp_phase(mrs_data)
```

Arguments

mrs_data	MRS data.
----------	-----------

Value

phase values in degrees.

fp_phase_correct	<i>Perform a zeroth order phase correction based on the phase of the first data point in the time-domain.</i>
------------------	---

Description

Perform a zeroth order phase correction based on the phase of the first data point in the time-domain.

Usage

```
fp_phase_correct(mrs_data, ret_phase = FALSE)
```

Arguments

mrs_data	MRS data to be corrected.
ret_phase	return phase values (logical).

Value

corrected data or a list with corrected data and optional phase values.

fp_scale	<i>Scale the first time-domain data point in an mrs_data object.</i>
----------	--

Description

Scale the first time-domain data point in an mrs_data object.

Usage

```
fp_scale(mrs_data, scale = 0.5)
```

Arguments

mrs_data	MRS data.
scale	scaling value, defaults to 0.5.

Value

scaled mrs_data object.

fs	<i>Return the sampling frequency in Hz of an MRS dataset.</i>
----	---

Description

Return the sampling frequency in Hz of an MRS dataset.

Usage

```
fs(mrs_data)
```

Arguments

mrs_data	MRS data.
----------	-----------

Value

sampling frequency in Hz.

ft_dyns	<i>Apply the Fourier transform over the dynamic dimension.</i>
---------	--

Description

Apply the Fourier transform over the dynamic dimension.

Usage

```
ft_dyns(mrs_data, ft_shift = FALSE, ret_mod = FALSE, fd = TRUE)
```

Arguments

mrs_data	MRS data where the dynamic dimension is in the time-domain.
ft_shift	apply FT shift to the output, default is FALSE.
ret_mod	return the modulus out the transform, default is FALSE.
fd	transform the chemical shift axis to the frequency domain first, default is TRUE.

Value

transformed MRS data.

ft_shift	<i>Perform a fft and fftshift on a vector.</i>
----------	--

Description

Perform a fft and fftshift on a vector.

Usage

```
ft_shift(vec_in)
```

Arguments

vec_in vector input.

Value

output vector.

ft_shift_mat	<i>Perform a fft and fftshift on a matrix with each column replaced by its shifted fft.</i>
--------------	---

Description

Perform a fft and fftshift on a matrix with each column replaced by its shifted fft.

Usage

```
ft_shift_mat(mat_in)
```

Arguments

mat_in matrix input.

Value

output matrix.

gausswin_2d	<i>Create a two dimensional Gaussian window function stored as a matrix.</i>
-------------	--

Description

Create a two dimensional Gaussian window function stored as a matrix.

Usage

```
gausswin_2d(xN, yN, x0, y0, xw, yw)
```

Arguments

xN	number of pixels in the x dimension.
yN	number of pixels in the y dimension.
x0	centre of window function in the x direction in units of pixels. Note, only integer values are applied.
y0	centre of window function in the y direction in units of pixels. Note, only integer values are applied.
xw	the reciprocal of the standard deviation of the Gaussian window in x direction.
yw	the reciprocal of the standard deviation of the Gaussian window in y direction.

Value

matrix with dimensions fov_yN x fov_xN.

gen_baseline_reg	<i>Generate baseline regressor.</i>
------------------	-------------------------------------

Description

Generate baseline regressor.

Usage

```
gen_baseline_reg(mrs_data = NULL, tr = NULL, Ndyns = NULL, Ntrans = NULL)
```

Arguments

mrs_data	mrs_data object for timing information.
tr	repetition time.
Ndyns	number of dynamic scans stored, potentially less than Ntrans if block averaging has been performed.
Ntrans	number of dynamic scans acquired.

Value

a single baseline regressor with value of 1.

gen_bold_reg	<i>Generate BOLD regressors.</i>
--------------	----------------------------------

Description

Generate BOLD regressors.

Usage

```
gen_bold_reg(
  onset,
  duration = NULL,
  trial_type = NULL,
  mrs_data = NULL,
  tr = NULL,
  Ndyns = NULL,
  Ntrans = NULL,
  match_tr = TRUE,
  dt = 0.1,
  normalise = FALSE
)
```

Arguments

onset	stimulus onset in seconds.
duration	stimulus duration in seconds.
trial_type	string label for the stimulus.
mrs_data	mrs_data object for timing information.
tr	repetition time.
Ndyns	number of dynamic scans stored, potentially less than Ntrans if block averaging has been performed.
Ntrans	number of dynamic scans acquired.
match_tr	match the output to the input mrs_data.
dt	timing resolution for internal calculations.
normalise	normalise the response function to have a maximum value of one.

Value

BOLD regressor data frame.

gen_conv_reg	<i>Generate regressors by convolving a specified response function with a stimulus.</i>
--------------	---

Description

Generate regressors by convolving a specified response function with a stimulus.

Usage

```
gen_conv_reg(
  onset,
  duration = NULL,
  trial_type = NULL,
  mrs_data = NULL,
  tr = NULL,
  Ndyns = NULL,
  Ntrans = NULL,
  resp_fn,
  match_tr = TRUE,
  normalise = FALSE
)
```

Arguments

onset	stimulus onset in seconds.
duration	stimulus duration in seconds.
trial_type	string label for the stimulus.
mrs_data	mrs_data object for timing information.
tr	repetition time.
Ndyns	number of dynamic scans stored, potentially less than Ntrans if block averaging has been performed.
Ntrans	number of dynamic scans acquired.
resp_fn	a data frame specifying the response function to be convolved.
match_tr	match the output to the input mrs_data.
normalise	normalise the response function to have a maximum value of one.

Value

BOLD regressor data frame.

gen_F *Generate the F product operator.*

Description

Generate the F product operator.

Usage

```
gen_F(sys, op, detect = NULL)
```

Arguments

sys	spin system object.
op	operator, one of "x", "y", "z", "p", "m".
detect	detection nuclei.

Value

F product operator matrix.

gen_F_xy *Generate the Fxy product operator with a specified phase.*

Description

Generate the Fxy product operator with a specified phase.

Usage

```
gen_F_xy(sys, phase, detect = NULL)
```

Arguments

sys	spin system object.
phase	phase angle in degrees.
detect	detection nuclei.

Value

product operator matrix.

gen_group_reg	<i>Expand a regressor matrix for a group analysis.</i>
---------------	--

Description

Expand a regressor matrix for a group analysis.

Usage

```
gen_group_reg(regressor_df, n)
```

Arguments

regressor_df	input regressor data frame.
n	number of datasets n the group.

gen_I	<i>Generate the I product operator for a single spin.</i>
-------	---

Description

Generate the I product operator for a single spin.

Usage

```
gen_I(n, spin_num, op)
```

Arguments

n	spin index number for the required operator.
spin_num	vector of spin numbers in the system.
op	operator, one of "x", "y", "z", "p", "m".

Value

I product operator matrix.

gen_impulse_reg *Generate impulse regressors.*

Description

Generate impulse regressors.

Usage

```
gen_impulse_reg(
  onset,
  trial_type = NULL,
  mrs_data = NULL,
  tr = NULL,
  Ndyns = NULL,
  Ntrans = NULL
)
```

Arguments

onset	stimulus onset in seconds.
trial_type	string label for the stimulus.
mrs_data	mrs_data object for timing information.
tr	repetition time.
Ndyns	number of dynamic scans stored, potentially less than Ntrans if block averaging has been performed.
Ntrans	number of dynamic scans acquired.

Value

impulse regressors data frame.

gen_poly_reg *Generate polynomial regressors.*

Description

Generate polynomial regressors.

Usage

```
gen_poly_reg(degree, mrs_data = NULL, tr = NULL, Ndyns = NULL, Ntrans = NULL)
```

Arguments

degree	the degree of the polynomial.
mrs_data	mrs_data object for timing information.
tr	repetition time.
Ndysns	number of dynamic scans stored, potentially less than Ntrans if block averaging has been performed.
Ntrans	number of dynamic scans acquired.

Value

polynomial regressors.

gen_trap_reg	<i>Generate trapezoidal regressors.</i>
--------------	---

Description

Generate trapezoidal regressors.

Usage

```
gen_trap_reg(
  onset,
  duration,
  trial_type = NULL,
  mrs_data = NULL,
  tr = NULL,
  Ndysns = NULL,
  Ntrans = NULL,
  rise_t = 0,
  fall_t = 0,
  exp_fall = FALSE,
  exp_fall_power = 1,
  smo_sigma = NULL,
  match_tr = TRUE,
  dt = 0.01,
  normalise = FALSE
)
```

Arguments

onset	stimulus onset in seconds.
duration	stimulus duration in seconds.
trial_type	string label for the stimulus.
mrs_data	mrs_data object for timing information.

tr	repetition time.
Ndysn	number of dynamic scans stored, potentially less than Ntrans if block averaging has been performed.
Ntrans	number of dynamic scans acquired.
rise_t	time to reach a plateau from baseline in seconds.
fall_t	time to fall from plateau level back to baseline in seconds.
exp_fall	model an exponential fall instead of linear.
exp_fall_power	exponential fall power.
smo_sigma	standard deviation of Gaussian smoothing kernel in seconds. Set to NULL to disable (default behavior).
match_tr	match the output to the input mrs_data.
dt	timing resolution for internal calculations.
normalise	normalise the response function to have a maximum value of one.

Value

trapezoidal regressor data frame.

get_1h_braino_basis_names

Return a character vector of molecules included in the GE BRAINO phantom.

Description

Return a character vector of molecules included in the GE BRAINO phantom.

Usage

```
get_1h_braino_basis_names()
```

Value

a character vector of molecule names.

get_1h_brain_basis_names

Return a character vector of common 1H molecules found in healthy human brain.

Description

Note, this is a basic set and it may be appropriate to also include Asc, Gly and PEth for high quality MRS data.

Usage

```
get_1h_brain_basis_names(add = NULL, remove = NULL, inc_lip_mm = TRUE)
```

Arguments

add	optional character vector of additional molecular names. Eg c("asc", "gly", "peth").
remove	optional character vector of molecular names to remove from the set. Eg c("m_cr_ch2").
inc_lip_mm	include Lipid and MM basis signals.

Value

a character vector of molecule names.

get_1h_brain_basis_paras

Return a list of mol_parameter objects suitable for 1H brain MRS analyses.

Description

Return a list of mol_parameter objects suitable for 1H brain MRS analyses.

Usage

```
get_1h_brain_basis_paras(ft, metab_lw = NULL, lcm_compat = FALSE)
```

Arguments

ft	transmitter frequency in Hz.
metab_lw	linewidth of metabolite signals (Hz).
lcm_compat	when TRUE, lipid, MM and -CrCH molecules will be excluded from the output.

Value

list of mol_parameter objects.

get_1h_brain_basis_paras_v1

Return a list of mol_parameter objects suitable for 1H brain MRS analyses.

Description

Return a list of mol_parameter objects suitable for 1H brain MRS analyses.

Usage

```
get_1h_brain_basis_paras_v1(ft, metab_lw = NULL, lcm_compat = FALSE)
```

Arguments

ft	transmitter frequency in Hz.
metab_lw	linewidth of metabolite signals (Hz).
lcm_compat	when TRUE, lipid, MM and -CrCH molecules will be excluded from the output.

Value

list of mol_parameter objects.

get_1h_brain_basis_paras_v2

Return a list of mol_parameter objects suitable for 1H brain MRS analyses.

Description

Return a list of mol_parameter objects suitable for 1H brain MRS analyses.

Usage

```
get_1h_brain_basis_paras_v2(ft, metab_lw = NULL, lcm_compat = FALSE)
```

Arguments

ft	transmitter frequency in Hz.
metab_lw	linewidth of metabolite signals (Hz).
lcm_compat	when TRUE, lipid, MM and -CrCH molecules will be excluded from the output.

Value

list of mol_parameter objects.

get_1h_brain_basis_paras_v3

Return a list of mol_parameter objects suitable for 1H brain MRS analyses.

Description

Return a list of mol_parameter objects suitable for 1H brain MRS analyses.

Usage

```
get_1h_brain_basis_paras_v3(ft, metab_lw = NULL, lcm_compat = FALSE)
```

Arguments

ft	transmitter frequency in Hz.
metab_lw	linewidth of metabolite signals (Hz).
lcm_compat	when TRUE, lipid, MM and -CrCH molecules will be excluded from the output.

Value

list of mol_parameter objects.

get_1h_spectre_basis_names

Return a character vector of molecules included in the Gold Star Phantoms SPECTRE phantom.

Description

Return a character vector of molecules included in the Gold Star Phantoms SPECTRE phantom.

Usage

```
get_1h_spectre_basis_names()
```

Value

a character vector of molecule names.

get_2d_psf	<i>Get the point spread function (PSF) for a 2D phase encoded MRSI scan.</i>
------------	--

Description

Get the point spread function (PSF) for a 2D phase encoded MRSI scan.

Usage

```
get_2d_psf(
    FOV = 160,
    mat_size = 16,
    sampling = "circ",
    hamming = FALSE,
    ensure_odd = TRUE
)
```

Arguments

FOV	field of view in mm.
mat_size	acquisition matrix size (not interpolated).
sampling	can be either "circ" for circular or "rect" for rectangular.
hamming	should Hamming k-space weighting be applied (default FALSE).
ensure_odd	add 1mm to the FOV when required to ensure the output pdf has odd dimensions. Required when using get_mrsi2d_seg.

Value

A matrix of the PSF with 1mm resolution.

get_acq_paras	<i>Return acquisition parameters from a MRS data object.</i>
---------------	--

Description

Return acquisition parameters from a MRS data object.

Usage

```
get_acq_paras(mrs_data)
```

Arguments

mrs_data	MRS data.
----------	-----------

Value

list of acquisition parameters.

get_basis_subset *Return a subset of the input basis.*

Description

Return a subset of the input basis.

Usage

```
get_basis_subset(basis, names, invert = FALSE)
```

Arguments

basis	input basis.
names	basis set elements to keep in the returned object.
invert	set to true to return all basis elements except those given in the names argument.

Value

a subset of the input basis.

get_dyns *Extract a subset of dynamic scans.*

Description

Extract a subset of dynamic scans.

Usage

```
get_dyns(mrs_data, subset)
```

Arguments

mrs_data	dynamic MRS data.
subset	vector containing indices to the dynamic scans to be returned.

Value

MRS data containing the subset of requested dynamics.

get_even_dyns	<i>Return even numbered dynamic scans starting from 1 (2,4,6...).</i>
---------------	---

Description

Return even numbered dynamic scans starting from 1 (2,4,6...).

Usage

```
get_even_dyns(mrs_data)
```

Arguments

mrs_data dynamic MRS data.

Value

dynamic MRS data containing even numbered scans.

get_fh_dyns	<i>Return the first half of a dynamic series.</i>
-------------	---

Description

Return the first half of a dynamic series.

Usage

```
get_fh_dyns(mrs_data)
```

Arguments

mrs_data dynamic MRS data.

Value

first half of the dynamic series.

get_fit_map	<i>Get a data array from a fit result.</i>
-------------	--

Description

Get a data array from a fit result.

Usage

```
get_fit_map(fit_res, name)
```

Arguments

fit_res	fit_result object.
name	name of the quantity to plot, eg "tNAA".

get_fp	<i>Return the first time-domain data point.</i>
--------	---

Description

Return the first time-domain data point.

Usage

```
get_fp(mrs_data)
```

Arguments

mrs_data	MRS data.
----------	-----------

Value

first time-domain data point.

get_guassian_pulse *Generate a gaussian pulse shape.*

Description

Generate a gaussian pulse shape.

Usage

```
get_guassian_pulse(angle, n, trunc = 1)
```

Arguments

angle	pulse angle in degrees.
n	number of points to generate.
trunc	percentage truncation factor.

get_head_dyns *Return the first scans of a dynamic series.*

Description

Return the first scans of a dynamic series.

Usage

```
get_head_dyns(mrs_data, n = 1)
```

Arguments

mrs_data	dynamic MRS data.
n	the number of dynamic scans to return.

Value

first scans of a dynamic series.

get_hrf	<i>Generate a double gamma model of the HRF as used in SPM.</i>
---------	---

Description

Generate a double gamma model of the HRF as used in SPM.

Usage

```
get_hrf(end_t = 30, res_t = 0.01)
```

Arguments

end_t	last time point to generate in seconds.
res_t	temporal resolution in seconds, defaults to 10ms.

Value

a data.frame of time and HRF vectors.

get_lcm_cmd	<i>Print the command to run the LCModel command-line program.</i>
-------------	---

Description

Print the command to run the LCModel command-line program.

Usage

```
get_lcm_cmd()
```

get_metab	<i>Extract the metabolite component from an mrs_data object.</i>
-----------	--

Description

Extract the metabolite component from an mrs_data object.

Usage

```
get_metab(mrs_data)
```

Arguments

mrs_data MRS data.

Value

metabolite component.

get_mol_names	<i>Return a character array of names that may be used with the get_mol_paras function.</i>
---------------	--

Description

Return a character array of names that may be used with the get_mol_paras function.

Usage

```
get_mol_names()
```

Value

a character array of names.

get_mol_paras	<i>Get a mol_parameters object for a named molecule.</i>
---------------	--

Description

Get a mol_parameters object for a named molecule.

Usage

```
get_mol_paras(name, ...)
```

Arguments

name the name of the molecule.
... arguments to pass to molecule definition function.

get_mrsi2d_seg	<i>Calculate the partial volume estimates for each voxel in a 2D MRSI dataset.</i>
----------------	--

Description

Localisation is assumed to be perfect in the z direction and determined by the ker input in the x-y direction.

Usage

```
get_mrsi2d_seg(mrs_data, mri_seg, ker)
```

Arguments

mrs_data	2D MRSI data with multiple voxels in the x-y dimension.
mri_seg	MRI data with values corresponding to the segmentation class. Must be 1mm isotropic resolution.
ker	MRSI PSF kernel in the x-y direction compatible with the mmand package, eg: mmand::shapeKernel(c(10, 10), type = "box").

Value

a data frame of partial volume estimates and individual segmentation maps.

get_mrsi_voi	<i>Generate a MRSI VOI from an mrs_data object.</i>
--------------	---

Description

Generate a MRSI VOI from an mrs_data object.

Usage

```
get_mrsi_voi(mrs_data, target_mri = NULL, map = NULL, ker = mmand::boxKernel())
```

Arguments

mrs_data	MRS data.
target_mri	optional image data to match the intended volume space.
map	optional voi intensity map.
ker	kernel to rescale the map data to the target_mri. Default value is mmand::boxKernel(), use mmand::mnKernel() for a smoothed map.

Value

volume data as a nifti object.

get_mrsi_voxel *Generate a MRSI voxel from an mrs_data object.*

Description

Generate a MRSI voxel from an mrs_data object.

Usage

```
get_mrsi_voxel(mrs_data, target_mri, x_pos, y_pos, z_pos)
```

Arguments

mrs_data	MRS data.
target_mri	optional image data to match the intended volume space.
x_pos	x voxel coordinate.
y_pos	y voxel coordinate.
z_pos	z voxel coordinate.

Value

volume data as a nifti object.

get_mrsi_voxel_xy_psf *Generate a MRSI voxel PSF from an mrs_data object.*

Description

Generate a MRSI voxel PSF from an mrs_data object.

Usage

```
get_mrsi_voxel_xy_psf(mrs_data, target_mri, x_pos, y_pos, z_pos)
```

Arguments

mrs_data	MRS data.
target_mri	optional image data to match the intended volume space.
x_pos	x voxel coordinate.
y_pos	y voxel coordinate.
z_pos	z voxel coordinate.

Value

volume data as a nifti object.

get_mrs_affine *Generate an affine for nifti generation.*

Description

Generate an affine for nifti generation.

Usage

```
get_mrs_affine(mrs_data, x_pos = 1, y_pos = 1, z_pos = 1)
```

Arguments

mrs_data	input data.
x_pos	x_position coordinate.
y_pos	y_position coordinate.
z_pos	z_position coordinate.

Value

affine matrix.

get_odd_dyns *Return odd numbered dynamic scans starting from 1 (1,3,5...).*

Description

Return odd numbered dynamic scans starting from 1 (1,3,5...).

Usage

```
get_odd_dyns(mrs_data)
```

Arguments

mrs_data	dynamic MRS data.
----------	-------------------

Value

dynamic MRS data containing odd numbered scans.

get_ref	<i>Extract the reference component from an mrs_data object.</i>
---------	---

Description

Extract the reference component from an mrs_data object.

Usage

```
get_ref(mrs_data)
```

Arguments

mrs_data	MRS data.
----------	-----------

Value

reference component.

get_seg_ind	<i>Get the indices of data points lying between two values (end > x > start).</i>
-------------	---

Description

Get the indices of data points lying between two values (end > x > start).

Usage

```
get_seg_ind(scale, start, end)
```

Arguments

scale	full list of values.
start	smallest value in the subset.
end	largest value in the subset.

Value

set of indices.

get_sh_dyns	<i>Return the second half of a dynamic series.</i>
-------------	--

Description

Return the second half of a dynamic series.

Usage

```
get_sh_dyns(mrs_data)
```

Arguments

mrs_data	dynamic MRS data.
----------	-------------------

Value

second half of the dynamic series.

get_slice	<i>Return a single slice from a larger MRSI dataset.</i>
-----------	--

Description

Return a single slice from a larger MRSI dataset.

Usage

```
get_slice(mrs_data, z_pos)
```

Arguments

mrs_data	MRSI data.
z_pos	the z index to extract.

Value

MRS data.

get_spin_num	<i>Return the spin number for a given nucleus.</i>
--------------	--

Description

Return the spin number for a given nucleus.

Usage

```
get_spin_num(nucleus)
```

Arguments

nucleus	nucleus name, eg "1H".
---------	------------------------

Value

spin number.

get_subset	<i>Extract a subset of MRS data.</i>
------------	--------------------------------------

Description

Extract a subset of MRS data.

Usage

```
get_subset(  
  mrs_data,  
  x_set = NULL,  
  y_set = NULL,  
  z_set = NULL,  
  dyn_set = NULL,  
  coil_set = NULL,  
  fd_set = NULL,  
  td_set = NULL  
)
```

Arguments

<code>mrs_data</code>	MRS data object.
<code>x_set</code>	x indices to include in the output (default all).
<code>y_set</code>	y indices to include in the output (default all).
<code>z_set</code>	z indices to include in the output (default all).
<code>dyn_set</code>	dynamic indices to include in the output (default all).
<code>coil_set</code>	coil indices to include in the output (default all).
<code>fd_set</code>	frequency domain data indices to include in the output (default all).
<code>td_set</code>	time-domain indices to include in the output (default all).

Value

selected subset of MRS data.

`get_svs_voi`*Generate a SVS acquisition volume from an `mrs_data` object.*

Description

Generate a SVS acquisition volume from an `mrs_data` object.

Usage

```
get_svs_voi(mrs_data, target_mri)
```

Arguments

<code>mrs_data</code>	MRS data.
<code>target_mri</code>	optional image data to match the intended volume space.

Value

volume data as a nifti object.

get_tail_dyns	<i>Return the last scans of a dynamic series.</i>
---------------	---

Description

Return the last scans of a dynamic series.

Usage

```
get_tail_dyns(mrs_data, n = 1)
```

Arguments

mrs_data	dynamic MRS data.
n	the number of dynamic scans to return.

Value

last scans of a dynamic series.

get_td_amp	<i>Return an array of amplitudes derived from fitting the initial points in the time domain and extrapolating back to t=0.</i>
------------	--

Description

Return an array of amplitudes derived from fitting the initial points in the time domain and extrapolating back to t=0.

Usage

```
get_td_amp(mrs_data, nstart = 10, nend = 50, method = "poly")
```

Arguments

mrs_data	MRS data.
nstart	first data point to fit.
nend	last data point to fit.
method	method for measuring the amplitude, one of "poly", "spline" or "exp".

Value

array of amplitudes.

get_tqn_cmd	<i>Print the command to run the TARQUIN command-line program.</i>
-------------	---

Description

Print the command to run the TARQUIN command-line program.

Usage

```
get_tqn_cmd()
```

get_uncoupled_mol	<i>Generate a mol_parameters object for a simple spin system with one resonance.</i>
-------------------	--

Description

Generate a mol_parameters object for a simple spin system with one resonance.

Usage

```
get_uncoupled_mol(
    name,
    chem_shift,
    nucleus,
    scale_factor,
    lw,
    lg,
    full_name = NULL
)
```

Arguments

name	abbreviated name of the molecule.
chem_shift	chemical shift of the resonance (PPM).
nucleus	nucleus (1H, 31P...).
scale_factor	multiplicative scaling factor. Note, this value can be made complex to adjust the phase of the resonance.
lw	linewidth in Hz.
lg	Lorentz-Gauss lineshape parameter (between 0 and 1).
full_name	long name of the molecule (optional).

Value

mol_parameters object.

get_voi_cog	<i>Calculate the centre of gravity for an image containing 0 and 1's.</i>
-------------	---

Description

Calculate the centre of gravity for an image containing 0 and 1's.

Usage

```
get_voi_cog(voi)
```

Arguments

voi nifti object.

Value

triplet of x,y,z coordinates.

get_voi_seg	<i>Return the white matter, gray matter and CSF composition of a volume.</i>
-------------	--

Description

Return the white matter, gray matter and CSF composition of a volume.

Usage

```
get_voi_seg(voi, mri_seg)
```

Arguments

voi volume data as a nifti object.
mri_seg segmented brain volume as a nifti object.

Value

a vector of partial volumes expressed as percentages.

get_voi_seg_psf	<i>Return the white matter, gray matter and CSF composition of a volume.</i>
-----------------	--

Description

Return the white matter, gray matter and CSF composition of a volume.

Usage

```
get_voi_seg_psf(psf, mri_seg)
```

Arguments

psf	volume data as a nifti object.
mri_seg	segmented brain volume as a nifti object.

Value

a vector of partial volumes expressed as percentages.

get_voxel	<i>Return a single voxel from a larger mrs dataset.</i>
-----------	---

Description

Return a single voxel from a larger mrs dataset.

Usage

```
get_voxel(mrs_data, x_pos = 1, y_pos = 1, z_pos = 1, dyn = 1, coil = 1)
```

Arguments

mrs_data	MRS data.
x_pos	the x index to plot.
y_pos	the y index to plot.
z_pos	the z index to plot.
dyn	the dynamic index to plot.
coil	the coil element number to plot.

Value

MRS data.

glm_spec	<i>Perform a GLM analysis of dynamic MRS data in the spectral domain.</i>
----------	---

Description

Perform a GLM analysis of dynamic MRS data in the spectral domain.

Usage

```
glm_spec(mrs_data, regressor_df, full_output = FALSE)
```

Arguments

mrs_data	single-voxel dynamics MRS data.
regressor_df	a data frame containing temporal regressors to be applied to each spectral data-point.
full_output	append mrs_data and regressor_df to the output list.

Value

list of statistical results.

glm_spec_fmrs_fl	<i>Perform first-level spectral GLM analysis of an fMRS dataset.</i>
------------------	--

Description

Perform first-level spectral GLM analysis of an fMRS dataset.

Usage

```
glm_spec_fmrs_fl(
  regressor_df,
  analysis_dir = "spant_analysis",
  exclude_labels = NULL,
  labels = NULL,
  xlim = c(4, 0.2),
  vline = c(1.35, 1.28, 2.35, 2.29),
  return_results = FALSE
)
```

Arguments

regressor_df	a data frame containing temporal regressors to be applied to each spectral data-point.
analysis_dir	directory containing preprocessed data generated by the preproc_svs_dataset function.
exclude_labels	vector of labels of scans to exclude, eg poor quality data.
labels	labels to describe each data set.
xlim	spectral range to include in the analysis.
vline	vertical lines to add to the plot.
return_results	function will return key outputs, defaults to FALSE.

glm_spec_fmrs_group *Perform group-level spectral GLM analysis of an fMRS dataset.*

Description

Perform group-level spectral GLM analysis of an fMRS dataset.

Usage

```
glm_spec_fmrs_group(  
  regressor_df,  
  analysis_dir = "spant_analysis",  
  exclude_labels = NULL,  
  labels = NULL  
)
```

Arguments

regressor_df	a data frame containing temporal regressors to be applied to each spectral data-point.
analysis_dir	directory containing preprocessed data generated by the preproc_svs_dataset function.
exclude_labels	vector of labels of scans to exclude, eg poor quality data.
labels	labels to describe each data set.

glm_spec_group_linhyp *Test a group-level spectral GLM linear hypothesis.*

Description

Test a group-level spectral GLM linear hypothesis.

Usage

```
glm_spec_group_linhyp(hmat, analysis_dir = "spant_analysis")
```

Arguments

hmat	linear hypothesis matrix.
analysis_dir	directory containing preprocessed data generated by the <code>preproc_svs_dataset</code> function.

gridplot *Arrange spectral plots in a grid.*

Description

Arrange spectral plots in a grid.

Usage

```
gridplot(x, ...)
```

Arguments

x	object for plotting.
...	arguments to be passed to methods.

gridplot.mrs_data *Arrange spectral plots in a grid.*

Description

Arrange spectral plots in a grid.

Usage

```
## S3 method for class 'mrs_data'
gridplot(
  x,
  rows = NA,
  cols = NA,
  mar = c(0, 0, 0, 0),
  oma = c(3.5, 1, 1, 1),
  bty = "o",
  restore_def_par = TRUE,
  ...
)
```

Arguments

x	object of class <code>mrs_data</code> .
rows	number of grid rows.
cols	number of grid columns.
mar	option to adjust the plot margins. See <code>?par</code> .
oma	outer margin area.
bty	option to draw a box around the plot. See <code>?par</code> .
restore_def_par	restore default plotting par values after the plot has been made.
...	other arguments to pass to the plot method.

grid_shift_xy *Grid shift MRSI data in the x/y dimension.*

Description

Grid shift MRSI data in the x/y dimension.

Usage

```
grid_shift_xy(mrs_data, x_shift, y_shift)
```

Arguments

<code>mrs_data</code>	MRSI data in the spatial domain.
<code>x_shift</code>	shift to apply in the x-direction in units of voxels.
<code>y_shift</code>	shift to apply in the y-direction in units of voxels.

Value

shifted data.

<code>hsvd</code>	<i>HSVD of an <code>mrs_data</code> object.</i>
-------------------	---

Description

HSVD method as described in: Barkhuijsen H, de Beer R, van Ormondt D. Improved algorithm for noniterative and timedomain model fitting to exponentially damped magnetic resonance signals. J Magn Reson 1987;73:553-557.

Usage

```
hsvd(mrs_data, comps = 40, irlba = TRUE, max_damp = 10)
```

Arguments

<code>mrs_data</code>	<code>mrs_data</code> object to be decomposed.
<code>comps</code>	number of Lorentzian components to use for modelling.
<code>irlba</code>	option to use irlba SVD (logical).
<code>max_damp</code>	maximum allowable damping factor.

Value

basis matrix and signal table.

hsvd_filt	<i>HSVD based signal filter.</i>
-----------	----------------------------------

Description

HSVD based signal filter described in: Barkhuijsen H, de Beer R, van Ormondt D. Improved algorithm for noniterative and timedomain model fitting to exponentially damped magnetic resonance signals. J Magn Reson 1987;73:553-557.

Usage

```
hsvd_filt(  
  mrs_data,  
  xlim = c(-30, 30),  
  comps = 40,  
  irlba = TRUE,  
  max_damp = 10,  
  scale = "hz",  
  return_model = FALSE  
)
```

Arguments

mrs_data	MRS data to be filtered.
xlim	frequency range to filter, default units are Hz which can be changed to ppm using the "scale" argument.
comps	number of Lorentzian components to use for modelling.
irlba	option to use irlba SVD (logical).
max_damp	maximum allowable damping factor.
scale	either "hz" or "ppm" to set the frequency units of xlim.
return_model	by default the filtered spectrum is returned. Set return_model to TRUE to return the HSVD model of the data.

Value

filtered data or model depending on the return_model argument.

hsvd_vec	<i>HSVD of a complex vector.</i>
----------	----------------------------------

Description

HSVD method as described in: Barkhuijsen H, de Beer R, van Ormondt D. Improved algorithm for noniterative and timedomain model fitting to exponentially damped magnetic resonance signals. J Magn Reson 1987;73:553-557.

Usage

```
hsvd_vec(y, fs, comps = 40, irlba = TRUE, max_damp = 0)
```

Arguments

y	time domain signal to be filtered as a vector.
fs	sampling frequency of y.
comps	number of Lorentzian components to use for modelling.
irlba	option to use irlba SVD (logical).
max_damp	maximum allowable damping factor. Default value of 0 ensures resultant model is damped.

Value

basis matrix and signal table.

hz	<i>Return the frequency scale of an MRS dataset in Hz.</i>
----	--

Description

Return the frequency scale of an MRS dataset in Hz.

Usage

```
hz(mrs_data, fs = NULL, N = NULL)
```

Arguments

mrs_data	MRS data.
fs	sampling frequency in Hz.
N	number of data points in the spectral dimension.

Value

frequency scale.

ift_shift	<i>Perform an iffshift and ifft on a vector.</i>
-----------	--

Description

Perform an iffshift and ifft on a vector.

Usage

```
ift_shift(vec_in)
```

Arguments

vec_in vector input.

Value

output vector.

ift_shift_mat	<i>Perform an ifft and ifftshift on a matrix with each column replaced by its shifted ifft.</i>
---------------	---

Description

Perform an ifft and ifftshift on a matrix with each column replaced by its shifted ifft.

Usage

```
ift_shift_mat(mat_in)
```

Arguments

mat_in matrix input.

Value

output matrix.

Im.mrs_data	<i>Apply Im operator to an MRS dataset.</i>
-------------	---

Description

Apply Im operator to an MRS dataset.

Usage

```
## S3 method for class 'mrs_data'  
Im(z)
```

Arguments

z MRS data.

Value

MRS data following Im operator.

image.mrs_data	<i>Image plot method for objects of class mrs_data.</i>
----------------	---

Description

Image plot method for objects of class mrs_data.

Usage

```
## S3 method for class 'mrs_data'  
image(  
  x,  
  xlim = NULL,  
  mode = "re",  
  col = NULL,  
  plot_dim = NULL,  
  x_pos = NULL,  
  y_pos = NULL,  
  z_pos = NULL,  
  dyn = 1,  
  coil = 1,  
  restore_def_par = TRUE,  
  y_ticks = NULL,  
  hline = NULL,  
  hline_lty = 2,  
  hline_col = "white",
```

```

    vline = NULL,
    vline_lty = 2,
    vline_col = "white",
    legend = FALSE,
    ...
)

```

Arguments

x	object of class <code>mrs_data</code> .
xlim	the range of values to display on the x-axis, eg <code>xlim = c(4,1)</code> .
mode	representation of the complex numbers to be plotted, can be one of: "re", "im", "mod" or "arg".
col	Colour map to use, defaults to <code>viridis</code> .
plot_dim	the dimension to display on the y-axis, can be one of: "dyn", "time_sec", "x", "y", "z", "coil" or <code>NULL</code> . If <code>NULL</code> (the default) all spectra are collapsed into the dynamic dimension and displayed.
x_pos	the x index to plot.
y_pos	the y index to plot.
z_pos	the z index to plot.
dyn	the dynamic index to plot.
coil	the coil element number to plot.
restore_def_par	restore default plotting par values after the plot has been made.
y_ticks	a vector of indices specifying where to place additional red tick marks.
hline	add a horizontal line at the specified value.
hline_lty	linetype for the horizontal line.
hline_col	colour for the horizontal line.
vline	add a vertical line at the specified value.
vline_lty	linetype for the vertical line.
vline_col	colour for the vertical line.
legend	add a colour bar to the plot using the <code>imagePlot</code> function from the <code>fields</code> package.
...	other arguments to pass to the plot method.

img2kspace_xy	<i>Transform 2D MRSI data to k-space in the x-y direction.</i>
---------------	--

Description

Transform 2D MRSI data to k-space in the x-y direction.

Usage

```
img2kspace_xy(mrs_data)
```

Arguments

mrs_data	2D MRSI data.
----------	---------------

Value

k-space data.

Imzap	<i>Complex rounding function taken from complexplus package to reduce the number of spant dependencies.</i>
-------	---

Description

Complex rounding function taken from complexplus package to reduce the number of spant dependencies.

Usage

```
Imzap(x, tol = 1e-06)
```

Arguments

x	a scalar or vector, real or complex.
tol	a tolerance, 10^{-6} by default. Prevents possible numerical problems. Can be set to 0 if desired.

install_cli	<i>Install the spant command-line interface scripts to a system path.</i>
-------------	---

Description

This should be run following each new install of spant to ensure consistency. Typical command line usage : `sudo Rscript -e "spant::install_cli()"`

Usage

```
install_cli(path = NULL)
```

Arguments

path optional path to install the scripts. Defaults to : `"/usr/local/bin"`.

interleave_dyns	<i>Interleave the first and second half of a dynamic series.</i>
-----------------	--

Description

Interleave the first and second half of a dynamic series.

Usage

```
interleave_dyns(mrs_data)
```

Arguments

mrs_data dynamic MRS data.

Value

interleaved data.

int_spec	<i>Integrate a spectral region.</i>
----------	-------------------------------------

Description

See spec_op function for a more complete set of spectral operations.

Usage

```
int_spec(mrs_data, xlim = NULL, freq_scale = "ppm", mode = "re")
```

Arguments

mrs_data	MRS data.
xlim	spectral range to be integrated (defaults to full range).
freq_scale	units of xlim, can be : "ppm", "hz" or "points".
mode	spectral mode, can be : "re", "im", "mod" or "cplx".

Value

an array of integral values.

inv_even_dyns	<i>Invert even numbered dynamic scans starting from 1 (2,4,6...).</i>
---------------	---

Description

Invert even numbered dynamic scans starting from 1 (2,4,6...).

Usage

```
inv_even_dyns(mrs_data)
```

Arguments

mrs_data	dynamic MRS data.
----------	-------------------

Value

dynamic MRS data with inverted even numbered scans.

inv_odd_dyns *Invert odd numbered dynamic scans starting from 1 (1,3,5...).*

Description

Invert odd numbered dynamic scans starting from 1 (1,3,5...).

Usage

```
inv_odd_dyns(mrs_data)
```

Arguments

mrs_data dynamic MRS data.

Value

dynamic MRS data with inverted odd numbered scans.

is.def *Check if an object is defined, which is the same as being not NULL.*

Description

Check if an object is defined, which is the same as being not NULL.

Usage

```
is.def(x)
```

Arguments

x object to test for being NULL.

Value

logical value.

is_fd	<i>Check if the chemical shift dimension of an MRS data object is in the frequency domain.</i>
-------	--

Description

Check if the chemical shift dimension of an MRS data object is in the frequency domain.

Usage

```
is_fd(mrs_data)
```

Arguments

mrs_data	MRS data.
----------	-----------

Value

logical value.

kspace2img_xy	<i>Transform 2D MRSI data from k-space to image space in the x-y direction.</i>
---------------	---

Description

Transform 2D MRSI data from k-space to image space in the x-y direction.

Usage

```
kspace2img_xy(mrs_data)
```

Arguments

mrs_data	2D MRSI data.
----------	---------------

Value

MRSI data in image space.

`l2_reg`*Perform l2 regularisation artefact suppression.*

Description

Perform l2 regularisation artefact suppression using the method proposed by Bilgic et al. JMRI 40(1):181-91 2014.

Usage

```
l2_reg(  
  mrs_data,  
  thresh = 0.05,  
  b = 1e-11,  
  A = NA,  
  xlim = NA,  
  thresh_xlim = NULL,  
  A_append = NULL,  
  ret_norms = FALSE  
)
```

Arguments

<code>mrs_data</code>	input data for artefact suppression.
<code>thresh</code>	threshold parameter to extract lipid signals from <code>mrs_data</code> based on the spectral integration of the <code>thresh_xlim</code> region in magnitude mode.
<code>b</code>	regularisation parameter.
<code>A</code>	set of spectra containing the artefact basis signals. The <code>thresh</code> parameter is ignored when <code>A</code> is specified.
<code>xlim</code>	spectral limits in ppm to restrict the reconstruction range. Defaults to the full spectral width.
<code>thresh_xlim</code>	spectral limits in ppm to integrate for the threshold map.
<code>A_append</code>	additional spectra to append to the <code>A</code> basis.
<code>ret_norms</code>	return the residual norm and solution norms.

Value

l2 reconstructed `mrs_data` object.

lb	<i>Apply line-broadening (apodisation) to MRS data or basis object.</i>
----	---

Description

Apply line-broadening (apodisation) to MRS data or basis object.

Usage

```
lb(x, lb, lg = 1)

## S3 method for class 'list'
lb(x, lb, lg = 1)

## S3 method for class 'mrs_data'
lb(x, lb, lg = 1)

## S3 method for class 'basis_set'
lb(x, lb, lg = 1)
```

Arguments

x	input mrs_data or basis_set object.
lb	amount of line-broadening in Hz.
lg	Lorentz-Gauss lineshape parameter (between 0 and 1).

Value

line-broadened data.

lofdc	<i>Correct linear frequency drift.</i>
-------	--

Description

Correct linear frequency drift.

Usage

```
lofdc(
  mrs_data,
  max_hz_s = 0.1,
  tr = NULL,
  ret_corr_only = TRUE,
  outlier_thresh = 3,
```

```

    xlim = c(4, 0.5),
    order = 1
  )

```

Arguments

mrs_data MRS data to be corrected.
max_hz_s the maximum drift rate to search over.
tr mrs_data repetition time.
ret_corr_only return the corrected mrs_data object only.
outlier_thresh threshold to remove outliers.
xlim spectral width (in ppm) to evaluate outliers.
order correction order.

Value

drift corrected mrs_data object.

lw2alpha	<i>Covert a linewidth in Hz to an equivalent alpha value in the time-domain ie: $x * \exp(-t * \alpha)$.</i>
----------	---

Description

Covert a linewidth in Hz to an equivalent alpha value in the time-domain ie: $x * \exp(-t * \alpha)$.

Usage

```
lw2alpha(lw)
```

Arguments

lw linewidth in Hz.

Value

beta damping value.

lw2beta	<i>Covert a linewidth in Hz to an equivalent beta value in the time-domain ie: $x * \exp(-t * t * \text{beta})$.</i>
---------	---

Description

Covert a linewidth in Hz to an equivalent beta value in the time-domain ie: $x * \exp(-t * t * \text{beta})$.

Usage

```
lw2beta(lw)
```

Arguments

lw	linewidth in Hz.
----	------------------

Value

beta damping value.

make_basis_from_raw	<i>Make a basis-set object from a directory containing LCModel formatted RAW files.</i>
---------------------	---

Description

Make a basis-set object from a directory containing LCModel formatted RAW files.

Usage

```
make_basis_from_raw(dir_path, ft, fs, ref)
```

Arguments

dir_path	path to the directory containing LCModel RAW files. One file per signal.
ft	transmitter frequency in Hz.
fs	sampling frequency in Hz.
ref	reference value for ppm scale.

Value

a basis-set object.

mask_dyns	<i>Mask an MRS dataset in the dynamic dimension.</i>
-----------	--

Description

Mask an MRS dataset in the dynamic dimension.

Usage

```
mask_dyns(mrs_data, mask)
```

Arguments

mrs_data	MRS data object.
mask	vector of boolean values specifying the dynamics to mask, where a value of TRUE indicates the spectrum should be removed.

Value

masked dataset.

mask_fit_res	<i>Mask fit result spectra depending on a vector of bool values.</i>
--------------	--

Description

Mask fit result spectra depending on a vector of bool values.

Usage

```
mask_fit_res(fit_result, mask_vec, amps_only = FALSE)
```

Arguments

fit_result	fit result object to be masked.
mask_vec	a Boolean vector with the same number of rows as there are rows in the results table.
amps_only	only mask the amplitude and associated error estimate columns.

Value

a masked fit result object.

mask_xy	<i>Mask an MRSI dataset in the x-y direction</i>
---------	--

Description

Mask an MRSI dataset in the x-y direction

Usage

```
mask_xy(mrs_data, x_dim, y_dim)
```

Arguments

mrs_data	MRS data object.
x_dim	x dimension output length.
y_dim	y dimension output length.

Value

masked MRS data.

mask_xy_corners	<i>Mask the four corners of an MRSI dataset in the x-y plane.</i>
-----------------	---

Description

Mask the four corners of an MRSI dataset in the x-y plane.

Usage

```
mask_xy_corners(mrs_data)
```

Arguments

mrs_data	MRS data object.
----------	------------------

Value

masked MRS data.

mask_xy_ellipse	<i>Mask the voxels outside an elliptical region spanning the MRSI dataset in the x-y plane.</i>
-----------------	---

Description

Mask the voxels outside an elliptical region spanning the MRSI dataset in the x-y plane.

Usage

```
mask_xy_ellipse(mrs_data)
```

Arguments

mrs_data	MRS data object.
----------	------------------

Value

masked MRS data.

mask_xy_mat	<i>Mask a 2D MRSI dataset in the x-y dimension.</i>
-------------	---

Description

Mask a 2D MRSI dataset in the x-y dimension.

Usage

```
mask_xy_mat(mrs_data, mask, value = NA)
```

Arguments

mrs_data	MRS data object.
mask	matrix of boolean values specifying the voxels to mask, where a value of TRUE indicates the voxel should be removed.
value	the value to set masked data to (usually NA or 0).

Value

masked dataset.

mat2mrs_data	<i>Convert a matrix (with spectral points in the column dimension and dynamics in the row dimensions) into a mrs_data object.</i>
--------------	---

Description

Convert a matrix (with spectral points in the column dimension and dynamics in the row dimensions) into a mrs_data object.

Usage

```
mat2mrs_data(
  mat,
  mrs_data = NULL,
  fs = NULL,
  ft = NULL,
  ref = NULL,
  nuc = NULL,
  fd = FALSE
)
```

Arguments

mat	data matrix.
mrs_data	example data to copy acquisition parameters from.
fs	sampling frequency in Hz.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
nuc	resonant nucleus.
fd	flag to indicate if the matrix is in the frequency domain (logical).

Value

mrs_data object.

matexp	<i>Matrix exponential function taken from complexplus package to reduce the number of spant dependencies.</i>
--------	---

Description

Matrix exponential function taken from complexplus package to reduce the number of spant dependencies.

Usage

```
matexp(x)
```

Arguments

x a square complex matrix.

Value

the matrix exponential of x.

max_mrs

Apply the max operator to an MRS dataset.

Description

Apply the max operator to an MRS dataset.

Usage

```
max_mrs(mrs_data)
```

Arguments

mrs_data MRS data.

Value

MRS data following max operator.

max_mrs_interp

Apply the max operator to an interpolated MRS dataset.

Description

Apply the max operator to an interpolated MRS dataset.

Usage

```
max_mrs_interp(mrs_data, interp_f = 4)
```

Arguments

mrs_data MRS data.
interp_f interpolation factor.

Value

Array of maximum values (real only).

mean.list	<i>Calculate the mean spectrum from an mrs_data object.</i>
-----------	---

Description

Calculate the mean spectrum from an mrs_data object.

Usage

```
## S3 method for class 'list'
mean(x, ...)
```

Arguments

x	object of class mrs_data.
...	other arguments to pass to the colMeans function.

Value

mean mrs_data object.

mean.mrs_data	<i>Calculate the mean spectrum from an mrs_data object.</i>
---------------	---

Description

Calculate the mean spectrum from an mrs_data object.

Usage

```
## S3 method for class 'mrs_data'
mean(x, ...)
```

Arguments

x	object of class mrs_data.
...	other arguments to pass to the colMeans function.

Value

mean mrs_data object.

mean_dyns	<i>Calculate the mean dynamic data.</i>
-----------	---

Description

Calculate the mean dynamic data.

Usage

```
mean_dyns(mrs_data, subset = NULL)
```

Arguments

mrs_data	dynamic MRS data.
subset	vector containing indices to the dynamic scans to be averaged.

Value

mean dynamic data.

mean_dyn_blocks	<i>Calculate the mean of adjacent dynamic scans.</i>
-----------------	--

Description

Calculate the mean of adjacent dynamic scans.

Usage

```
mean_dyn_blocks(mrs_data, block_size)
```

Arguments

mrs_data	dynamic MRS data.
block_size	number of adjacent dynamics scans to average over.

Value

dynamic data averaged in blocks.

mean_dyn_pairs	<i>Calculate the pairwise means across a dynamic data set.</i>
----------------	--

Description

Calculate the pairwise means across a dynamic data set.

Usage

```
mean_dyn_pairs(mrs_data)
```

Arguments

mrs_data dynamic MRS data.

Value

mean dynamic data of adjacent dynamic pairs.

mean_mrs_list	<i>Return the mean of a list of mrs_data objects.</i>
---------------	---

Description

Return the mean of a list of mrs_data objects.

Usage

```
mean_mrs_list(mrs_list)
```

Arguments

mrs_list list of mrs_data objects.

Value

mean mrs_data object.

mean_vec_blocks *Calculate the mean of adjacent blocks in a vector.*

Description

Calculate the mean of adjacent blocks in a vector.

Usage

```
mean_vec_blocks(x, block_size)
```

Arguments

x input vector.
block_size number of adjacent elements to average over.

Value

vector data averaged in blocks.

median_dyns *Calculate the median dynamic data.*

Description

Calculate the median dynamic data.

Usage

```
median_dyns(mrs_data)
```

Arguments

mrs_data dynamic MRS data.

Value

median dynamic data.

Mod.mrs_data	<i>Apply Mod operator to an MRS dataset.</i>
--------------	--

Description

Apply Mod operator to an MRS dataset.

Usage

```
## S3 method for class 'mrs_data'  
Mod(z)
```

Arguments

z MRS data.

Value

MRS data following Mod operator.

mod_td	<i>Apply the Modulus operator to the time-domain MRS signal.</i>
--------	--

Description

Apply the Modulus operator to the time-domain MRS signal.

Usage

```
mod_td(mrs_data)
```

Arguments

mrs_data MRS data input.

Value

time-domain modulus of input.

mrs_data2basis	<i>Convert an mrs_data object to basis object - where basis signals are spread across the dynamic dimension in the MRS data.</i>
----------------	--

Description

Convert an mrs_data object to basis object - where basis signals are spread across the dynamic dimension in the MRS data.

Usage

```
mrs_data2basis(mrs_data, names)
```

Arguments

mrs_data	mrs_data object with basis signals spread across the dynamic dimension.
names	list of names corresponding to basis signals.

Value

basis set object.

mrs_data2bids	<i>Create a BIDS file structure from a vector of MRS data paths or list of mrs_data objects.</i>
---------------	--

Description

Create a BIDS file structure from a vector of MRS data paths or list of mrs_data objects.

Usage

```
mrs_data2bids(  
  mrs_data,  
  output_dir,  
  suffix = NULL,  
  sub = NULL,  
  ses = NULL,  
  task = NULL,  
  acq = NULL,  
  nuc = NULL,  
  voi = NULL,  
  rec = NULL,  
  run = NULL,  
  echo = NULL,
```



```

    inv = NULL,
    skip_existing = TRUE
)

```

Arguments

mrs_data	vector of MRS data paths or list of mrs_data objects.
output_dir	the base directory to create the BIDS structure.
suffix	optional vector of file suffixes. Default behaviour is to automatically determine these from the input data, however it is recommended that they are specified to allow more efficient skipping of existing data.
sub	optional vector of subject labels. If not specified, these will be automatically generated as a series of increasing zero-padded integer values corresponding to the mrs_data input indices.
ses	optional vector of session labels.
task	optional vector of task labels.
acq	optional vector of acquisition labels.
nuc	optional vector of nucleus labels.
voi	optional vector of volume of interest labels.
rec	optional vector of reconstruction labels.
run	optional vector of run indices.
echo	optional vector of echo time indices.
inv	optional vector of inversion indices.
skip_existing	skip any data files that have already been converted. Defaults to TRUE, set to FALSE to force an overwrite of any existing data files.

mrs_data2mat	<i>Convert mrs_data object to a matrix, with spectral points in the column dimension and dynamics in the row dimension.</i>
--------------	---

Description

Convert mrs_data object to a matrix, with spectral points in the column dimension and dynamics in the row dimension.

Usage

```
mrs_data2mat(mrs_data, collapse = TRUE)
```

Arguments

mrs_data	MRS data object or list of MRS data objects.
collapse	collapse all other dimensions along the dynamic dimension, eg a 16x16 MRSI grid would be first collapsed across 256 dynamic scans.

Value

MRS data matrix.

mrs_data2spec_mat	<i>Convert mrs_data object to a matrix, with spectral points in the column dimension and dynamics in the row dimension.</i>
-------------------	---

Description

Convert mrs_data object to a matrix, with spectral points in the column dimension and dynamics in the row dimension.

Usage

```
mrs_data2spec_mat(mrs_data, collapse = TRUE)
```

Arguments

mrs_data	MRS data object or list of MRS data objects.
collapse	collapse all other dimensions along the dynamic dimension, eg a 16x16 MRSI grid would be first collapsed across 256 dynamic scans.

Value

MRS data matrix.

mrs_data2vec	<i>Convert mrs_data object to a vector.</i>
--------------	---

Description

Convert mrs_data object to a vector.

Usage

```
mrs_data2vec(mrs_data, dyn = 1, x_pos = 1, y_pos = 1, z_pos = 1, coil = 1)
```

Arguments

mrs_data	MRS data object.
dyn	dynamic index.
x_pos	x index.
y_pos	y index.
z_pos	z index.
coil	coil element index.

Value

MRS data vector.

mvfftshift	<i>Perform a fftshift on a matrix, with each column replaced by its shifted result.</i>
------------	---

Description

Perform a fftshift on a matrix, with each column replaced by its shifted result.

Usage

mvfftshift(x)

Arguments

x matrix input.

Value

output matrix.

mvifftshift	<i>Perform an ifftshift on a matrix, with each column replaced by its shifted result.</i>
-------------	---

Description

Perform an ifftshift on a matrix, with each column replaced by its shifted result.

Usage

mvifftshift(x)

Arguments

x matrix input.

Value

output matrix.

n2coord	<i>Print fit coordinates from a single index.</i>
---------	---

Description

Print fit coordinates from a single index.

Usage

```
n2coord(n, fit_res)
```

Arguments

n	fit index.
fit_res	fit_result object.

Ncoils	<i>Return the total number of coil elements in an MRS dataset.</i>
--------	--

Description

Return the total number of coil elements in an MRS dataset.

Usage

```
Ncoils(mrs_data)
```

Arguments

mrs_data	MRS data.
----------	-----------

Ndyns	<i>Return the total number of dynamic scans in an MRS dataset.</i>
-------	--

Description

Return the total number of dynamic scans in an MRS dataset.

Usage

```
Ndyns(mrs_data)
```

Arguments

mrs_data	MRS data.
----------	-----------

nifti_flip_lr	<i>Flip the x data dimension order of a nifti image. This corresponds to flipping MRI data in the left-right direction, assuming the data is saved in neurological format (can check with fsorient program).</i>
---------------	--

Description

Flip the x data dimension order of a nifti image. This corresponds to flipping MRI data in the left-right direction, assuming the data is saved in neurological format (can check with fsorient program).

Usage

```
nifti_flip_lr(x)
```

Arguments

x nifti object to be processed.

Value

nifti object with reversed x data direction.

Npts	<i>Return the number of data points in an MRS dataset.</i>
------	--

Description

Return the number of data points in an MRS dataset.

Usage

```
Npts(mrs_data)
```

Arguments

mrs_data MRS data.

Value

number of data points.

Nspec	<i>Return the total number of spectra in an MRS dataset.</i>
-------	--

Description

Return the total number of spectra in an MRS dataset.

Usage

Nspec(mrs_data)

Arguments

mrs_data MRS data.

Ntrans	<i>Return the total number of acquired transients for an MRS dataset.</i>
--------	---

Description

Return the total number of acquired transients for an MRS dataset.

Usage

Ntrans(mrs_data)

Arguments

mrs_data MRS data.

Nx	<i>Return the total number of x locations in an MRS dataset.</i>
----	--

Description

Return the total number of x locations in an MRS dataset.

Usage

Nx(mrs_data)

Arguments

mrs_data MRS data.

Ny *Return the total number of y locations in an MRS dataset.*

Description

Return the total number of y locations in an MRS dataset.

Usage

Ny(mrs_data)

Arguments

mrs_data MRS data.

Nz *Return the total number of z locations in an MRS dataset.*

Description

Return the total number of z locations in an MRS dataset.

Usage

Nz(mrs_data)

Arguments

mrs_data MRS data.

one_page_pdf *Export a one-page pdf of a single fit result*

Description

Export a one-page pdf of a single fit result

Usage

one_page_pdf(fit_res, pdf_out_path, title = NULL)

Arguments

fit_res fit_result object.
pdf_out_path path to the exported pdf file.
title output title.

`ortho3`*Display an orthographic projection plot of a nifti object.*

Description

Display an orthographic projection plot of a nifti object.

Usage

```
ortho3(  
  underlay,  
  overlay = NULL,  
  xyz = NULL,  
  zlim = NULL,  
  zlim_ol = NULL,  
  alpha = 0.7,  
  col_ol = viridisLite::viridis(64),  
  orient_lab = TRUE,  
  rescale = 1,  
  crosshairs = TRUE,  
  ch_lwd = 1,  
  colourbar = TRUE,  
  bg = "black",  
  mar = c(0, 0, 0, 0),  
  smallplot = c(0.63, 0.65, 0.07, 0.42),  
  legend_axis_cex = 0.75  
)
```

Arguments

<code>underlay</code>	underlay image to be shown in grayscale.
<code>overlay</code>	optional overlay image.
<code>xyz</code>	x, y, z slice coordinates to display.
<code>zlim</code>	underlay intensity limits.
<code>zlim_ol</code>	overlay intensity limits.
<code>alpha</code>	transparency of overlay.
<code>col_ol</code>	colour palette of overlay.
<code>orient_lab</code>	display orientation labels (default TRUE).
<code>rescale</code>	rescale factor for the underlay and overlay images.
<code>crosshairs</code>	display the crosshairs (default TRUE).
<code>ch_lwd</code>	crosshair linewidth.
<code>colourbar</code>	display a colourbar for the overlay (default TRUE).
<code>bg</code>	plot background colour.

mar	plot margins.
smallplot	smallplot option for positioning the colourbar.
legend_axis_cex	font expansion factor for the legend axis text.

ortho3_inter	<i>Display an interactive orthographic projection plot of a nifti object.</i>
--------------	---

Description

Display an interactive orthographic projection plot of a nifti object.

Usage

```
ortho3_inter(
  underlay,
  overlay = NULL,
  xyz = NULL,
  zlim = NULL,
  zlim_ol = NULL,
  alpha = 0.7,
  ...
)
```

Arguments

underlay	underlay image to be shown in grayscale.
overlay	optional overlay image.
xyz	x, y, z slice coordinates to display.
zlim	underlay intensity limits.
zlim_ol	overlay intensity limits.
alpha	transparency of overlay.
...	other options to be passed to the ortho3 function.

peak_info	<i>Search for the highest peak in a spectral region and return the frequency, height and FWHM.</i>
-----------	--

Description

Search for the highest peak in a spectral region and return the frequency, height and FWHM.

Usage

```
peak_info(
  mrs_data,
  xlim = c(4, 0.5),
  interp_f = 4,
  scale = "ppm",
  mode = "real"
)
```

Arguments

mrs_data	an object of class mrs_data.
xlim	frequency range (default units of PPM) to search for the highest peak.
interp_f	interpolation factor, defaults to 4x.
scale	the units to use for the frequency scale, can be one of: "ppm", "hz" or "points".
mode	spectral mode, can be : "real", "imag" or "mod".

Value

list of arrays containing the highest peak frequency, height and FWHM in units of PPM and Hz.

pg_extrap_xy	<i>Papoulis-Gerchberg (PG) algorithm method for k-space extrapolation.</i>
--------------	--

Description

PG method as described in: Haupt CI, Schuff N, Weiner MW, Maudsley AA. Removal of lipid artifacts in 1H spectroscopic imaging by data extrapolation. Magn Reson Med. 1996 May;35(5):678-87. Extrapolation is performed to expand k-space coverage by a factor of 2, with the aim to reduce Gibbs ringing.

Usage

```
pg_extrap_xy(
  mrs_data,
  img_mask = NULL,
  kspace_mask = NULL,
  intensity_thresh = 0.15,
  iters = 50
)
```

Arguments

<code>mrs_data</code>	MRS data object.
<code>img_mask</code>	a boolean matrix of voxels with strong signals to be extrapolated. Must be twice the dimensions of the input data.
<code>kspace_mask</code>	a boolean matrix of kspace points that have been sampled. Typically a circle for MRSI, but defaults to the full rectangular area of k-space covered by the input data. Must match the x-y dimensions of the input data.
<code>intensity_thresh</code>	used to define <code>img_mask</code> based on the strength of the signal in each voxel. Defaults to intensities greater than 15% of the maximum. Ignored if <code>img_mask</code> is specified as argument.
<code>iters</code>	number of iterations to perform.

Value

extrapolated `mrs_data` object.

<code>phase</code>	<i>Apply phasing parameters to MRS data.</i>
--------------------	--

Description

Apply phasing parameters to MRS data.

Usage

```
phase(mrs_data, zero_order, first_order = 0)
```

Arguments

<code>mrs_data</code>	MRS data.
<code>zero_order</code>	zero'th order phase term in degrees.
<code>first_order</code>	first order (frequency dependent) phase term in ms.

Value

MRS data with applied phase parameters.

phase_ref_1h_brain	<i>Corrected zero order phase and chemical shift offset in 1H MRS data from the brain.</i>
--------------------	--

Description

Corrected zero order phase and chemical shift offset in 1H MRS data from the brain.

Usage

```
phase_ref_1h_brain(mrs_data, mean_ref = FALSE, ret_corr_only = TRUE)
```

Arguments

mrs_data	MRS data to be corrected.
mean_ref	apply the phase and offset of the mean spectrum to all others. Default is FALSE.
ret_corr_only	return the corrected data only.

Value

corrected MRS data.

plot.fit_result	<i>Plot the fitting results of an object of class fit_result.</i>
-----------------	---

Description

Plot the fitting results of an object of class fit_result.

Usage

```
## S3 method for class 'fit_result'  
plot(  
  x,  
  dyn = 1,  
  x_pos = 1,  
  y_pos = 1,  
  z_pos = 1,  
  coil = 1,  
  xlim = NULL,  
  data_only = FALSE,  
  label = NULL,  
  plot_sigs = NULL,  
  n = NULL,  
  sub_b1 = FALSE,
```

```

    mar = NULL,
    restore_def_par = TRUE,
    ylim = NULL,
    y_scale = FALSE,
    show_grid = TRUE,
    grid_nx = NULL,
    grid_ny = NA,
    invert_fit = FALSE,
    ...
)

```

Arguments

x	fit_result object.
dyn	the dynamic index to plot.
x_pos	the x index to plot.
y_pos	the y index to plot.
z_pos	the z index to plot.
coil	the coil element number to plot.
xlim	the range of values to display on the x-axis, eg xlim = c(4,1).
data_only	display only the processed data (logical).
label	character string to add to the top left of the plot window.
plot_sigs	a character vector of signal names to add to the plot.
n	single index element to plot (overrides other indices when given).
sub_bl	subtract the baseline from the data and fit (logical).
mar	option to adjust the plot margins. See ?par.
restore_def_par	restore default plotting par values after the plot has been made.
ylim	range of values to display on the y-axis, eg ylim = c(0,10).
y_scale	option to display the y-axis values (logical).
show_grid	plot gridlines behind the data (logical). Defaults to TRUE.
grid_nx	number of cells of the grid in x and y direction. When NULL the grid aligns with the tick marks on the corresponding default axis (i.e., tickmarks as computed by axTicks). When NA, no grid lines are drawn in the corresponding direction.
grid_ny	as above.
invert_fit	show the fit result "upside-down"/
...	further arguments to plot method.

`plot.mrs_data`*Plotting method for objects of class mrs_data.*

Description

Plotting method for objects of class `mrs_data`.

Usage

```
## S3 method for class 'mrs_data'
plot(
  x,
  dyn = 1,
  x_pos = 1,
  y_pos = 1,
  z_pos = 1,
  coil = 1,
  fd = TRUE,
  x_units = NULL,
  xlim = NULL,
  y_scale = FALSE,
  x_ax = TRUE,
  mode = "re",
  lwd = NULL,
  bty = NULL,
  label = "",
  restore_def_par = TRUE,
  mar = NULL,
  xaxis_lab = NULL,
  yaxis_lab = NULL,
  xat = NULL,
  xlabs = TRUE,
  yat = NULL,
  ylabs = TRUE,
  show_grid = TRUE,
  grid_nx = NULL,
  grid_ny = NA,
  col = NULL,
  alpha = NULL,
  bl_lty = NULL,
  hline = NULL,
  hline_lty = 2,
  hline_col = "red",
  vline = NULL,
  vline_lty = 2,
  vline_col = "red",
  ...
)
```

)

Arguments

x	object of class mrs_data.
dyn	the dynamic index to plot.
x_pos	the x index to plot.
y_pos	the y index to plot.
z_pos	the z index to plot.
coil	the coil element number to plot.
fd	display data in the frequency-domain (default), or time-domain (logical).
x_units	the units to use for the x-axis, can be one of: "ppm", "hz", "points" or "seconds".
xlim	the range of values to display on the x-axis, eg xlim = c(4,1).
y_scale	option to display the y-axis values (logical).
x_ax	option to display the x-axis values (logical).
mode	representation of the complex numbers to be plotted, can be one of: "re", "im", "mod" or "arg".
lwd	plot linewidth.
bty	option to draw a box around the plot. See ?par.
label	character string to add to the top left of the plot window.
restore_def_par	restore default plotting par values after the plot has been made.
mar	option to adjust the plot margins. See ?par.
xaxis_lab	x-axis label.
yaxis_lab	y-axis label.
xat	x-axis tick label values.
xlabs	x-axis tick labels.
yat	y-axis tick label values.
ylabs	y-axis tick labels.
show_grid	plot gridlines behind the data (logical). Defaults to TRUE.
grid_nx	number of cells of the grid in x and y direction. When NULL the grid aligns with the tick marks on the corresponding default axis (i.e., tickmarks as computed by axTicks). When NA, no grid lines are drawn in the corresponding direction.
grid_ny	as above.
col	set the line colour, eg col = rgb(0.5, 0.5, 0.5).
alpha	set the line transparency, eg alpha = 0.5 is 50% transparency. Overrides any transparency levels set by col.
bl_lty	linetype for the y = 0 baseline trace. A default value NULL results in no baseline being plotted.
hline	add a horizontal line at the specified value.

hline_lty	linetype for the horizontal line.
hline_col	colour for the horizontal line.
vline	add a vertical line at the specified value.
vline_lty	linetype for the vertical line.
vline_col	colour for the vertical line.
...	other arguments to pass to the plot method.

plot_bc	<i>Convenience function to plot a baseline estimate with the original data.</i>
---------	---

Description

Convenience function to plot a baseline estimate with the original data.

Usage

```
plot_bc(orig_data, bc_data, ...)
```

Arguments

orig_data	the original data.
bc_data	the baseline corrected data.
...	other arguments to pass to the stackplot function.

plot_reg	<i>Plot regressors as an image.</i>
----------	-------------------------------------

Description

Plot regressors as an image.

Usage

```
plot_reg(regressor_df)
```

Arguments

regressor_df	input regressor data frame.
--------------	-----------------------------

plot_slice_fit *Plot a 2D slice from an MRSI fit result object.*

Description

Plot a 2D slice from an MRSI fit result object.

Usage

```
plot_slice_fit(  
    fit_res,  
    map,  
    map_denom = NULL,  
    slice = 1,  
    zlim = NULL,  
    interp = 1  
)
```

Arguments

fit_res	fit_result object.
map	fit result values to display as a colour map. Can be specified as a character string or array of numeric values. Defaults to "tNAA".
map_denom	fit result values to divide the map argument by. Can be specified as a character string (eg "tCr") or array of numeric values.
slice	slice to plot in the z direction.
zlim	range of values to plot.
interp	interpolation factor.

plot_slice_fit_inter *Plot a 2D slice from an MRSI fit result object.*

Description

Plot a 2D slice from an MRSI fit result object.

Usage

```
plot_slice_fit_inter(  
    fit_res,  
    map = NULL,  
    map_denom = NULL,  
    slice = 1,  
    zlim = NULL,  
    interp = 1,  
    xlim = NULL  
)
```

Arguments

fit_res	fit_result object.
map	fit result values to display as a colour map. Can be specified as a character string or array of numeric values. Defaults to "tNAA".
map_denom	fit result values to divide the map argument by. Can be specified as a character string (eg "tCr") or array of numeric values.
slice	slice to plot in the z direction.
zlim	range of values to plot.
interp	interpolation factor.
xlim	spectral plot limits for the x axis.

plot_slice_map	<i>Plot a slice from a 7 dimensional array.</i>
----------------	---

Description

Plot a slice from a 7 dimensional array.

Usage

```
plot_slice_map(
  data,
  zlim = NULL,
  mask_map = NULL,
  mask_cutoff = 20,
  interp = 1,
  slice = 1,
  dyn = 1,
  coil = 1,
  ref = 1,
  denom = NULL,
  horizontal = FALSE
)
```

Arguments

data	7d array of values to be plotted.
zlim	smallest and largest values to be plotted.
mask_map	matching map with logical values to indicate if the corresponding values should be plotted.
mask_cutoff	minimum values to plot (as a percentage of the maximum).
interp	map interpolation factor.
slice	the slice index to plot.

dyn	the dynamic index to plot.
coil	the coil element number to plot.
ref	reference index to plot.
denom	map to use as a denominator.
horizontal	display the colourbar horizontally (logical).

plot_slice_map_inter *Plot an interactive slice map from a data array where voxels can be selected to display a corresponding spectrum.*

Description

Plot an interactive slice map from a data array where voxels can be selected to display a corresponding spectrum.

Usage

```
plot_slice_map_inter(
  mrs_data,
  map = NULL,
  xlim = NULL,
  slice = 1,
  zlim = NULL,
  mask_map = NULL,
  denom = NULL,
  mask_cutoff = 20,
  interp = 1,
  mode = "re",
  y_scale = FALSE,
  ylim = NULL,
  coil = 1,
  fd = TRUE
)
```

Arguments

mrs_data	spectral data.
map	array of values to be plotted, defaults to the integration of the modulus of the full spectral width.
xlim	spectral region to plot.
slice	the slice index to plot.
zlim	smallest and largest values to be plotted.
mask_map	matching map with logical values to indicate if the corresponding values should be plotted.

denom	map to use as a denominator.
mask_cutoff	minimum values to plot (as a percentage of the maximum).
interp	map interpolation factor.
mode	representation of the complex spectrum to be plotted, can be one of: "re", "im", "mod" or "arg".
y_scale	option to display the y-axis values (logical).
ylim	intensity range to plot.
coil	coil element to plot.
fd	display data in the frequency-domain (default), or time-domain (logical).

plot_spec_sd *Plot the spectral standard deviation.*

Description

Plot the spectral standard deviation.

Usage

```
plot_spec_sd(mrs_data, xlim = NULL, scale_sd = 1.96, ...)
```

Arguments

mrs_data	MRS data to be plotted.
xlim	plotting limits in ppm.
scale_sd	scaling factor for the standard deviation trace.
...	other arguments passed to the stackplot function.

plot_voi_overlay *Plot a volume as an image overlay.*

Description

Plot a volume as an image overlay.

Usage

```
plot_voi_overlay(mri, voi, export_path = NULL, zlim = NULL, ...)
```

Arguments

mri	image data as a nifti object or path to data file.
voi	volume data as a nifti object or path to data file.
export_path	optional path to save the image in png format.
zlim	underlay intensity limits.
...	additional arguments to the ortho3 function.

plot_voi_overlay_seg *Plot a volume as an overlay on a segmented brain volume.*

Description

Plot a volume as an overlay on a segmented brain volume.

Usage

```
plot_voi_overlay_seg(mri_seg, voi, export_path = NULL, ...)
```

Arguments

mri_seg	segmented brain volume as a nifti object.
voi	volume data as a nifti object.
export_path	optional path to save the image in png format.
...	additional arguments to the ortho3 function.

ppm *Return the ppm scale of an MRS dataset or fit result.*

Description

Return the ppm scale of an MRS dataset or fit result.

Usage

```
ppm(x, ft = NULL, ref = NULL, fs = NULL, N = NULL)
```

```
## S3 method for class 'mrs_data'
ppm(x, ft = NULL, ref = NULL, fs = NULL, N = NULL)
```

```
## S3 method for class 'fit_result'
ppm(x, ft = NULL, ref = NULL, fs = NULL, N = NULL)
```

Arguments

x	MRS dataset or fit result.
ft	transmitter frequency in Hz, does not apply when the object is a fit result.
ref	reference value for ppm scale, does not apply when the object is a fit result.
fs	sampling frequency in Hz, does not apply when the object is a fit result.
N	number of data points in the spectral dimension, does not apply when the object is a fit result.

Value

ppm scale.

precomp	<i>Save function results to file and load on subsequent calls to avoid repeat computation.</i>
---------	--

Description

Save function results to file and load on subsequent calls to avoid repeat computation.

Usage

```
precomp(file, fun, ...)
```

Arguments

file	file name to write the results.
fun	function to run.
...	arguments to be passed to fun.

preproc_svs	<i>Preprocess and perform quality assessment of a single SVS data set.</i>
-------------	--

Description

Preprocess and perform quality assessment of a single SVS data set.

Usage

```
preproc_svs(path, label = NULL, output_dir = NULL, ref_inds = NULL)
```

Arguments

path	path to the fMRS data file or IMA directory.
label	a label to describe the data set.
output_dir	output directory.
ref_inds	a vector of 1-based indices for any water reference dynamic scans.

preproc_svs_dataset	<i>Preprocess and perform quality assessment of one or more SVS data sets.</i>
---------------------	--

Description

Preprocess and perform quality assessment of one or more SVS data sets.

Usage

```
preproc_svs_dataset(
  paths,
  labels = NULL,
  output_dir = "spant_analysis",
  exclude_labels = NULL,
  overwrite = FALSE,
  ref_inds = NULL,
  return_results = FALSE
)
```

Arguments

paths	paths to the fMRS data file or IMA directory.
labels	labels to describe each data set.
output_dir	output directory.
exclude_labels	vector of labels of scans to exclude, eg poor quality data.
overwrite	overwrite saved results, defaults to FALSE.
ref_inds	a vector of 1-based indices for any water reference dynamic scans.
return_results	function will return key outputs, defaults to FALSE.

print.fit_result	<i>Print a summary of an object of class fit_result.</i>
------------------	--

Description

Print a summary of an object of class fit_result.

Usage

```
## S3 method for class 'fit_result'
print(x, ...)
```

Arguments

x	fit_result object.
...	further arguments.

`print.mrs_data` *Print a summary of mrs_data parameters.*

Description

Print a summary of mrs_data parameters.

Usage

```
## S3 method for class 'mrs_data'  
print(x, full = FALSE, ...)
```

Arguments

<code>x</code>	mrs_data object.
<code>full</code>	print all parameters (default FALSE).
<code>...</code>	further arguments.

`qn_states` *Get the quantum coherence matrix for a spin system.*

Description

Get the quantum coherence matrix for a spin system.

Usage

```
qn_states(sys)
```

Arguments

<code>sys</code>	spin system object.
------------------	---------------------

Value

quantum coherence number matrix.

basis_type may be one of "poly" or "spline".
rescale_output rescale the bl_matched_spec and bl output to improve consistency between dynamic scans.
phase_corr apply phase correction (in addition to frequency). TRUE by default.
ret_corr_only return the corrected mrs_data object only.
zero_freq_shift_t0
 perform a linear fit to the frequency shifts and set the (linearly modeled) shift to be 0 Hz for the first dynamic scan.
remove_freq_outliers
 remove dynamics based on their frequency shift.
freq_outlier_thresh
 threshold to remove frequency outliers.
remove_phase_outliers
 remove dynamics based on their phase shift.
phase_outlier_thresh
 threshold to remove phase outliers.
remove_amp_outliers
 remove dynamics based on their amplitude change.
amp_outlier_thresh
 threshold to remove amplitude outliers.

Value

a list containing the corrected data; phase and shift values in units of degrees and Hz respectively.

Re.mrs_data

Apply Re operator to an MRS dataset.

Description

Apply Re operator to an MRS dataset.

Usage

```
## S3 method for class 'mrs_data'
Re(z)
```

Arguments

z MRS data.

Value

MRS data following Re operator.

read_basis	<i>Read a basis file in LCModel .basis format.</i>
------------	--

Description

Read a basis file in LCModel .basis format.

Usage

```
read_basis(basis_file, ref = def_ref(), sort_basis = TRUE)
```

Arguments

basis_file	path to basis file.
ref	assumed ppm reference value.
sort_basis	sort the basis set based on signal names.

Value

basis object.

read_ima_coil_dir	<i>Read a directory containing Siemens MRS IMA files and combine along the coil dimension. Note that the coil ID is inferred from the sorted file name and should be checked when consistency is required between two directories.</i>
-------------------	--

Description

Read a directory containing Siemens MRS IMA files and combine along the coil dimension. Note that the coil ID is inferred from the sorted file name and should be checked when consistency is required between two directories.

Usage

```
read_ima_coil_dir(dir, extra = NULL, verbose = FALSE)
```

Arguments

dir	data directory path.
extra	an optional data frame to provide additional variables for use in subsequent analysis steps, eg id or grouping variables.
verbose	output extra information to the console.

Value

mrs_data object.

read_ima_dyn_dir	<i>Read a directory containing Siemens MRS IMA files and combine along the dynamic dimension. Note that the coil ID is inferred from the sorted file name and should be checked when consistency is required.</i>
------------------	---

Description

Read a directory containing Siemens MRS IMA files and combine along the dynamic dimension. Note that the coil ID is inferred from the sorted file name and should be checked when consistency is required.

Usage

```
read_ima_dyn_dir(dir, extra = NULL, verbose = FALSE)
```

Arguments

dir	data directory path.
extra	an optional data frame to provide additional variables for use in subsequent analysis steps, eg id or grouping variables.
verbose	output extra information to the console.

Value

mrs_data object.

read_lcm_coord	<i>Read an LCModel formatted coord file containing fit information.</i>
----------------	---

Description

Read an LCModel formatted coord file containing fit information.

Usage

```
read_lcm_coord(coord_f)
```

Arguments

coord_f	path to the coord file.
---------	-------------------------

Value

list containing a table of fit point and results structure containing signal amplitudes, errors and fitting diagnostics.

read_mrs	<i>Read MRS data from the filesystem.</i>
----------	---

Description

Read MRS data from the filesystem.

Usage

```
read_mrs(
  path,
  format = NULL,
  ft = NULL,
  fs = NULL,
  ref = NULL,
  n_ref_scans = NULL,
  full_fid = FALSE,
  omit_svs_ref_scans = TRUE,
  verbose = FALSE,
  extra = NULL,
  fid_filt_dist = NULL
)
```

Arguments

path	file name or directory containing the MRS data.
format	string describing the data format. Must be one of the following : "spar_sdat", "rda", "dicom", "twix", "pfile", "list_data", "paravis", "dpt", "lcm_raw", "rds", "nifti", "varian", "jmru_i_txt". If not specified, the format will be guessed from the filename extension, or will be assumed to be a Siemens ima dynamic data if the path is a directory.
ft	transmitter frequency in Hz (required for list_data format).
fs	sampling frequency in Hz (required for list_data format).
ref	reference value for ppm scale (required for list_data format).
n_ref_scans	override the number of water reference scans detected in the file header (GE p-file only).
full_fid	export all data points, including those before the start of the FID (default = FALSE), TWIX format only.
omit_svs_ref_scans	remove any reference scans sometimes saved in SVS twix data (default = TRUE).
verbose	print data file information (default = FALSE).
extra	an optional data frame to provide additional variables for use in subsequent analysis steps, eg id or grouping variables.
fid_filt_dist	indicate if the data has a distorted FID due to a brick-wall filter being used to downsample the data. Default is to auto detect this from the data, but TRUE or FALSE options can be given to override detection.

Value

MRS data object.

Examples

```
fname <- system.file("extdata", "philips_spar_sdat_WS.SDAT", package = "spant")
mrs_data <- read_mrs(fname)
print(mrs_data)
```

read_mrs_tqn	<i>Read MRS data using the TARQUIN software package.</i>
--------------	--

Description

Read MRS data using the TARQUIN software package.

Usage

```
read_mrs_tqn(fname, fname_ref = NA, format, id = NA, group = NA)
```

Arguments

fname	the filename containing the MRS data.
fname_ref	a second filename containing reference MRS data.
format	format of the MRS data. Can be one of the following: siemens, philips, ge, dcm, dpt, rda, lcm, varian, bruker, jmrui_txt.
id	optional ID string.
group	optional group string.

Value

MRS data object.

Examples

```
fname <- system.file("extdata", "philips_spar_sdat_WS.SDAT", package="spant")
## Not run:
mrs_data <- read_mrs_tqn(fname, format="philips")

## End(Not run)
```

read_pulse_ascii *Read an ASCII formatted pulse file.*

Description

Read an ASCII formatted pulse file.

Usage

```
read_pulse_ascii(fname, deg2rad = TRUE)
```

Arguments

fname ASCII formatted pulse file path.
deg2rad convert phase values stored in degrees to radians.

Value

pulse waveform and header.

read_pulse Bruker *Read a Bruker formatted pulse file*

Description

Read a Bruker formatted pulse file

Usage

```
read_pulse Bruker(fname)
```

Arguments

fname Bruker formatted pulse file path.

Value

pulse waveform and header.

read_pulse_pta	<i>Read a .pta formatted pulse file compatible with Siemens PulseTool.</i>
----------------	--

Description

Read a .pta formatted pulse file compatible with Siemens PulseTool.

Usage

```
read_pulse_pta(fname)
```

Arguments

fname	pta formatted pulse file path.
-------	--------------------------------

Value

pulse waveform and header.

read_siemens_txt_hdr	<i>Read the text format header found in Siemens IMA and TWIX data files.</i>
----------------------	--

Description

Read the text format header found in Siemens IMA and TWIX data files.

Usage

```
read_siemens_txt_hdr(input, version = "vd", verbose = FALSE, offset = 0)
```

Arguments

input	file name to read or raw data.
version	software version, can be "vb" or "vd".
verbose	print information to the console.
offset	offset to begin searching for the text header.

Value

a list of parameter values

read_tqn_fit	<i>Reader for csv fit results generated by TARQUIN.</i>
--------------	---

Description

Reader for csv fit results generated by TARQUIN.

Usage

```
read_tqn_fit(fit_f)
```

Arguments

fit_f TARQUIN fit file.

Value

A data frame of the fit data points.

Examples

```
## Not run:  
fit <- read_tqn_fit(system.file("extdata", "fit.csv", package="spant"))  
  
## End(Not run)
```

read_tqn_result	<i>Reader for csv results generated by TARQUIN.</i>
-----------------	---

Description

Reader for csv results generated by TARQUIN.

Usage

```
read_tqn_result(result_f, remove_rcs = TRUE)
```

Arguments

result_f TARQUIN result file.
remove_rcs omit row, column and slice ids from output.

Value

list of amplitudes, crlbs and diagnostics.

Examples

```
## Not run:  
result <- read_tqn_result(system.file("extdata", "result.csv", package="spant"))  
  
## End(Not run)
```

recon_imag	<i>Reconstruct complex time-domain data from the real part of frequency-domain data.</i>
------------	--

Description

Reconstruct complex time-domain data from the real part of frequency-domain data.

Usage

```
recon_imag(mrs_data)
```

Arguments

mrs_data MRS data.

Value

reconstructed MRS data.

recon_imag_vec	<i>Reconstruct complex time-domain data from the real part of frequency-domain data.</i>
----------------	--

Description

Reconstruct complex time-domain data from the real part of frequency-domain data.

Usage

```
recon_imag_vec(data)
```

Arguments

data data points in the frequency domain.

Value

reconstructed signal.

recon_twix_2d_mrsi *Reconstruct 2D MRSI data from a twix file loaded with read_mrs.*

Description

Reconstruct 2D MRSI data from a twix file loaded with read_mrs.

Usage

```
recon_twix_2d_mrsi(twix_mrs)
```

Arguments

twix_mrs raw dynamic data.

Value

reconstructed data.

rectangular_mask *Create a rectangular mask stored as a matrix of logical values.*

Description

Create a rectangular mask stored as a matrix of logical values.

Usage

```
rectangular_mask(xN, yN, x0, y0, xw, yw, angle)
```

Arguments

xN	number of pixels in the x dimension.
yN	number of pixels in the y dimension.
x0	centre of rectangle in the x direction in units of pixels.
y0	centre of rectangle in the y direction in units of pixels.
xw	width in the x direction in units of pixels.
yw	width in the y direction in units of pixels.
angle	angle of rotation in degrees.

Value

logical mask matrix with dimensions fov_yN x fov_xN.

rep_array_dim	<i>Repeat an array over a given dimension.</i>
---------------	--

Description

Repeat an array over a given dimension.

Usage

```
rep_array_dim(x, rep_dim, n)
```

Arguments

x	array.
rep_dim	dimension to extend.
n	number of times to repeat.

Value

extended array.

rep_dyn	<i>Replicate a scan in the dynamic dimension.</i>
---------	---

Description

Replicate a scan in the dynamic dimension.

Usage

```
rep_dyn(mrs_data, times)
```

Arguments

mrs_data	MRS data to be replicated.
times	number of times to replicate.

Value

replicated data object.

rep_mrs	<i>Replicate a scan over a given dimension.</i>
---------	---

Description

Replicate a scan over a given dimension.

Usage

```
rep_mrs(  
  mrs_data,  
  x_rep = 1,  
  y_rep = 1,  
  z_rep = 1,  
  dyn_rep = 1,  
  coil_rep = 1,  
  warn = TRUE  
)
```

Arguments

mrs_data	MRS data to be replicated.
x_rep	number of x replications.
y_rep	number of y replications.
z_rep	number of z replications.
dyn_rep	number of dynamic replications.
coil_rep	number of coil replications.
warn	print a warning when the data dimensions do not change.

Value

replicated data object.

resample_basis	<i>Resample a basis-set to match a mrs_data acquisition.</i>
----------------	--

Description

Resample a basis-set to match a mrs_data acquisition.

Usage

```
resample_basis(basis, mrs_data, ref_freq_match = TRUE)
```

Arguments

basis	the basis to be resampled.
mrs_data	the mrs_data to match the number of data points and sampling frequency.
ref_freq_match	apply a frequency shift to the basis to match the reference frequency (usually 4.65 or 4.68) of the mrs_data.

Value

resampled basis set object.

resample_img	<i>Resample an image to match a target image space.</i>
--------------	---

Description

Resample an image to match a target image space.

Usage

```
resample_img(source, target, interp = 3L)
```

Arguments

source	image data as a nifti object.
target	image data as a nifti object.
interp	interpolation parameter, see niftyreg.linear definition.

Value

resampled image data as a nifti object.

resample_voi	<i>Resample a VOI to match a target image space using nearest-neighbour interpolation.</i>
--------------	--

Description

Resample a VOI to match a target image space using nearest-neighbour interpolation.

Usage

```
resample_voi(voi, mri)
```

Arguments

`voi` volume data as a nifti object.
`mri` image data as a nifti object.

Value

volume data as a nifti object.

`reslice_to_mrs` *Reslice a nifti object to match the orientation of mrs data.*

Description

Reslice a nifti object to match the orientation of mrs data.

Usage

```
reslice_to_mrs(mri, mrs, interp = 3L)
```

Arguments

`mri` nifti object to be resliced.
`mrs` `mrs_data` object for the target orientation.
`interp` interpolation parameter, see `niftyreg.linear` definition.

Value

resliced imaging data.

`reson_table2mrs_data` *Generate mrs_data from a table of single Lorentzian resonances.*

Description

Generate `mrs_data` from a table of single Lorentzian resonances.

Usage

```
reson_table2mrs_data(  
  reson_table,  
  acq_params = def_acq_params(),  
  back_extrap_pts = 0  
)
```

Arguments

reson_table as produced by the hsvd function.
 acq_paras list of acquisition parameters. See
 back_extrap_pts number of data points to back extrapolate [def_acq_paras](#)

Value

mrs_data object.

re_weighting	<i>Apply a weighting to the FID to enhance spectral resolution.</i>
--------------	---

Description

Apply a weighting to the FID to enhance spectral resolution.

Usage

```
re_weighting(mrs_data, re, alpha)
```

Arguments

mrs_data data to be enhanced.
 re resolution enhancement factor (rising exponential factor).
 alpha alpha factor (Gaussian decay)

Value

resolution enhanced mrs_data.

rm_dyns	<i>Remove a subset of dynamic scans.</i>
---------	--

Description

Remove a subset of dynamic scans.

Usage

```
rm_dyns(mrs_data, subset)
```


Arguments

mrs_data	dynamic MRS data.
subset	vector containing indices to the dynamic scans to be removed.

Value

MRS data without the specified dynamic scans.

scale_amp_legacy	<i>Apply water reference scaling to a fitting results object to yield metabolite quantities in units of "mmol per Kg wet weight".</i>
------------------	---

Description

See the LCModel manual (section 10.2) on water-scaling for details on the assumptions and relevant references. Use this type of concentration scaling to compare fit results with LCModel and TARQUIN defaults. Otherwise scale_amp_molal_pvc is the preferred method. Note, the LCModel manual (section 1.3) states:

Usage

```
scale_amp_legacy(fit_result, ref_data, w_att = 0.7, w_conc = 35880, ...)
```

Arguments

fit_result	a result object generated from fitting.
ref_data	water reference MRS data object.
w_att	water attenuation factor (default = 0.7). Assumes water T2 of 80ms and a TE = 30 ms. $\exp(-30\text{ms} / 80\text{ms}) \sim 0.7$.
w_conc	assumed water concentration (default = 35880). Default value corresponds to typical white matter. Set to 43300 for gray matter, and 55556 for phantom measurements.
...	additional arguments to get_td_amp function.

Details

"Concentrations should be labelled 'mmol per Kg wet weight'. We use the shorter (incorrect) abbreviation mM. The actual mM is the mmol per Kg wet weight multiplied by the specific gravity of the tissue, typically 1.04 in brain."

Value

a fit_result object with a rescaled results table.

scale_amp_molal	<i>Apply water reference scaling to a fitting results object to yield metabolite quantities in millimolar (mM) units (mol / kg of tissue water).</i>
-----------------	--

Description

Note, this function assumes the volume contains a homogeneous voxel, eg pure WM, GM or CSF. Also note that in the case of a homogeneous voxel the relative densities of MR-visible water (eg GM=0.78, WM=0.65, and CSF=0.97) cancel out and don't need to be considered. Use `scale_amp_molal_pvc` for volumes containing multiple compartments. Details of this method can be found in "Use of tissue water as a concentration reference for proton spectroscopic imaging" by Gasparovic et al MRM 2006 55(6):1219-26.

Usage

```
scale_amp_molal(
  fit_result,
  ref_data,
  te,
  tr,
  water_t1,
  water_t2,
  metab_t1,
  metab_t2,
  ...
)
```

Arguments

<code>fit_result</code>	result object generated from fitting.
<code>ref_data</code>	water reference MRS data object.
<code>te</code>	the MRS TE in seconds.
<code>tr</code>	the MRS TR in seconds.
<code>water_t1</code>	assumed water T1 value.
<code>water_t2</code>	assumed water T2 value.
<code>metab_t1</code>	assumed metabolite T1 value.
<code>metab_t2</code>	assumed metabolite T2 value.
<code>...</code>	additional arguments to <code>get_td_amp</code> function.

Value

A `fit_result` object with a rescaled results table.

scale_amp_molal_pvc	<i>Apply water reference scaling to a fitting results object to yield metabolite quantities in millimolar (mM) units (mol / kg of tissue water).</i>
---------------------	--

Description

Details of this method can be found in "Use of tissue water as a concentration reference for proton spectroscopic imaging" by Gasparovic et al MRM 2006 55(6):1219-26. 1.5 Tesla relaxation assumptions are taken from this paper. For 3 Tesla data, relaxation assumptions are taken from "NMR relaxation times in the human brain at 3.0 Tesla" by Wansapura et al J Magn Reson Imaging 1999 9(4):531-8.

Usage

```
scale_amp_molal_pvc(fit_result, ref_data, p_vols, te, tr, ...)
```

Arguments

fit_result	result object generated from fitting.
ref_data	water reference MRS data object.
p_vols	a numeric vector of partial volumes expressed as percentages. For example, a voxel containing 100% white matter tissue would use : p_vols = c(WM = 100, GM = 0, CSF = 0).
te	the MRS TE in seconds.
tr	the MRS TR in seconds.
...	additional arguments to get_td_amp function.

Value

A fit_result object with a rescaled results table.

scale_amp_molar	<i>Apply water reference scaling to a fitting results object to yield metabolite quantities in millimolar (mM) units (mol / Litre of tissue). This function is deprecated, please use scale_amp_legacy instead.</i>
-----------------	---

Description

See the LCModel manual (section 10.2) on water-scaling for details on the assumptions and relevant references. Use this type of concentration scaling to compare fit results with LCModel and TARQUIN defaults. Otherwise scale_amp_molal_pvc is generally the preferred method.

Usage

```
scale_amp_molar(fit_result, ref_data, w_att = 0.7, w_conc = 35880, ...)
```

Arguments

fit_result	a result object generated from fitting.
ref_data	water reference MRS data object.
w_att	water attenuation factor (default = 0.7). Assumes water T2 of 80ms and a TE = 30 ms. $\exp(-30\text{ms} / 80\text{ms}) \sim 0.7$.
w_conc	assumed water concentration (default = 35880). Default value corresponds to typical white matter. Set to 43300 for gray matter, and 55556 for phantom measurements.
...	additional arguments to get_td_amp function.

Value

a fit_result object with a rescaled results table.

scale_amp_molar2molal_pvc

Convert default LCM/TARQUIN concentration scaling to molal units with partial volume correction.

Description

Convert default LCM/TARQUIN concentration scaling to molal units with partial volume correction.

Usage

```
scale_amp_molar2molal_pvc(fit_result, p_vols, te, tr)
```

Arguments

fit_result	a fit_result object to apply partial volume correction.
p_vols	a numeric vector of partial volumes expressed as percentages. For example, a voxel containing 100% white matter tissue would use : p_vols = c(WM = 100, GM = 0, CSF = 0).
te	the MRS TE.
tr	the MRS TR.

Value

a fit_result object with a rescaled results table.

scale_amp_ratio	<i>Scale fitted amplitudes to a ratio of signal amplitude.</i>
-----------------	--

Description

Scale fitted amplitudes to a ratio of signal amplitude.

Usage

```
scale_amp_ratio(fit_result, name, use_mean_value = FALSE)
```

Arguments

`fit_result` a result object generated from fitting.
`name` the signal name to use as a denominator (usually, "tCr" or "tNAA").
`use_mean_value` scales the result by the mean of the signal when set to TRUE.

Value

a `fit_result` object with a rescaled results table.

scale_amp_ratio_value	<i>Scale fitted amplitudes to a ratio of signal amplitude.</i>
-----------------------	--

Description

Scale fitted amplitudes to a ratio of signal amplitude.

Usage

```
scale_amp_ratio_value(fit_result, value)
```

Arguments

`fit_result` a result object generated from fitting.
`value` the number use as a denominator.

Value

a `fit_result` object with a rescaled results table.

scale_amp_water_ratio *Scale metabolite amplitudes as a ratio to the unsuppressed water amplitude.*

Description

Scale metabolite amplitudes as a ratio to the unsuppressed water amplitude.

Usage

```
scale_amp_water_ratio(fit_result, ref_data, ...)
```

Arguments

fit_result a result object generated from fitting.
ref_data a water reference MRS data object.
... additional arguments to get_td_amp function.

Value

a fit_result object with a rescaled results table.

scale_basis_amp *Scale a basis object by a scalar.*

Description

Scale a basis object by a scalar.

Usage

```
scale_basis_amp(basis, amp)
```

Arguments

basis basis_set object to be scaled.
amp multiplicative factor with length 1.

Value

basis_set object multiplied by the amplitude scale factor.

 scale_basis_from_singlet

Scale a basis-set to be consistent with spant assumptions for water scaling.

Description

For correct water scaling, spant assumes the time-domain amplitude ($t = 0$) for a single proton is 0.5. Internally simulated basis-sets will be correctly scaled, however imported basis-sets should be assumed to be un-scaled and this function should be used. Note that the singlet specified should only contain one resonance, and that any additional signals (eg TSP or residual water) will result in incorrect scaling. Therefore, only simulated basis sets are appropriate for use with this function.

Usage

```
scale_basis_from_singlet(basis, name, protons)
```

Arguments

basis	basis set to be scaled.
name	the name of the singlet to be used as a scaling reference.
protons	the number of MRS visible protons contributing to the singlet resonance.

Value

a scaled basis.

scale_mrs_amp

Scale an mrs_data object by a scalar or vector or amplitudes.

Description

Scale an mrs_data object by a scalar or vector or amplitudes.

Usage

```
scale_mrs_amp(mrs_data, amp)
```

Arguments

mrs_data	data to be scaled.
amp	multiplicative factor, must have length equal to 1 or Nspec(mrs_data).

Value

mrs_data object multiplied by the amplitude scale factor.

scale_spec	<i>Scale mrs_data to a spectral region.</i>
------------	---

Description

Scale mrs_data to a spectral region.

Usage

```
scale_spec(
  mrs_data,
  xlim = NULL,
  operator = "sum",
  freq_scale = "ppm",
  mode = "re",
  mean_dyns = NULL,
  ret_scale_factor = FALSE
)
```

Arguments

mrs_data	MRS data.
xlim	spectral range to be integrated (defaults to full range).
operator	can be "sum" (default), "mean", "l2", "max", "min" or "max-min".
freq_scale	units of xlim, can be : "ppm", "Hz" or "points".
mode	spectral mode, can be : "re", "im", "mod" or "cplx".
mean_dyns	mean the dynamic scans before applying the operator. The same scaling value will be applied to each individual dynamic.
ret_scale_factor	option to return the scaling factor in addition to the scaled data.

Value

normalised data.

sd	<i>Calculate the standard deviation spectrum from an mrs_data object.</i>
----	---

Description

Calculate the standard deviation spectrum from an mrs_data object.

Usage

```
sd(x, na.rm)
```


Arguments

x object of class `mrs_data`.
na.rm remove NA values.

Value

sd `mrs_data` object.

sd.mrs_data *Calculate the standard deviation spectrum from an mrs_data object.*

Description

Calculate the standard deviation spectrum from an `mrs_data` object.

Usage

```
## S3 method for class 'mrs_data'
sd(x, na.rm = FALSE)
```

Arguments

x object of class `mrs_data`.
na.rm remove NA values.

Value

sd `mrs_data` object.

seconds *Return a time scale vector to match the FID of an MRS data object.*

Description

Return a time scale vector to match the FID of an MRS data object.

Usage

```
seconds(mrs_data)
```

Arguments

mrs_data MRS data.

Value

time scale vector in units of seconds.

segment_t1_fsl	<i>Segment T1 weighted MRI data using FSL FAST and write to file. Runs deface and bet as preprocessing steps by default.</i>
----------------	--

Description

This function requires a working installation of FSL and uses the fslr package. You may need to specify the fsl install directory, eg: 'options(fsl.path = "/path/to/fsl")'

Usage

```
segment_t1_fsl(mri_path, deface = TRUE, bet_fit = 0.5)
```

Arguments

mri_path	path to the volumetric T1 data.
deface	deface the input T1 data before analysis. Defaults to TRUE.
bet_fit	fractional intensity threshold for bet brain extraction. Values should be between 0 and 1. Defaults to 0.5 with smaller values giving larger brain estimates.

seq_cpmg_ideal	<i>CPMG style sequence with ideal pulses.</i>
----------------	---

Description

CPMG style sequence with ideal pulses.

Usage

```
seq_cpmg_ideal(spin_params, ft, ref, TE = 0.03, echoes = 4)
```

Arguments

spin_params	spin system definition.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
TE	echo time in seconds.
echoes	number of echoes.

Value

list of resonance amplitudes and frequencies.

seq_mega_press_ideal *MEGA-PRESS sequence with ideal localisation pulses and Gaussian shaped editing pulse.*

Description

MEGA-PRESS sequence with ideal localisation pulses and Gaussian shaped editing pulse.

Usage

```
seq_mega_press_ideal(  
  spin_params,  
  ft,  
  ref,  
  ed_freq = 1.89,  
  TE1 = 0.015,  
  TE2 = 0.053,  
  BW = 110,  
  steps = 50  
)
```

Arguments

spin_params	spin system definition.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
ed_freq	editing pulse frequency in ppm.
TE1	TE1 sequence parameter in seconds (TE=TE1+TE2).
TE2	TE2 sequence parameter in seconds.
BW	editing pulse bandwidth in Hz.
steps	number of hard pulses used to approximate the editing pulse.

Value

list of resonance amplitudes and frequencies.

seq_press_2d_shaped *PRESS sequence with shaped refocusing pulses.*

Description

PRESS sequence with shaped refocusing pulses.

Usage

```
seq_press_2d_shaped(
  spin_params,
  ft,
  ref,
  TE1 = 0.01,
  TE2 = 0.02,
  pulse_file,
  pulse_dur,
  pulse_file_format,
  refoc_flip_angle = 180,
  xy_pulse_ppm = NULL,
  resamp = TRUE,
  fs_resamp = 1e-04
)
```

Arguments

spin_params	spin system definition.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
TE1	TE1 sequence parameter in seconds (TE=TE1+TE2).
TE2	TE2 sequence parameter in seconds.
pulse_file	path to refocusing pulse file.
pulse_dur	refocusing pulse duration.
pulse_file_format	file format for the refocusing pulse.
refoc_flip_angle	refocusing pulse flip angle in degrees (defaults to 180).
xy_pulse_ppm	a vector of ppm values for the offset of each sub-simulation.
resamp	option to resample the pulse shape.
fs_resamp	sampling frequency (Hz) to resample.

Value

list of resonance amplitudes and frequencies.

seq_press_ideal *PRESS sequence with ideal pulses.*

Description

PRESS sequence with ideal pulses.

Usage

```
seq_press_ideal(spin_params, ft, ref, TE1 = 0.01, TE2 = 0.02)
```

Arguments

spin_params	spin system definition.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
TE1	TE1 sequence parameter in seconds (TE=TE1+TE2).
TE2	TE2 sequence parameter in seconds.

Value

list of resonance amplitudes and frequencies.

seq_pulse_acquire *Simple pulse and acquire sequence with ideal pulses.*

Description

Simple pulse and acquire sequence with ideal pulses.

Usage

```
seq_pulse_acquire(spin_params, ft, ref, nuc = "1H", acq_delay = 0)
```

Arguments

spin_params	spin system definition.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
nuc	acquisition nucleus.
acq_delay	delay between excitation and acquisition.

Value

list of resonance amplitudes and frequencies.

seq_slaser_ideal *sLASER sequence with ideal pulses.*

Description

sLASER sequence with ideal pulses.

Usage

```
seq_slaser_ideal(spin_params, ft, ref, TE1 = 0.008, TE2 = 0.011, TE3 = 0.009)
```

Arguments

spin_params	spin system definition.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
TE1	first echo time (between exc. and 1st echo) in seconds.
TE2	second echo time (between 2nd echo and 4th echo) in seconds.
TE3	third echo time (between 4th echo and 5th echo) in seconds.

Value

list of resonance amplitudes and frequencies.

seq_spin_echo_ideal *Spin echo sequence with ideal pulses.*

Description

Spin echo sequence with ideal pulses.

Usage

```
seq_spin_echo_ideal(spin_params, ft, ref, nuc = "1H", TE = 0.03)
```

Arguments

spin_params	spin system definition.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
nuc	acquisition nucleus.
TE	echo time in seconds.

Value

list of resonance amplitudes and frequencies.

seq_steam_ideal	<i>STEAM sequence with ideal pulses.</i>
-----------------	--

Description

STEAM sequence with ideal pulses.

Usage

```
seq_steam_ideal(spin_params, ft, ref, TE = 0.03, TM = 0.02, amp_scale = 2)
```

Arguments

spin_params	spin system definition.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
TE	sequence parameter in seconds.
TM	sequence parameter in seconds.
amp_scale	amplitude scaling factor. Set to 2 (default) to ensure correct scaling for water reference scaling. Set to 1 to maintain the inherent loss of signal associated with STEAM.

Value

list of resonance amplitudes and frequencies.

seq_steam_ideal_cof	<i>STEAM sequence with ideal pulses and coherence order filtering to simulate gradient crushers.</i>
---------------------	--

Description

See Landheer et al NMR Biomed 2021 34(5):e4129 and Landheer et al MRM 2019 Apr;81(4):2209-2222 for more details on the coherence order filtering method.

Usage

```
seq_steam_ideal_cof(spin_params, ft, ref, TE = 0.03, TM = 0.02, amp_scale = 2)
```

Arguments

spin_params	spin system definition.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
TE	sequence parameter in seconds.
TM	sequence parameter in seconds.
amp_scale	amplitude scaling factor. Set to 2 (default) to ensure correct scaling for water reference scaling. Set to 1 to maintain the inherent loss of signal associated with STEAM.

Value

list of resonance amplitudes and frequencies.

seq_steam_ideal_young *STEAM sequence with ideal pulses using the z-rotation gradient simulation method described by Young et al JMR 140, 146-152 (1999).*

Description

STEAM sequence with ideal pulses using the z-rotation gradient simulation method described by Young et al JMR 140, 146-152 (1999).

Usage

```
seq_steam_ideal_young(
  spin_params,
  ft,
  ref,
  TE = 0.03,
  TM = 0.02,
  amp_scale = 2
)
```

Arguments

spin_params	spin system definition.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
TE	sequence parameter in seconds.
TM	sequence parameter in seconds.
amp_scale	amplitude scaling factor. Set to 2 (default) to ensure correct scaling for water reference scaling. Set to 1 to maintain the inherent loss of signal associated with STEAM.

Value

list of resonance amplitudes and frequencies.

set_def_acq_paras *Set the default acquisition parameters.*

Description

Set the default acquisition parameters.

Usage

```
set_def_acq_paras(  
  ft = getOption("spant.def_ft"),  
  fs = getOption("spant.def_fs"),  
  N = getOption("spant.def_N"),  
  ref = getOption("spant.def_ref"),  
  nuc = getOption("spant.nuc")  
)
```

Arguments

ft	transmitter frequency in Hz.
fs	sampling frequency in Hz.
N	number of data points in the spectral dimension.
ref	reference value for ppm scale.
nuc	resonant nucleus.

set_lcm_cmd *Set the command to run the LCModel command-line program.*

Description

Set the command to run the LCModel command-line program.

Usage

```
set_lcm_cmd(cmd)
```

Arguments

cmd	path to binary.
-----	-----------------

set_lw	<i>Apply line-broadening to an mrs_data object to achieve a specified linewidth.</i>
--------	--

Description

Apply line-broadening to an mrs_data object to achieve a specified linewidth.

Usage

```
set_lw(mrs_data, lw, xlim = c(4, 0.5), lg = 1, mask_narrow = TRUE)
```

Arguments

mrs_data	data in.
lw	target linewidth in units of ppm.
xlim	region to search for peaks to obtain a linewidth estimate.
lg	Lorentz-Gauss lineshape parameter.
mask_narrow	masks spectra where the requested linewidth is too narrow, if set FALSE the spectra are not changed.

Value

line-broadened data.

set_mask_xy_mat	<i>Set the masked voxels in a 2D MRSI dataset to given spectrum.</i>
-----------------	--

Description

Set the masked voxels in a 2D MRSI dataset to given spectrum.

Usage

```
set_mask_xy_mat(mrs_data, mask, mask_mrs_data)
```

Arguments

mrs_data	MRSI data object.
mask	matrix of boolean values specifying the voxels to set, where a value of TRUE indicates the voxel should be set to mask_mrs_data.
mask_mrs_data	the spectral data to be assigned to the masked voxels.

Value

updated dataset.

set_Ntrans	<i>Set the number of transients for an mrs_data object.</i>
------------	---

Description

Set the number of transients for an mrs_data object.

Usage

```
set_Ntrans(mrs_data, n_trans)
```

Arguments

mrs_data	MRS data.
n_trans	number of acquired transients.

set_precomp_mode	<i>Set the precompute mode.</i>
------------------	---------------------------------

Description

Set the precompute mode.

Usage

```
set_precomp_mode(mode = NA)
```

Arguments

mode	can be one of: "default", "overwrite", "clean" or "disabled".
------	---

set_precomp_verbose	<i>Set the verbosity of the precompute function.</i>
---------------------	--

Description

Set the verbosity of the precompute function.

Usage

```
set_precomp_verbose(verbose = NA)
```

Arguments

verbose	can be TRUE or FALSE.
---------	-----------------------

set_ref	<i>Set the ppm reference value (eg ppm value at 0Hz).</i>
---------	---

Description

Set the ppm reference value (eg ppm value at 0Hz).

Usage

```
set_ref(mrs_data, ref)
```

Arguments

mrs_data	MRS data.
ref	reference value for ppm scale.

set_td_pts	<i>Set the number of time-domain data points, truncating or zero-filling as appropriate.</i>
------------	--

Description

Set the number of time-domain data points, truncating or zero-filling as appropriate.

Usage

```
set_td_pts(mrs_data, pts)
```

Arguments

mrs_data	MRS data.
pts	number of data points.

Value

MRS data with pts data points.

set_tqn_cmd	<i>Set the command to run the TARQUIN command-line program.</i>
-------------	---

Description

Set the command to run the TARQUIN command-line program.

Usage

```
set_tqn_cmd(cmd)
```

Arguments

cmd	path to binary.
-----	-----------------

set_tr	<i>Set the repetition time of an MRS dataset.</i>
--------	---

Description

Set the repetition time of an MRS dataset.

Usage

```
set_tr(mrs_data, tr)
```

Arguments

mrs_data	MRS data.
tr	repetition time in seconds.

Value

updated mrs_data set.

shift	<i>Apply a frequency shift to MRS data.</i>
-------	---

Description

Apply a frequency shift to MRS data.

Usage

```
shift(mrs_data, shift, units = "ppm")
```

Arguments

mrs_data	MRS data.
shift	frequency shift (in ppm by default).
units	of the shift ("ppm" or "hz").

Value

frequency shifted MRS data.

shift_basis	<i>Apply frequency shifts to basis set signals.</i>
-------------	---

Description

Apply frequency shifts to basis set signals.

Usage

```
shift_basis(basis, shifts)
```

Arguments

basis	the basis to apply the shift to.
shifts	a vector of frequency shifts to apply in ppm units. Must be the same length as there are basis elements, or one value to be applied to all elements.

Value

modified basis set object.

sim_basis	<i>Simulate a basis set object.</i>
-----------	-------------------------------------

Description

Simulate a basis set object.

Usage

```
sim_basis(  
  mol_list,  
  pul_seq = seq_pulse_acquire,  
  acq paras = def_acq_paras(),  
  xlim = NULL,  
  auto_scale = FALSE,  
  use_basis_cache = FALSE,  
  verbose = FALSE,  
  ...  
)
```

Arguments

mol_list	list of mol_parameter objects. Alternatively, a character vector matching molecules may also be provided. Use the get_mol_names function for a full list of molecules.
pul_seq	pulse sequence function to use.
acq_paras	list of acquisition parameters or an mrs_data object. See def_acq_paras
xlim	ppm range limiting signals to be simulated.
auto_scale	scale the basis based on the intensity of a singlet resonance. Needed for sequences with spatial simulation.
use_basis_cache	create and use a cache of simulated basis sets stored in the "spant_basis_cache" folder in the users home directory. Defaults to FALSE.
verbose	output simulation progress and timings.
...	extra parameters to pass to the pulse sequence function.

Value

basis object.

sim_basis_1h_brain	<i>Simulate a basis-set suitable for 1H brain MRS analysis acquired with a PRESS sequence. Note, ideal pulses are assumed.</i>
--------------------	--

Description

Simulate a basis-set suitable for 1H brain MRS analysis acquired with a PRESS sequence. Note, ideal pulses are assumed.

Usage

```
sim_basis_1h_brain(  
  pul_seq = seq_press_ideal,  
  acq_paras = def_acq_paras(),  
  xlim = c(0.5, 4.2),  
  lcm_compat = FALSE,  
  ...  
)
```

Arguments

pul_seq	pulse sequence function to use.
acq_paras	list of acquisition parameters or an mrs_data object. See def_acq_paras .
xlim	range of frequencies to simulate in ppm.
lcm_compat	exclude lipid and MM signals for use with default LCModel options.
...	extra parameters to pass to the pulse sequence function.

Value

basis object.

sim_basis_1h_brain_press	<i>Simulate a basis-set suitable for 1H brain MRS analysis acquired with a PRESS sequence. Note, ideal pulses are assumed.</i>
--------------------------	--

Description

Simulate a basis-set suitable for 1H brain MRS analysis acquired with a PRESS sequence. Note, ideal pulses are assumed.

Usage

```
sim_basis_1h_brain_press(
  acq paras = def_acq paras(),
  xlim = c(0.5, 4.2),
  lcm_compat = FALSE,
  TE1 = 0.01,
  TE2 = 0.02
)
```

Arguments

acq_paras	list of acquisition parameters or an mrs_data object. See def_acq_paras
xlim	range of frequencies to simulate in ppm.
lcm_compat	exclude lipid and MM signals for use with default LCModel options.
TE1	TE1 of PRESS sequence (TE = TE1 + TE2).
TE2	TE2 of PRESS sequence.

Value

basis object.

sim_basis_mm_lip_lcm *Simulate a macromolecular and lipid basis-set suitable for 1H brain MRS analysis.*

Description

Simulate a macromolecular and lipid basis-set suitable for 1H brain MRS analysis.

Usage

```
sim_basis_mm_lip_lcm(acq paras = def_acq paras())
```

Arguments

acq_paras	list of acquisition parameters or an mrs_data object. See def_acq_paras
-----------	---

Value

basis object.

sim_basis_tqn	<i>Simulate a basis file using TARQUIN.</i>
---------------	---

Description

Simulate a basis file using TARQUIN.

Usage

```
sim_basis_tqn(  
  fs = def_fs(),  
  ft = def_ft(),  
  N = def_N(),  
  ref = def_ref(),  
  opts = NULL  
)
```

Arguments

fs	sampling frequency
ft	transmitter frequency
N	number of data points
ref	chemical shift reference
opts	list of options to pass to TARQUIN.

Examples

```
## Not run:  
write_basis_tqn('test.basis',mrs_data,c("--echo","0.04"))  
  
## End(Not run)
```

sim_brain_1h	<i>Simulate MRS data with a similar appearance to normal brain (by default).</i>
--------------	--

Description

Simulate MRS data with a similar appearance to normal brain (by default).

Usage

```

sim_brain_1h(
  acq_params = def_acq_params(),
  type = "normal_v2",
  pul_seq = seq_slaser_ideal,
  xlim = c(0.5, 4.2),
  full_output = FALSE,
  amps = NULL,
  basis_lb = NULL,
  zero_lip_mm = FALSE,
  remove_lip_mm = FALSE,
  ...
)

```

Arguments

acq_params	list of acquisition parameters or an <code>mrs_data</code> object. See def_acq_params .
type	type of spectrum, only "normal" is implemented currently.
pul_seq	pulse sequence function to use.
xlim	range of frequencies to simulate in ppm.
full_output	when FALSE (default) only output the simulated MRS data. When TRUE output a list containing the MRS data, basis set object and corresponding amplitudes.
amps	a vector of basis amplitudes may be specified to modify the output spectrum.
basis_lb	apply additional Gaussian line-broadening to the basis (Hz).
zero_lip_mm	zero the amplitudes of any lipid or macromolecular components based on their name starting with "MM" or "Lip".
remove_lip_mm	remove any lipid or macromolecular basis components based on their name starting with "MM" or "Lip".
...	extra parameters to pass to the pulse sequence function.

Value

see `full_output` option.

sim_mol

Simulate a mol_parameter object.

Description

Simulate a `mol_parameter` object.

Usage

```

sim_mol(
  mol,
  pul_seq = seq_pulse_acquire,
  ft = def_ft(),
  ref = def_ref(),
  fs = def_fs(),
  N = def_N(),
  xlim = NULL,
  ...
)

```

Arguments

mol	mol_parameter object.
pul_seq	pulse sequence function to use.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
fs	sampling frequency in Hz.
N	number of data points in the spectral dimension.
xlim	ppm range limiting signals to be simulated.
...	extra parameters to pass to the pulse sequence function.

Value

mrs_data object.

sim_noise	<i>Simulate an mrs_data object containing simulated Gaussian noise.</i>
-----------	---

Description

Simulate an mrs_data object containing simulated Gaussian noise.

Usage

```

sim_noise(
  sd = 0.1,
  fs = def_fs(),
  ft = def_ft(),
  N = def_N(),
  ref = def_ref(),
  nuc = def_nuc(),
  dyns = 1,
  fd = TRUE
)

```

Arguments

sd	standard deviation of the noise.
fs	sampling frequency in Hz.
ft	transmitter frequency in Hz.
N	number of data points in the spectral dimension.
ref	reference value for ppm scale.
nuc	resonant nucleus.
dyns	number of dynamic scans to generate.
fd	return data in the frequency-domain (TRUE) or time-domain (FALSE)

Value

mrs_data object.

sim_resonances	<i>Simulate a MRS data object containing a set of simulated resonances.</i>
----------------	---

Description

Simulate a MRS data object containing a set of simulated resonances.

Usage

```
sim_resonances(
  freq = 0,
  amp = 1,
  lw = 0,
  lg = 0,
  phase = 0,
  freq_ppm = TRUE,
  acq_paras = def_acq_paras(),
  fp_scale = TRUE,
  back_extrap_pts = 0,
  sum_resonances = TRUE
)
```

Arguments

freq	resonance frequency.
amp	resonance amplitude.
lw	line width in Hz.
lg	Lorentz-Gauss lineshape parameter (between 0 and 1).
phase	phase in degrees.

freq_ppm	frequencies are given in ppm units if set to TRUE, otherwise Hz are assumed.
acq_paras	list of acquisition parameters. See def_acq_paras
fp_scale	multiply the first data point by 0.5.
back_extrap_pts	number of data points to back extrapolate.
sum_resonances	sum all resonances (default is TRUE), otherwise return a dynamic mrs_data object.

Value

MRS data object.

Examples

```
sim_data <- sim_resonances(freq = 2, lw = 5)
```

sim_th_excit_profile *Simulate an ideal pulse excitation profile by smoothing a top-hat function with a Gaussian.*

Description

Simulate an ideal pulse excitation profile by smoothing a top-hat function with a Gaussian.

Usage

```
sim_th_excit_profile(bw = 1500, sigma = 50, fa = 180)
```

Arguments

bw	top-hat bandwidth (Hz).
sigma	Gaussian width smoothing parameter (Hz).
fa	intended flip angle of the pulse.

Value

data frame containing the frequency scale, excitation profile and corresponding flip-angles.

sim_zero	<i>Simulate an mrs_data object containing complex zero valued samples.</i>
----------	--

Description

Simulate an mrs_data object containing complex zero valued samples.

Usage

```
sim_zero(  
  fs = def_fs(),  
  ft = def_ft(),  
  N = def_N(),  
  ref = def_ref(),  
  nuc = def_nuc(),  
  dyns = 1  
)
```

Arguments

fs	sampling frequency in Hz.
ft	transmitter frequency in Hz.
N	number of data points in the spectral dimension.
ref	reference value for ppm scale.
nuc	resonant nucleus.
dyns	number of dynamic scans to generate.

Value

mrs_data object.

smooth_dyns	<i>Smooth data across the dynamic dimension with a Gaussian kernel.</i>
-------------	---

Description

Smooth data across the dynamic dimension with a Gaussian kernel.

Usage

```
smooth_dyns(mrs_data, sigma)
```

Arguments

mrs_data data to be smoothed.
 sigma standard deviation of the underlying Gaussian kernel in seconds.

Value

smoothed mrs_data object.

sort_basis *Sort the basis-set elements alphabetically.*

Description

Sort the basis-set elements alphabetically.

Usage

```
sort_basis(basis)
```

Arguments

basis input basis.

Value

sorted basis.

spant_abfit_benchmark *Simulate and fit some spectra with ABfit for benchmarking purposes. Basic timing and performance metrics will be printed.*

Description

Simulate and fit some spectra with ABfit for benchmarking purposes. Basic timing and performance metrics will be printed.

Usage

```
spant_abfit_benchmark(noise_reps = 10, return_res = FALSE, opts = abfit_opts())
```

Arguments

noise_reps number of spectra to fit with differing noise samples.
 return_res return a list of fit_result objects.
 opts ABfit options structure.

spant_simulation_benchmark

Simulate a typical metabolite basis set for benchmarking. Timing metrics will be printed on completion.

Description

Simulate a typical metabolite basis set for benchmarking. Timing metrics will be printed on completion.

Usage

```
spant_simulation_benchmark(sim_reps = 10, N = 1024)
```

Arguments

sim_reps	number of times to simulate the basis set.
N	number of FID data points to simulate.

spant_sim_fmrs_dataset

Simulate an example fMRS dataset for a block design fMRS experiment and export a BIDS structure.

Description

Simulate an example fMRS dataset for a block design fMRS experiment and export a BIDS structure.

Usage

```
spant_sim_fmrs_dataset(output_dir = NULL)
```

Arguments

output_dir	output directory for the BIDS data. Defaults to : "HOME/sim_fmrs_dataset/data".
------------	---

spec_decomp	<i>Decompose an mrs_data object into white and gray matter spectra.</i>
-------------	---

Description

An implementation of the method published by Goryawala et al MRM 79(6) 2886-2895 (2018). "Spectral decomposition for resolving partial volume effects in MRSI".

Usage

```
spec_decomp(mrs_data, wm, gm, norm_fractions = TRUE)
```

Arguments

mrs_data	data to be decomposed into white and gray matter spectra.
wm	vector of white matter contributions to each voxel.
gm	vector of gray matter contributions to each voxel.
norm_fractions	option to normalise the wm, gm vectors for each voxel.

Value

a list of two mrs_data objects corresponding to the two tissue types.

spec_op	<i>Perform a mathematical operation on a spectral region.</i>
---------	---

Description

Perform a mathematical operation on a spectral region.

Usage

```
spec_op(  
  mrs_data,  
  xlim = NULL,  
  operator = "sum",  
  freq_scale = "ppm",  
  mode = "re"  
)
```

Arguments

mrs_data	MRS data.
xlim	spectral range to be integrated (defaults to full range).
operator	can be "sum" (default), "mean", "I2", "max", "max_cplx", "min" or "max-min".
freq_scale	units of xlim, can be : "ppm", "hz" or "points".
mode	spectral mode, can be : "re", "im", "mod" or "cplx".

Value

an array of integral values.

spin_sys	<i>Create a spin system object for pulse sequence simulation.</i>
----------	---

Description

Create a spin system object for pulse sequence simulation.

Usage

```
spin_sys(spin_params, ft, ref, precomp_jc_H = NULL, precomp_Iz = NULL)
```

Arguments

spin_params	an object describing the spin system properties.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
precomp_jc_H	use a precomputed J-coupling H matrix to save time.
precomp_Iz	use precomputed Iz matrices to save time.

Value

spin system object.

spm_pve2categorical	<i>Convert SPM style segmentation files to a single categorical image where the numerical values map as: 0) Other, 1) CSF, 2) GM and 3) WM.</i>
---------------------	---

Description

Convert SPM style segmentation files to a single categorical image where the numerical values map as: 0) Other, 1) CSF, 2) GM and 3) WM.

Usage

```
spm_pve2categorical(fname)
```

Arguments

fname	any of the segmentation files (eg c1_MY_T1.nii).
-------	--

Value

nifti object.

ssp	<i>Signal space projection method for lipid suppression.</i>
-----	--

Description

Signal space projection method as described in: Tsai SY, Lin YR, Lin HY, Lin FH. Reduction of lipid contamination in MR spectroscopy imaging using signal space projection. *Magn Reson Med* 2019 Mar;81(3):1486-1498.

Usage

```
ssp(mrs_data, comps = 5, xlim = c(1.5, 0.8))
```

Arguments

mrs_data	MRS data object.
comps	the number of spatial components to use.
xlim	spectral range (in ppm) covering the lipid signals.

Value

lipid suppressed mrs_data object.

stackplot	<i>Produce a plot with multiple traces.</i>
-----------	---

Description

Produce a plot with multiple traces.

Usage

```
stackplot(x, ...)
```

Arguments

x	object for plotting.
...	arguments to be passed to methods.

stackplot.fit_result	<i>Plot the fitting results of an object of class fit_result with individual basis set components shown.</i>
----------------------	--

Description

Plot the fitting results of an object of class fit_result with individual basis set components shown.

Usage

```
## S3 method for class 'fit_result'  
stackplot(  
  x,  
  xlim = NULL,  
  y_offset = 0,  
  dyn = 1,  
  x_pos = 1,  
  y_pos = 1,  
  z_pos = 1,  
  coil = 1,  
  n = NULL,  
  sub_bl = FALSE,  
  labels = FALSE,  
  label_names = NULL,  
  sig_col = "black",  
  restore_def_par = TRUE,  
  omit_signals = NULL,  
  combine_lipmm = FALSE,  
  combine_metab = FALSE,
```

```

    mar = NULL,
    show_grid = TRUE,
    grid_nx = NULL,
    grid_ny = NA,
    invert_fit = FALSE,
    ...
)

```

Arguments

x	fit_result object.
xlim	the range of values to display on the x-axis, eg xlim = c(4,1).
y_offset	separate basis signals in the y-axis direction by this value.
dyn	the dynamic index to plot.
x_pos	the x index to plot.
y_pos	the y index to plot.
z_pos	the z index to plot.
coil	the coil element number to plot.
n	single index element to plot (overrides other indices when given).
sub_bl	subtract the baseline from the data and fit (logical).
labels	print signal labels at the right side of the plot.
label_names	provide a character vector of signal names to replace the defaults determined from the basis set.
sig_col	colour of individual signal components.
restore_def_par	restore default plotting par values after the plot has been made.
omit_signals	a character vector of basis signal names to be removed from the plot.
combine_lipmm	combine all basis signals with names starting with "Lip" or "MM".
combine_metab	combine all basis signals with names not starting with "Lip" or "MM".
mar	option to adjust the plot margins. See ?par.
show_grid	plot gridlines behind the data (logical). Defaults to TRUE.
grid_nx	number of cells of the grid in x and y direction. When NULL the grid aligns with the tick marks on the corresponding default axis (i.e., tickmarks as computed by axTicks). When NA, no grid lines are drawn in the corresponding direction.
grid_ny	as above.
invert_fit	show the fit result "upside-down"/
...	further arguments to plot method.

stackplot.mrs_data *Stackplot plotting method for objects of class mrs_data.*

Description

Stackplot plotting method for objects of class mrs_data.

Usage

```
## S3 method for class 'mrs_data'
stackplot(
  x,
  xlim = NULL,
  mode = "re",
  x_units = NULL,
  fd = TRUE,
  col = NULL,
  alpha = NULL,
  x_offset = 0,
  y_offset = 0,
  plot_dim = NULL,
  x_pos = NULL,
  y_pos = NULL,
  z_pos = NULL,
  dyn = 1,
  coil = 1,
  bty = NULL,
  labels = NULL,
  lab_cex = 1,
  bl_lty = NULL,
  restore_def_par = TRUE,
  show_grid = NULL,
  grid_nx = NULL,
  grid_ny = NA,
  lwd = NULL,
  vline = NULL,
  vline_lty = 2,
  vline_col = "red",
  mar = NULL,
  ...
)
```

Arguments

x object of class mrs_data.
xlim the range of values to display on the x-axis, eg xlim = c(4,1).

mode	representation of the complex numbers to be plotted, can be one of: "re", "im", "mod" or "arg".
x_units	the units to use for the x-axis, can be one of: "ppm", "hz", "points" or "seconds".
fd	display data in the frequency-domain (default), or time-domain (logical).
col	set the colour of the line, eg col = rgb(1, 0, 0, 0.5).
alpha	set the line transparency, eg alpha = 0.5 is 50% transparency. Overrides any transparency levels set by col.
x_offset	separate plots in the x-axis direction by this value. Default value is 0.
y_offset	separate plots in the y-axis direction by this value.
plot_dim	the dimension to display on the y-axis, can be one of: "dyn", "x", "y", "z", "coil" or NULL. If NULL (the default) all spectra will be collapsed into the dynamic dimension and displayed.
x_pos	the x index to plot.
y_pos	the y index to plot.
z_pos	the z index to plot.
dyn	the dynamic index to plot.
coil	the coil element number to plot.
bty	option to draw a box around the plot. See ?par.
labels	add labels to each data item.
lab_cex	label size.
bl_lty	linetype for the y = 0 baseline trace. A default value NULL results in no baseline being plotted.
restore_def_par	restore default plotting par values after the plot has been made.
show_grid	plot gridlines behind the data (logical). Defaults to TRUE.
grid_nx	number of cells of the grid in x and y direction. When NULL the grid aligns with the tick marks on the corresponding default axis (i.e., tickmarks as computed by axTicks). When NA, no grid lines are drawn in the corresponding direction.
grid_ny	as above.
lwd	plot linewidth.
vline	x-value to draw a vertical line.
vline_lty	linetype for the vertical line.
vline_col	colour for the vertical line.
mar	option to adjust the plot margins. See ?par.
...	other arguments to pass to the matplot method.

sub_first_dyn	<i>Subtract the first dynamic spectrum from a dynamic series.</i>
---------------	---

Description

Subtract the first dynamic spectrum from a dynamic series.

Usage

```
sub_first_dyn(mrs_data, scale = 1)
```

Arguments

mrs_data	dynamic MRS data.
scale	scale factor for the first spectrum.

Value

subtracted data.

sub_mean_dyns	<i>Subtract the mean dynamic spectrum from a dynamic series.</i>
---------------	--

Description

Subtract the mean dynamic spectrum from a dynamic series.

Usage

```
sub_mean_dyns(mrs_data, scale = 1)
```

Arguments

mrs_data	dynamic MRS data.
scale	scale factor for the mean spectrum.

Value

subtracted data.

sub_median_dyns	<i>Subtract the median dynamic spectrum from a dynamic series.</i>
-----------------	--

Description

Subtract the median dynamic spectrum from a dynamic series.

Usage

```
sub_median_dyns(mrs_data, scale = 1)
```

Arguments

mrs_data	dynamic MRS data.
scale	scale factor for the medium spectrum.

Value

subtracted data.

sum_coils	<i>Calculate the sum across receiver coil elements.</i>
-----------	---

Description

Calculate the sum across receiver coil elements.

Usage

```
sum_coils(mrs_data)
```

Arguments

mrs_data	MRS data split across receiver coil elements.
----------	---

Value

sum across coil elements.

sum_dyns	<i>Calculate the sum of data dynamics.</i>
----------	--

Description

Calculate the sum of data dynamics.

Usage

```
sum_dyns(mrs_data)
```

Arguments

mrs_data dynamic MRS data.

Value

sum of data dynamics.

sum_mrs	<i>Sum two mrs_data objects.</i>
---------	----------------------------------

Description

Sum two mrs_data objects.

Usage

```
sum_mrs(a, b, force = FALSE)
```

Arguments

a first mrs_data object to be summed.
b second mrs_data object to be summed.
force set to TRUE to force mrs_data objects to be summed, even if they are in different time/frequency domains.

Value

a + b

`sum_mrs_list` *Return the sum of a list of mrs_data objects.*

Description

Return the sum of a list of mrs_data objects.

Usage

```
sum_mrs_list(mrs_list)
```

Arguments

`mrs_list` list of mrs_data objects.

Value

sum mrs_data object.

`svs_1h_brain_analysis` *Standard SVS 1H brain analysis pipeline.*

Description

Standard SVS 1H brain analysis pipeline.

Usage

```
svs_1h_brain_analysis(  
  metab,  
  basis = NULL,  
  w_ref = NULL,  
  mri_seg = NULL,  
  mri = NULL,  
  output_dir = NULL,  
  extra = NULL,  
  decimate = NULL,  
  rats_corr = TRUE,  
  ecc = FALSE,  
  comb_dyns = TRUE,  
  hsvd_filt = FALSE,  
  scale_amps = TRUE,  
  te = NULL,  
  tr = NULL,  
  preproc_only = FALSE,  
  method = "ABFIT",  
  opts = NULL  
)
```

Arguments

metab	filepath or mrs_data object containing MRS metabolite data.
basis	basis set object to use for analysis.
w_ref	filepath or mrs_data object containing MRS water reference data.
mri_seg	filepath or nifti object containing segmented MRI data.
mri	filepath or nifti object containing anatomical MRI data.
output_dir	directory path to output fitting results.
extra	data.frame with one row containing additional information to be attached to the fit results table.
decimate	option to decimate the input data by a factor of two. The default value of NULL does not perform decimation unless the spectral width is greater than 20 PPM.
rats_corr	option to perform rats correction, defaults to TRUE.
ecc	option to perform water reference based eddy current correction, defaults to FALSE.
comb_dyns	option to combine dynamic scans, defaults to TRUE.
hsvd_filt	option to apply hsvd water removal, defaults to FALSE.
scale_amps	option to scale metabolite amplitude estimates, defaults to TRUE.
te	metabolite mrs data echo time in seconds.
tr	metabolite mrs data repetition time in seconds.
preproc_only	only perform the preprocessing steps and omit fitting. The preprocessed metabolite data will be returned in this case.
method	analysis method to use, see fit_mrs help.
opts	options to pass to the analysis method.

Value

a fit_result or mrs_data object depending on the preproc_only option.

svs_1h_brain_analysis_dev

Standard SVS 1H brain analysis pipeline.

Description

Note this function is still under development and liable to changes.

Usage

```
svs_1h_brain_analysis_dev(
  metab,
  w_ref = NULL,
  output_dir = NULL,
  basis = NULL,
  p_vols = NULL,
  append_basis = NULL,
  remove_basis = NULL,
  dfp_corr = FALSE,
  omit_bad_dynamics = FALSE,
  te = NULL,
  tr = NULL,
  output_ratio = "tCr",
  ecc = FALSE,
  abfit_opts = NULL,
  verbose = FALSE
)
```

Arguments

metab	filepath or mrs_data object containing MRS metabolite data.
w_ref	filepath or mrs_data object containing MRS water reference data.
output_dir	directory path to output fitting results.
basis	precompiled basis set object to use for analysis.
p_vols	a numeric vector of partial volumes expressed as percentages. Defaults to 100% white matter. A voxel containing 100% gray matter tissue would use : p_vols = c(WM = 0, GM = 100, CSF = 0).
append_basis	names of extra signals to add to the default basis. Eg append_basis = c("peth", "cit"). Cannot be used with precompiled basis sets.
remove_basis	names of signals to remove from the basis. Cannot be used with precompiled basis sets.
dfp_corr	perform dynamic frequency and phase correction using the RATS method.
omit_bad_dynamics	detect and remove bad dynamics.
te	metabolite mrs data echo time in seconds. If not supplied this will be guessed from the metab data file.
tr	metabolite mrs data repetition time in seconds. If not supplied this will be guessed from the metab data file.
output_ratio	optional string to specify a metabolite ratio to output. Defaults to "tCr" and multiple metabolites may be specified for multiple outputs. Set as NULL to omit.
ecc	option to perform water reference based eddy current correction, defaults to FALSE.
abfit_opts	options to pass to ABfit.
verbose	output potentially useful information.

Examples

```

metab <- system.file("extdata", "philips_spar_sdat_WS.SDAT",
                    package = "spant")
w_ref <- system.file("extdata", "philips_spar_sdat_W.SDAT",
                    package = "spant")

## Not run:
fit_result <- svs_1h_brain_analysis(metab, w_ref, "fit_res_dir")

## End(Not run)

```

```
svs_1h_brain_batch_analysis
```

Batch interface to the standard SVS 1H brain analysis pipeline.

Description

Batch interface to the standard SVS 1H brain analysis pipeline.

Usage

```

svs_1h_brain_batch_analysis(
  metab_list,
  w_ref_list = NULL,
  mri_seg_list = NULL,
  mri_list = NULL,
  output_dir_list = NULL,
  extra = NULL,
  ...
)

```

Arguments

<code>metab_list</code>	list of file paths or <code>mrs_data</code> objects containing MRS metabolite data.
<code>w_ref_list</code>	list of file paths or <code>mrs_data</code> objects containing MRS water reference data.
<code>mri_seg_list</code>	list of file paths or <code>nifti</code> objects containing segmented MRI data.
<code>mri_list</code>	list of file paths or <code>nifti</code> objects containing anatomical MRI data.
<code>output_dir_list</code>	list of directory paths to output fitting results.
<code>extra</code>	a data frame with the same number of rows as <code>metab_list</code> , containing additional information to be attached to the fit results table.
<code>...</code>	additional options to be passed to the <code>svs_1h_brain_analysis</code> function.

Value

a list of `fit_result` objects.

sv_res_table	<i>Output a table of fit amplitudes and error estimates for a single-voxel fit.</i>
--------------	---

Description

Output a table of fit amplitudes and error estimates for a single-voxel fit.

Usage

```
sv_res_table(fit_res, format_out = FALSE)
```

Arguments

fit_res	input vector.
format_out	reduce the accuracy of values to aid table formatting.

Value

data.frame of values.

td2fd	<i>Transform time-domain data to the frequency-domain.</i>
-------	--

Description

Transform time-domain data to the frequency-domain.

Usage

```
td2fd(mrs_data)
```

Arguments

mrs_data	MRS data in time-domain representation.
----------	---

Value

MRS data in frequency-domain representation.

tdsr	<i>Time-domain spectral registration.</i>
------	---

Description

An implementation of the method published by Near et al MRM 73:44-50 (2015).

Usage

```
tdsr(mrs_data, ref = NULL, xlim = c(4, 0.5), max_t = 0.2)
```

Arguments

mrs_data	MRS data to be corrected.
ref	optional MRS data to use as a reference, the mean of all dynamics is used if this argument is not supplied.
xlim	optional frequency range to perform optimisation, set to NULL to use the full range.
max_t	truncate the FID when longer than max_t to reduce time taken.

Value

a list containing the corrected data; phase and shift values in units of degrees and Hz respectively.

td_conv_filt	<i>Time-domain convolution based filter.</i>
--------------	--

Description

Time-domain convolution based filter described by: Marion D, Ikura M, Bax A. Improved solvent suppression in one-dimensional and twodimensional NMR spectra by convolution of time-domain data. J Magn Reson 1989;84:425-430.

Usage

```
td_conv_filt(mrs_data, K = 25, ext = 1)
```

Arguments

mrs_data	MRS data to be filtered.
K	window width in data points.
ext	point separation for linear extrapolation.

t_test_spec	<i>Perform a t-test on spectral data points.</i>
-------------	--

Description

Perform a t-test on spectral data points.

Usage

```
t_test_spec(mrs_data, group)
```

Arguments

mrs_data	an mrs_data object with spectra in the dynamic dimension.
group	vector describing the group membership of each dynamic spectrum.

Value

a list of statistical results.

varpro_3_para_opts	<i>Return a list of options for VARPRO based fitting with 3 free parameters.</i>
--------------------	--

Description

Return a list of options for VARPRO based fitting with 3 free parameters.

Usage

```
varpro_3_para_opts(  
  nstart = 20,  
  init_damping = 2,  
  maxiters = 200,  
  max_shift = 5,  
  max_damping = 5,  
  anal_jac = FALSE,  
  bl_smth_pts = 80  
)
```

Arguments

nstart	position in the time-domain to start fitting, units of data points.
init_damping	starting value for the global Gaussian line-broadening term - measured in Hz.
maxiters	maximum number of levmar iterations to perform.
max_shift	maximum global shift allowed, measured in Hz.
max_damping	maximum damping allowed, FWHM measured in Hz.
anal_jac	option to use the analytic or numerical Jacobian (logical).
bl_smth_pts	number of data points to use in the baseline smoothing calculation.

Value

list of options.

varpro_basic_opts *Return a list of options for a basic VARPRO analysis.*

Description

Return a list of options for a basic VARPRO analysis.

Usage

```
varpro_basic_opts(method = "fd_re", nnls = TRUE, ppm_left = 4, ppm_right = 0.2)
```

Arguments

method	one of "td", "fd", "fd_re".
nnls	restrict basis amplitudes to non-negative values.
ppm_left	downfield frequency limit for the fitting range (ppm).
ppm_right	upfield frequency limit for the fitting range (ppm).

Value

full list of options.

varpro_opts *Return a list of options for VARPRO based fitting.*

Description

Return a list of options for VARPRO based fitting.

Usage

```
varpro_opts(  
  nstart = 20,  
  init_g_damping = 2,  
  maxiters = 200,  
  max_shift = 5,  
  max_g_damping = 5,  
  max_ind_damping = 5,  
  anal_jac = TRUE,  
  bl_smth_pts = 80  
)
```

Arguments

nstart	position in the time-domain to start fitting, units of data points.
init_g_damping	starting value for the global Gaussian line-broadening term - measured in Hz.
maxiters	maximum number of levmar iterations to perform.
max_shift	maximum shift allowed to each element in the basis set, measured in Hz.
max_g_damping	maximum permitted global Gaussian line-broadening.
max_ind_damping	maximum permitted Lorentzian line-broadening for each element in the basis set, measured in Hz.
anal_jac	option to use the analytic or numerical Jacobian (logical).
bl_smth_pts	number of data points to use in the baseline smoothing calculation.

Value

list of options.

Examples

```
varpro_opts(nstart = 10)
```

vec2mrs_data	<i>Convert a vector into a mrs_data object.</i>
--------------	---

Description

Convert a vector into a mrs_data object.

Usage

```
vec2mrs_data(  
  vec,  
  mrs_data = NULL,  
  fs = NULL,  
  ft = NULL,  
  ref = NULL,  
  nuc = NULL,  
  dyns = 1,  
  fd = FALSE  
)
```

Arguments

vec	the data vector.
mrs_data	example data to copy acquisition parameters from.
fs	sampling frequency in Hz.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
nuc	resonant nucleus.
dyns	replicate the data across the dynamic dimension.
fd	flag to indicate if the vector is in the frequency domain (logical).

Value

mrs_data object.

write_basis	<i>Write a basis object to an LCMModel .basis formatted file.</i>
-------------	---

Description

Write a basis object to an LCMModel .basis formatted file.

Usage

```
write_basis(basis, basis_file, fwhmba = 0.1)
```

Arguments

basis	basis object to be exported.
basis_file	path to basis file to be generated.
fwhmba	parameter used by LCMModel.

write_basis_tqn	<i>Generate a basis file using TARQUIN.</i>
-----------------	---

Description

Generate a basis file using TARQUIN.

Usage

```
write_basis_tqn(basis_file, metab_data, opts = NULL)
```

Arguments

basis_file	filename of the basis file to be generated.
metab_data	MRS data object to match the generated basis parameters.
opts	list of options to pass to TARQUIN.

Examples

```
## Not run:  
write_basis_tqn('test.basis', mrs_data, c("--echo", "0.04"))  
  
## End(Not run)
```

write_mrs	<i>Write MRS data object to file.</i>
-----------	---------------------------------------

Description

Write MRS data object to file.

Usage

```
write_mrs(mrs_data, fname, format = NULL, force = FALSE)
```

Arguments

mrs_data	object to be written to file, or list of mrs_data objects.
fname	one or more filenames to output.
format	string describing the data format. Must be one of the following : "nifti", "dpt", "lcm_raw", "rds". If not specified, the format will be guessed from the filename extension.
force	set to TRUE to overwrite any existing files.

write_mrs_nifti	<i>Write MRS data object to file in NIFTI format.</i>
-----------------	---

Description

Write MRS data object to file in NIFTI format.

Usage

```
write_mrs_nifti(mrs_data, fname)
```

Arguments

mrs_data	object to be written to file.
fname	the filename of the output NIFTI MRS data.

write_pulse_ascii	<i>Write an ASCII formatted pulse file.</i>
-------------------	---

Description

Write an ASCII formatted pulse file.

Usage

```
write_pulse_ascii(pulse, path)
```

Arguments

pulse	pulse data object.
path	file path for export.

zero_fade_spec	<i>Fade a spectrum to zero by frequency domain multiplication with a tanh function. Note this operation distorts data points at the end of the FID.</i>
----------------	---

Description

Fade a spectrum to zero by frequency domain multiplication with a tanh function. Note this operation distorts data points at the end of the FID.

Usage

```
zero_fade_spec(mrs_data, start_ppm, end_ppm)
```

Arguments

mrs_data	data to be faded.
start_ppm	start point of the fade in ppm units.
end_ppm	end point of the fade in ppm units.

Value

modified mrs_data object.

zero_higher_orders *Zero all coherences including and above a given order.*

Description

Zero all coherences including and above a given order.

Usage

```
zero_higher_orders(sys, rho, order)
```

Arguments

sys	spin system object.
rho	density matrix.
order	states higher than or equal to this argument will be set to zero.

Value

density matrix.

zero_td_pts_end *Set mrs_data object data points at the end of the FID to zero.*

Description

Set mrs_data object data points at the end of the FID to zero.

Usage

```
zero_td_pts_end(mrs_data, pts)
```

Arguments

mrs_data	MRS data.
pts	number of end points to set to zero.

Value

modified mrs_data object.

zf *Zero-fill MRS data in the time domain.*

Description

Zero-fill MRS data in the time domain.

Usage

```
zf(x, factor = 2, offset = 0)

## S3 method for class 'list'
zf(x, factor = 2, offset = 0)

## S3 method for class 'mrs_data'
zf(x, factor = 2, offset = 0)

## S3 method for class 'basis_set'
zf(x, factor = 2, offset = 0)
```

Arguments

x	input mrs_data or basis_set object.
factor	zero-filling factor, factor of 2 returns a dataset with twice the original data points.
offset	number of points from the end of the FID to insert the zero values.

Value

zero-filled data.

zf_xy *Zero-fill MRSI data in the k-space x-y direction.*

Description

Zero-fill MRSI data in the k-space x-y direction.

Usage

```
zf_xy(mrs_data, factor = 2)
```

Arguments

mrs_data	MRSI data.
factor	zero-filling factor, a factor of 2 returns a dataset with twice the original points in the x-y directions. Factors smaller than one are permitted, such that a factor of 0.5 returns half the k-space points in the x-y directions.

Value

zero-filled data.

Index

abfit_opts, [10](#), [14](#)
abfit_opts_v1_9_0, [14](#)
abfit_reg_opts, [15](#)
acquire, [18](#)
add_noise, [19](#)
add_noise_spec_snr, [20](#)
align, [20](#)
apodise_xy, [21](#)
append_basis, [22](#)
append_coils, [22](#)
append_dyns, [23](#)
append_regs, [23](#)
apply_axes, [24](#)
apply_mrs, [24](#)
apply_pulse, [25](#)
Arg.mrs_data, [26](#)
array2mrs_data, [26](#)
auto_phase, [27](#)

back_extrap_ar, [28](#)
basis2dyn_mrs_data, [28](#)
basis2mrs_data, [29](#)
bbase, [30](#)
bc_als, [30](#)
bc_constant, [31](#)
bc_gauss, [31](#)
bc_poly, [32](#)
bc_spline, [32](#)
beta2lw, [33](#)
bin_spec, [33](#)

calc_basis_corr_mat, [34](#)
calc_basis_crlbs, [34](#)
calc_coil_noise_cor, [35](#)
calc_coil_noise_sd, [35](#)
calc_design_efficiency, [36](#)
calc_ed_from_lambda, [36](#)
calc_peak_info_vec, [37](#)
calc_sd_poly, [37](#)
calc_spec_diff, [38](#)

calc_spec_snr, [38](#)
check_lcm, [39](#)
check_tqn, [39](#)
circ_mask, [40](#)
coherence_filter, [40](#)
collapse_to_dyns, [41](#)
comb_coils, [41](#)
comb_coils_mrsi_gls, [42](#)
comb_coils_svs_gls, [43](#)
comb_fit_list_fit_tables, [43](#)
comb_fit_list_result_tables, [44](#)
comb_fit_tables, [45](#)
comb_metab_ref, [45](#)
Conj.mrs_data, [46](#)
conv_mrs, [46](#)
crop_basis, [47](#)
crop_spec, [47](#)
crop_td_pts, [48](#)
crop_td_pts_end, [48](#)
crop_td_pts_pot, [49](#)
crop_xy, [49](#)
crossprod_3d, [50](#)

decimate_mrs_fd, [50](#)
decimate_mrs_td, [51](#)
deconv_mrs, [51](#)
def_acq_paras, [52](#), [176](#), [199–201](#), [203](#), [206](#)
def_fs, [53](#)
def_ft, [53](#)
def_N, [53](#)
def_nuc, [54](#)
def_ref, [54](#)
dicom_reader, [54](#)
diff_mrs, [55](#)
downsample_mrs_fd, [56](#)
downsample_mrs_td, [56](#)
dyn_acq_times, [57](#)

ecc, [57](#)
elliptical_mask, [58](#)

est_noise_sd, 59
 fd2td, 59
 fd_conv_filt, 60
 fd_gauss_smo, 60
 find_bids_mrs, 61
 find_mrs_files, 61
 fit_amps, 62
 fit_diags, 62
 fit_mrs, 63
 fit_res2csv, 64
 fit_svs, 65
 fit_svs_edited, 68
 fit_svs_group_results, 71
 fit_svs_gui, 72
 fit_t1_ti_array, 72
 fit_t1_tr_array, 73
 fit_t2_te_array, 73
 fp_phase, 74
 fp_phase_correct, 75
 fp_scale, 75
 fs, 76
 ft_dyns, 76
 ft_shift, 77
 ft_shift_mat, 77
 gausswin_2d, 78
 gen_baseline_reg, 78
 gen_bold_reg, 79
 gen_conv_reg, 80
 gen_F, 81
 gen_F_xy, 81
 gen_group_reg, 82
 gen_I, 82
 gen_impulse_reg, 83
 gen_poly_reg, 83
 gen_trap_reg, 84
 get_1h_brain_basis_names, 86
 get_1h_brain_basis_params, 86
 get_1h_brain_basis_params_v1, 87
 get_1h_brain_basis_params_v2, 87
 get_1h_brain_basis_params_v3, 88
 get_1h_braino_basis_names, 85
 get_1h_spectre_basis_names, 88
 get_2d_psf, 89
 get_acq_params, 89
 get_basis_subset, 90
 get_dyns, 90
 get_even_dyns, 91
 get_fh_dyns, 91
 get_fit_map, 92
 get_fp, 92
 get_gaussian_pulse, 93
 get_head_dyns, 93
 get_hrf, 94
 get_lcm_cmd, 94
 get_metab, 94
 get_mol_names, 95
 get_mol_params, 95
 get_mrs_affine, 98
 get_mrsi2d_seg, 96
 get_mrsi_voi, 96
 get_mrsi_voxel, 97
 get_mrsi_voxel_xy_psf, 97
 get_odd_dyns, 98
 get_ref, 99
 get_seg_ind, 99
 get_sh_dyns, 100
 get_slice, 100
 get_spin_num, 101
 get_subset, 101
 get_svs_voi, 102
 get_tail_dyns, 103
 get_td_amp, 103
 get_tqn_cmd, 104
 get_uncoupled_mol, 104
 get_voi_cog, 105
 get_voi_seg, 105
 get_voi_seg_psf, 106
 get_voxel, 106
 glm_spec, 107
 glm_spec_fmrs_fl, 107
 glm_spec_fmrs_group, 108
 glm_spec_group_linhyp, 109
 grid_shift_xy, 110
 gridplot, 109
 gridplot.mrs_data, 110
 hsvd, 111
 hsvd_filt, 112
 hsvd_vec, 113
 hz, 113
 ift_shift, 114
 ift_shift_mat, 114
 Im.mrs_data, 115
 image.mrs_data, 115
 img2kspace_xy, 117

Imzap, 117
install_cli, 118
int_spec, 119
interleave_dyns, 118
inv_even_dyns, 119
inv_odd_dyns, 120
is.def, 120
is_fd, 121

kspace2img_xy, 121

l2_reg, 122
lb, 123
lofdc, 123
lw2alpha, 124
lw2beta, 125

make_basis_from_raw, 125
mask_dyns, 126
mask_fit_res, 126
mask_xy, 127
mask_xy_corners, 127
mask_xy_ellipse, 128
mask_xy_mat, 128
mat2mrs_data, 129
matexp, 129
max_mrs, 130
max_mrs_interp, 130
mean.list, 131
mean.mrs_data, 131
mean_dyn_blocks, 132
mean_dyn_pairs, 133
mean_dyns, 132
mean_mrs_list, 133
mean_vec_blocks, 134
median_dyns, 134
Mod.mrs_data, 135
mod_td, 135
mrs_data2basis, 136
mrs_data2bids, 136
mrs_data2mat, 137
mrs_data2spec_mat, 138
mrs_data2vec, 138
mvfftshift, 139
mviffshift, 139

n2coord, 140
Ncoils, 140
Ndyns, 140

nifti_flip_lr, 141
Npts, 141
Nspec, 142
Ntrans, 142
Nx, 142
Ny, 143
Nz, 143

one_page_pdf, 143
ortho3, 144
ortho3_inter, 145

peak_info, 146
pg_extrap_xy, 146
phase, 147
phase_ref_1h_brain, 148
plot.fit_result, 148
plot.mrs_data, 150
plot_bc, 152
plot_reg, 152
plot_slice_fit, 153
plot_slice_fit_inter, 153
plot_slice_map, 154
plot_slice_map_inter, 155
plot_spec_sd, 156
plot_voi_overlay, 156
plot_voi_overlay_seg, 157
ppm, 157
precomp, 158
preproc_svs, 158
preproc_svs_dataset, 159
print.fit_result, 159
print.mrs_data, 160

qn_states, 160

rats, 161
Re.mrs_data, 162
re_weighting, 176
read_basis, 163
read_ima_coil_dir, 163
read_ima_dyn_dir, 164
read_lcm_coord, 164
read_mrs, 165
read_mrs(), 66, 69
read_mrs_tqn, 166
read_pulse_ascii, 167
read_pulse_bruker, 167
read_pulse_pta, 168

read_siemens_txt_hdr, 168
read_tqn_fit, 169
read_tqn_result, 169
recon_imag, 170
recon_imag_vec, 170
recon_twix_2d_mrsi, 171
rectangular_mask, 171
rep_array_dim, 172
rep_dyn, 172
rep_mrs, 173
resample_basis, 173
resample_img, 174
resample_voi, 174
reslice_to_mrs, 175
reson_table2mrs_data, 175
rm_dyns, 176

scale_amp_legacy, 177
scale_amp_molal, 178
scale_amp_molal_pvc, 179
scale_amp_molar, 179
scale_amp_molar2molal_pvc, 180
scale_amp_ratio, 181
scale_amp_ratio_value, 181
scale_amp_water_ratio, 182
scale_basis_amp, 182
scale_basis_from_singlet, 183
scale_mrs_amp, 183
scale_spec, 184
sd, 184
sd.mrs_data, 185
seconds, 185
segment_t1_fsl, 186
seq_cpmg_ideal, 186
seq_mega_press_ideal, 187
seq_press_2d_shaped, 188
seq_press_ideal, 189
seq_pulse_acquire, 189
seq_slaser_ideal, 190
seq_spin_echo_ideal, 190
seq_steam_ideal, 191
seq_steam_ideal_cof, 191
seq_steam_ideal_young, 192
set_def_acq_paras, 193
set_lcm_cmd, 193
set_lw, 194
set_mask_xy_mat, 194
set_Ntrans, 195
set_precomp_mode, 195

set_precomp_verbose, 195
set_ref, 196
set_td_pts, 196
set_tqn_cmd, 197
set_tr, 197
shift, 198
shift_basis, 198
sim_basis, 199
sim_basis_1h_brain, 200
sim_basis_1h_brain_press, 200
sim_basis_mm_lip_lcm, 201
sim_basis_tqn, 202
sim_brain_1h, 202
sim_mol, 203
sim_noise, 204
sim_resonances, 205
sim_th_excit_profile, 206
sim_zero, 207
smooth_dyns, 207
sort_basis, 208
spant (spant-package), 9
spant-package, 9
spant_abfit_benchmark, 208
spant_sim_fmrs_dataset, 209
spant_simulation_benchmark, 209
spec_decomp, 210
spec_op, 210
spin_sys, 211
spm_pve2categorical, 212
ssp, 212
stackplot, 213
stackplot.fit_result, 213
stackplot.mrs_data, 215
sub_first_dyn, 217
sub_mean_dyns, 217
sub_median_dyns, 218
sum_coils, 218
sum_dyns, 219
sum_mrs, 219
sum_mrs_list, 220
sv_res_table, 224
svs_1h_brain_analysis, 220
svs_1h_brain_analysis_dev, 221
svs_1h_brain_batch_analysis, 223

t_test_spec, 227
td2fd, 224
td_conv_filt, 225
tdsr, 225

te, [226](#)

tr, [226](#)

varpro_3_para_opts, [227](#)

varpro_basic_opts, [228](#)

varpro_opts, [229](#)

vec2mrs_data, [230](#)

write_basis, [231](#)

write_basis_tqn, [231](#)

write_mrs, [232](#)

write_mrs_nifti, [232](#)

write_pulse_ascii, [233](#)

zero_fade_spec, [233](#)

zero_higher_orders, [234](#)

zero_td_pts_end, [234](#)

zf, [235](#)

zf_xy, [235](#)